JVC

SERVICE MANUAL

COLOR TELEVISION

AV-27F577/R, AV-27F577/S, AV-32F577/R, AV-32F577/Y, AV-32F577/Z

BASIC CHASSIS
GJ6

I'Art™

DCR DOLBY DIGITAL

TABLE OF CONTENTS

1 PRECAUTION 1-3
2 SPECIFIC SERVICE INSTRUCTIONS 1-4
3 DISASSEMBLY 1-6
4 ADJUSTMENT 1-12
5 TROUBLESHOOTING 1-30

COPYRIGHT © 2006 Victor Company of Japan, Limited

No.YA387
2006/5

SPECIFICATION

Items		Contents	
		AV-27F577	AV-32F577
Dimensions (W × H × D)		75.8 cm × 59.3 cm × 50.0 cm (29-7/8" × 23-3/8" × 19-3/4")	87.7 cm × 69.9 cm × 56.5 cm (34-5/8" × 27-5/8" × 22-1/4")
Mass		43.0 kg (94.6 lbs)	64.0 kg (140.8 lbs)
TV RF System (Analog / Digital)	Analog Digital	CCIR (M) ATSC terrestrial / Digital cable	
Color System (Analog)		NTSC	
Stereo System (Analog)		BTSC (Multi Channel Sound)	
Teletext System (Analog)		Closed caption (T1-T4 / CC1-CC4)	
TV Receiving Channels and Frequency (Analog)	VHF Low VHF High UHF CATV	02ch - 06ch : 54MHz - 88MHz 07ch - 13ch : 174MHz - 216MHz 14ch - 69ch : 470MHz - 806MHz 54MHz - 804MHz Low Band : 02 - 06 High Band : 07 - 13 Mid Band : 14 - 22 Super Band : 23 - 36 Hyper Band : 37 - 64 Ultra Band : 65 - 94, 100 - 135 Sub Mid Band : 01, 96 - 99	
TV / CATV Total Channel		191 Channels	
Intermediate Frequency (Analog)	Video IF Sound IF	45.75 MHz 41.25 MHz (4.5MHz)	
Color Sub Carrier Frequency (Analog)		3.58 MHz	
Power Input		AC120 V, 60 Hz	
Power Consumption		140 W	160 W
Picture Tube (Visible size)		67.6 cm (27") Measured diagonally (H: 55.4 cm × V: 41.8 cm)	82.2 cm (32") Measured diagonally (H: 65.6 cm × V : 49.6 cm)
High Voltage		30.0 kV ±1.3 kV [at Zero beam current]	31.4 kV ±1.3 kV [at Zero beam current]
Speaker		5 cm × 12 cm (2" × 4-3/4"), Oval type × 2	
Audio Power Output		5 W + 5 W	
Antenna Terminal (VHF / UHF)		F-type connector, 75 Ω unbalanced	
Video / Audio input [Input-1/2/3]	Component Video [Input-2] S-video [Input-1] Video Audio	RCA pin jack × 3 Y : 1V(p-p), 75 Ω, negative sync Pb/Pr : 0.7 V(p-p), 75 Ω Mini DIN 4-pin connector × 1 Y : 1 V(p-p), 75 Ω, negative sync C : 0.286 V(p-p)(burst signal), 75 Ω 1 V(p-p), 75 Ω, negative sync, RCA pin jack × 2 500 mV(rms)(-4dBs), high impedance, RCA pin jack × 6	
Audio Output (Fix)		500 mV(rms)(-4dBs), low Impedance, (400 Hz when modulated 100 %), RCA pin jack × 2	
Digital Audio Optical Output		Digital SPDIF × 1	
Remote Control Unit		RM-C1290G (AA/R6/UM-3 battery × 2)	

Design & specifications are subject to change without notice.

SECTION 1
PRECAUTION

1.1 SAFETY PRECAUTIONS

(1) The design of this product contains special hardware, many circuits and components specially for safety purposes. For continued protection, no changes should be made to the original design unless authorized in writing by the manufacturer. Replacement parts must be identical to those used in the original circuits. Service should be performed by qualified personnel only.

(2) Alterations of the design or circuitry of the products should not be made. Any design alterations or additions will void the manufacturer's warranty and will further relieve the manufacturer of responsibility for personal injury or property damage resulting therefrom.

(3) Many electrical and mechanical parts in the products have special safety-related characteristics. These characteristics are often not evident from visual inspection nor can the protection afforded by them necessarily be obtained by using replacement components rated for higher voltage, wattage, etc. Replacement parts which have these special safety characteristics are identified in the parts list of Service manual. **Electrical components having such features are identified by shading on the schematics and by (⚠) on the parts list in Service manual**. The use of a substitute replacement which does not have the same safety characteristics as the recommended replacement part shown in the parts list of Service manual may cause shock, fire, or other hazards.

(4) **Use isolation transformer when hot chassis.**
The chassis and any sub-chassis contained in some products are connected to one side of the AC power line. An isolation transformer of adequate capacity should be inserted between the product and the AC power supply point while performing any service on some products when the HOT chassis is exposed.

(5) **Don't short between the LIVE side ground and ISOLATED (NEUTRAL) side ground or EARTH side ground when repairing.**
Some model's power circuit is partly different in the GND. The difference of the GND is shown by the LIVE : (⊥) side GND, the ISOLATED (NEUTRAL) : (⏚) side GND and EARTH : (⏚) side GND.
Don't short between the LIVE side GND and ISOLATED (NEUTRAL) side GND or EARTH side GND and never measure the LIVE side GND and ISOLATED (NEUTRAL) side GND or EARTH side GND at the same time with a measuring apparatus (oscilloscope etc.). If above note will not be kept, a fuse or any parts will be broken.

(6) If any repair has been made to the chassis, it is recommended that the B1 setting should be checked or adjusted (See B1 POWER SUPPLY check).

(7) The high voltage applied to the picture tube must conform with that specified in Service manual. Excessive high voltage can cause an increase in X-Ray emission, arcing and possible component damage, therefore operation under excessive high voltage conditions should be kept to a minimum, or should be prevented. If severe arcing occurs, remove the AC power immediately and determine the cause by visual inspection (incorrect installation, cracked or melted high voltage harness, poor soldering, etc.). To maintain the proper minimum level of soft X-Ray emission, components in the high voltage circuitry including the picture tube must be the exact replacements or alternatives approved by the manufacturer of the complete product.

(8) Do not check high voltage by drawing an arc. Use a high voltage meter or a high voltage probe with a VTVM. Discharge the picture tube before attempting meter connection, by connecting a clip lead to the ground frame and connecting the other end of the lead through a 10kΩ 2W resistor to the anode button.

(9) When service is required, observe the original lead dress. Extra precaution should be given to assure correct lead dress in the high voltage circuit area. Where a short circuit has occurred, those components that indicate evidence of overheating should be replaced. Always use the manufacturer's replacement components.

(10) **Isolation Check (Safety for Electrical Shock Hazard)**
After re-assembling the product, always perform an isolation check on the exposed metal parts of the cabinet (antenna terminals, video/audio input and output terminals, Control knobs, metal cabinet, screw heads, earphone jack, control shafts, etc.) to be sure the product is safe to operate without danger of electrical shock.

a) **Dielectric Strength Test**
The isolation between the AC primary circuit and all metal parts exposed to the user, particularly any exposed metal part having a return path to the chassis should withstand a voltage of 1100V AC (r.m.s.) for a period of one second.
(. . . . Withstand a voltage of 1100V AC (r.m.s.) to an appliance rated up to 120V, and 3000V AC (r.m.s.) to an appliance rated 200V or more, for a period of one second.) This method of test requires a test equipment not generally found in the service trade.

b) **Leakage Current Check**
Plug the AC line cord directly into the AC outlet (do not use a line isolation transformer during this check.). Using a "Leakage Current Tester", measure the leakage current from each exposed metal part of the cabinet, particularly any exposed metal part having a return path to the chassis, to a known good earth ground (water pipe, etc.). Any leakage current must not exceed 0.5mA AC (r.m.s.).
However, in tropical area, this must not exceed 0.2mA AC (r.m.s.).

Alternate Check Method
Plug the AC line cord directly into the AC outlet (do not use a line isolation transformer during this check.). Use an AC voltmeter having 1000Ω per volt or more sensitivity in the following manner. Connect a 1500Ω 10W resistor paralleled by a 0.15μF AC-type capacitor between an exposed metal part and a known good earth ground (water pipe, etc.). Measure the AC voltage across the resistor with the AC voltmeter. Move the resistor connection to each exposed metal part, particularly any exposed metal part having a return path to the chassis, and measure the AC voltage across the resistor. Now, reverse the plug in the AC outlet and repeat each measurement. Any voltage measured must not exceed 0.75V AC (r.m.s.). This corresponds to 0.5mA AC (r.m.s.).
However, in tropical area, this must not exceed 0.3V AC (r.m.s.). This corresponds to 0.2mA AC (r.m.s.).



(11) **High voltage hold down circuit check.**
After repair of the high voltage hold down circuit, this circuit shall be checked to operate correctly.See item **"How to check the high voltage hold down circuit"**.





SECTION 2
SPECIFIC SERVICE INSTRUCTIONS

2.1 FEATURES

Built in ATSC (Advanced Television Systems Committee) TUNER

This TV can receive Digital broadcasting (ATSC), Digital cable and Analogue broadcasting.

SMART CAPTION

Smart caption will appear when you press the MUTING button, only on channels where the broadcast contains CLOSED CAPTION information.

SMART SOUND

Decreases high sound levels, giving a regulated sound level.

FLAT SQUARE CRT

It became legible from any position by CRT with few reflection and reflect lumps on the flat screen.

DIGITAL COMB FILTER

By the 3D digital comb filter, the refreshed image can be seen.

VIDEO STATUS

Expression of a favorite screen can be chosen by the VIDEO STATUS function.

COMPONENT INPUT

Since the component signal input terminal is equipped, it reappears direct without deteriorating the signal from DVD.

V-CHIP

Since the V-CHIP is built in, it can choose, view and listen to a healthy program.

MTS STEREO

The voice multiplex function of the MTS system is built in. (MTS = Multi channel Television Sound system)

RETURN PLUS

You program a specific channel to return to while scanning through the channels using the CH+ and CH - keys.

VIDEO INPUT LABEL

This function is used to label video input connections for the onscreen displays.

A.H.S.

A.H.S. adds a more spacious surround sound. Music gives basic effect and movie for more effect.

2.2 MAIN DIFFERENCE LIST

Item	AV-27F577/R	AV-27F577/S	AV-32F577/R	AV-32F577/Y	AV-32F577/Z
PICTURE TUBE (ITC)	A68ELH021X201	A68QCP693X003	A80ALB20X09	A80AKS90X03	A80ERF182X17L
MAIN PWB	SGJ-1308A-M2	SGJ-1302A-M2	SGJ-1313A-M2	SGJ-1301A-M2	SGJ-1307A-M2
CRT SOCKET PWB	SGJ-3304A-M2	SGJ-3302A-M2	SGJ-3305A-M2	SGJ-3301A-M2	SGJ-3303A-M2
L/F PWB	SGJ-9302A-M2	←	SGJ-9301A-M2	←	←

2.3 HOW TO IDENTIFY MODELS

How to recognize from the appearance of the model concerned is written below. Please distinguish from several contents currently printed on the rating label



2.4 TECHNICAL INFORMATION

2.4.1 MAIN MI-COM (CPU) PIN FUNCTION

Pin No.	Pin name	I/O	Function	Pin No.	Pin name	I/O	Function
1	M_MUTE	O	Fixed output muting [Muting : H]	29	YC_GND	-	GND
2	KEY1	I	Front key scan voltage (CH+ / VOL+ / VOL-)	30	V1_IN	I	Not used
3	KEY2	I	Front key scan voltage (CH- / MENU/POWER)	31	ABCL	I	Current for automatic beam (brightness)/contrast limit
4	uP_DVss	-	GND	32	MONITOR_OUT	O	Not used
5	Reset	I	CPU reset [Reset: L]	33	BLACK_DET	-	Black level detection filter
6	8MHz_OUT	O	CPU system clock: 8MHz oscillation	34	SVM_OUT	O	Y signal for scan velocity scan modulation
7	8MHz_IN	I	CPU system clock: 8MHz oscillation	35	APL_FIL	-	Average picture level filter
8	TEST	-	GND	36	APC_FIL	-	Automatic phase control filter
9	uP_DVDD	I	5V	37	fsc_OUT	O	Not used
10	TU_RESET	O	Reset for digital tuner module [Reset : H]	38	YC_Vcc	I	5V (for video process circuit)
11	uP_VVSS	-	GND	39	R_OUT	O	R signal for CRT output
12	TV_HGND	-	GND	40	G_OUT	O	G signal for CRT output
13	FBP_SCP	I	Flyback pulse (H. pulse)	41	B_OUT	O	B signal for CRT output
14	HOUT	O	H. drive (oscillation)	42	RGB_Vcc	I	9V (for RGB process circuit)
15	H_Vcc	I	9V (for H. oscillation start)	43	IK_IN	I	Not used
16	HAFC_1	-	H. AFC filter	44	TV_DGND	-	GND
17	Vsaw	-	V. saw filter	45	uP_AGND	-	GND
18	VOUT	O	V. drive	46	uP_AVdd	-	5V
19	EW_OUT	O	Parabola waveform (for sidepin correection)	47	MAIN_POWER	O	Power on/off switching control [Powen on: L]
20	X-RAY	I	Not used: X-ray detection (for protection) [Detection : H]	48	DTVM_REQ	I	Read request from DTV micom [Request : H]
21	Ys	I	Not used	49	SDA1	I/O	Data for Inter IC control bus (for DTV micom)
22	Cb_IN	I	Cb (external) signal	50	SCL1	O	Clock for Inter IC control bus (for DTV micom)
23	Y_IN	I	Y (external) signal	51	SDA0	I/O	Data for Inter IC control bus (for main memory)
24	Cr_IN	I	Cr (external) signal	52	A_MUTING	O	Audio output muting [Muting : H]
25	TV_DVcc	I	3.3V	53	SCL0	O	Clock for Inter IC control bus (for main memory)
26	V3IN/CIN	I	Not used	54	AC_IN	I	AC 50/60Hz input for timer clock
27	EHT_IN	I	HV change control	55	REMOCON	I	Remote control sensor input [No input : H]
28	V2_IN/Y_IN	I	Not used	56	LED	O	POWER / ON TIMER LED Indication [lighting : L]

SECTION 3
DISASSEMBLY

3.1 DISASSEMBLY PROCEDURE

CAUTION AT DISASSEMBLY:

- Be sure to perform the SYSTEM SETTEING, at the end of the procedure.
- Make sure that the power cord is disconnected from the outlet.
- Pay special attention not to break or damage the parts.
- When removing each board, remove the connectors as required. Taking notes of the connecting points (connector numbers) makes service procedure manageable.
- Make sure that there is no bent or stain on the connectors before inserting, and firmly insert the connectors.

3.1.1 REMOVING THE REAR COVER

(1) Disconnect the power plug.
(2) Remove the 12 screws **[A]**.
(3) Withdraw the REAR COVER backward.

3.1.2 REMOVING THE AV TERMINAL BOARD

- Remove the REAR COVER.
  (1) Remove the 4 screws **[B]**.
  (2) Withdraw the AV TERMINAL BOARD toward you.

3.1.3 REMOVING THE CHASSIS

- Remove the REAR COVER.
- Remove the AV TERMINAL BOARD.
  (1) Slightly raise the both sides of CHASSIS by hand.
  (2) Remove the 2 claws under the both side of the CHASSIS from the front cabinet.
  (3) Withdraw the CHASSIS backward.
  (If necessary, remove the wire clamp, connectors etc.)

3.1.4 REMOVING THE SPEAKER [AV-27F577]

- Remove the REAR COVER.
  (1) Remove the 4 screws **[C]**.
  (2) Remove the SPEAKER.
  (3) Follow the same steps when removing the other hand SPEAKER.

3.1.5 REMOVING THE SPEAKER [AV-32F577]

- Remove the REAR COVER.
  (1) Remove the 2 screws **[D]**.
  (2) Remove the SPEAKER with SPEAKER HOLDER.
  (3) Remove the 2 screws **[E]**.
  (4) Remove the SPEAKER from the SPEAKER HOLDER.
  (5) Follow the same steps when removing the other hand SPEAKER.

NOTE :

When remove the 2 screws **[D]** of the SPEAKER, remove the lower side screw first, and then remove the upper one.

3.1.6 REMOVING THE LED & POWER SW PWB

- Remove the REAR COVER.
- Remove the CHASSIS.
  (1) Remove the 2 screws **[F]**.
  (2) Withdraw the LED & POWER SW PWB toward you.

*If necessary, remove the wire clamp, connector etc.

3.1.7 REMOVING THE FRONT CONTROL PWB

- Remove the REAR COVER.
- Remove the CHASSIS.
  (1) Remove the 2 screws **[G]**.
  (2) Withdraw the FRONT CONTROL PWB toward you.

*If necessary, remove the wire clamp, connector etc.

3.1.8 REMOVING THE USB PWB

- Remove the REAR COVER.
- Remove the AV TERMINAL BOARD.
  (1) Remove the 2 screws **[H]**.
  (2) Withdraw the USB PWB toward you.

*If necessary, remove the wire clamp, connector etc.

3.1.9 CHECKING THE CHASSIS

To check the PW Board from back side.
(1) Pull out the CHASSIS (refer to REMOVING THE CHASSIS).
(2) Erect the CHASSIS vertically with the HVT side facing up so that you can easily check the back side of the PW board.

CAUTION :

- When erecting the CHASSIS, be careful so that there will be no contacting with other PW Board.
- Before turning on power, make sure that the wire connector is properly connected.
- **When conducting a check with power supplied, be sure to confirm that the CRT EARTH WIRE (BRAIDED ASS'Y) is connected to the CRT SOCKET PWB.**

3.1.10 WIRE CLAMPING AND CABLE TYING

(1) Be sure to clamp the wire.
(2) Never remove the cable tie used for tying the wires together. Should it be inadvertently removed, be sure to tie the wires with a new cable tie.


FRONT CABINET
CRT SOCKET PWB
FRONT CONTROL PWB
AV TERMINAL BOARD
Claw
MAIN PWB
REAR
LED&POWER SW PWB
G
F
H
USB PWB
<AV-27F577>
SPEKAER
C
CHASSIS
AV TERMINAL BOARD
<AV-32F577>
SPACER
E
D
L/F PWB
AV SW PWB
ATSC TUNER MODULE PWB
B
SPEKAER
SPEAKER HOLDER
POWER CORD
REAR COVER
A

Fig.1

3.1.11 REMOVING THE CRT

NOTE:

- Replacement of the CRT should be performed by 2 or more persons.
- After removing the REAR COVER, CHASSIS etc.,

(1) Putting the CRT change table on soft cloth, the CRT change table should also be covered with such soft cloth (shown in Fig. 2).

(2) While keeping the surface of CRT down, mount the TV set on the CRT change table balanced will as shown in Fig. 2.

(3) Remove 4 screws marked by arrows with a box type screw-driver as shown in Fig. 3.

NOTE:

Since the cabinet will drop when screws have been removed, be sure to support the cabinet with hands.

(4) After 4 screws have been removed, put the cabinet slowly on cloth (At this time, be carefully so as not to damage the front
surface of the cabinet) shown in Fig. 4.

NOTE:

- The CRT should be assembled according to the opposite sequence of its dismounting steps.
- The CRT change table should preferably be smaller that the CRT surface, and its height be about 35cm.



Fig.2



Fig.3



Fig.4

COATING OF SILICON GREASE FOR ELECTRICAL INSULATION ON THE CRT ANODE CAP SECTION.

Subsequent to replacement of the CRT and HV transformer or repair of the anode cap, etc. by dismounting them, be sure to coat silicon grease for electrical insulation as shown in Fig.5.Wipe around the anode button with clean and dry cloth. (Fig.5)Coat silicon grease on the section around the anode button. At this time, take care so that any silicon greases dose not sticks to the anode button. (Fig.6)

Silicon grease product No. KS - 650N



Fig.5



Fig.6

3.2 MEMORY IC REPLACEMENT

- This model uses the memory IC.
- This memory IC stores data for proper operation of the video and drive circuits.
- When replacing, be sure to use an IC containing this (initial value) data.

3.2.1 MEMORY IC TABLE

Simbol	Number of pins	Mounting PWB	Main content of data
IC702	8-pin	MAIN PWB	Setting value of Initial setting data is memorized.

3.2.2 MEMORY IC REPLACEMENT PROCEDURE

1. Power off
Switch off the power and disconnect the power plug.

2. Replace the memory IC
Be sure to use a memory IC written with the initial setting data.

3. Power on
Connect the power cord to the wall outlet and switch on the power.

4. Receiving channel setting
Refer to the OPERATING INSTRUCTIONS (USER'S GUIDE) and set the receive channels (Channels Preset) as described.

5. User settings
Check the user setting items according to the "FACTORY SETTING ITEM" table.
Where these do not agree, refer to the OPERATING INSTRUCTIONS (USER'S GUIDE) and set the items as described.

6. SERVICE MODE setting
Verify what to set in the SERVICE MODE, and set whatever is necessary(Fig.1) .
Refer to the SERVICE ADJUSTMENT for setting.

3.2.3 SERVICE MODE SETTING ITEMS



Fig.1

Setting items	Settings	Item No.
1. Digital Service		
Audio system setting	Adjust	A001~A010
2. TV-Micro Service		
Video system setting	Adjust	S001 - S045
Deflection system	Adjust	D001 - D033
Factory system setting	Fixed	F001 - F003

3.2.4 SETTINGS OF FACTORY SHIPMENT

3.2.4.1 BUTTON OPERATION

Setting item	Setting position
POWER	Off
CHANNEL	CABLE-02
VOLUME	10

3.2.4.2 REMOTE CONTROL DIRECT OPERATION

Setting item		Setting position
INPUT		TV
CHANNEL		CABLE-02
VOLUME		10
MUTING		OFF
DISPLAY		OFF
SLEEP TIMER		OFF
V. STATUS		DYNAMIC
THEAT. PRO		OFF
C.C.		OFF
MTS		STEREO
ASPECT		4 : 3
SOUND	A.H.S	OFF
	Smart Sound	OFF

3.2.4.3 REMOTE CONTROL MENU OPERATION

(1) INITIAL SETUP

Setting item	Setting position
Noise Muting	On
Language	English
Front Panel Lock	Off
V-Chip	Off
Set Lock Code	0000
Closed Caption	Auto(CC1/T1)
Auto Shut Off	Off

(2) TUNER SETUP

Setting item	Setting position
Auto Tuner Setup	Unnecessary to set

(3) EXTERNAL INPUT

Setting item	Setting position
Video Input Label	All blank

(4) SOUND ADJUST

Setting item	Setting position
Bass	0
Treble	+2
Balance	0
Optical Out	PCM
Turn On Volume	Current
Volume Limit	50

(5) CLOCK / TIMERS

Setting item	Setting position
Set Clock	Manual
On / Off Timer	Off

(6) INTERACTIVE PLUG-IN MENU

Refer to the OPERATING INSTRUCTIONS (USER'S GUIDE).

(7) PICTURE ADJUST

Customers can adjust the picture setting of menu screen as their own like but the picture standard value during factory shipment is as below.

Setting item	TINT	COLOR	PICTURE	BRIGHT	DETAIL	COLOR TEMPERATURE	VSM
STANDARD	0	0	0	0	0	LOW	ON
DINAMIC	0	0	+14	0	+10	HIGH	ON
THEATER	-3	-3	-10	+1	0	HIGH	OFF
GAME	0	+7	-10	0	+7	LOW	ON

3.3 REPLACEMENT OF CHIP COMPONENT

3.3.1 CAUTIONS

(1) Avoid heating for more than 3 seconds.
(2) Do not rub the electrodes and the resist parts of the pattern.
(3) When removing a chip part, melt the solder adequately.
(4) Do not reuse a chip part after removing it.

3.3.2 SOLDERING IRON

(1) Use a high insulation soldering iron with a thin pointed end of it.
(2) A 30w soldering iron is recommended for easily removing parts.

3.3.3 REPLACEMENT STEPS

1. How to remove Chip parts

[Resistors, capacitors, etc.]

(1) As shown in the figure, push the part with tweezers and alternately melt the solder at each end.



(2) Shift with the tweezers and remove the chip part.



[Transistors, diodes, variable resistors, etc.]

(1) Apply extra solder to each lead.

(2) As shown in the figure, push the part with tweezers and alternately melt the solder at each lead. Shift and remove the chip part.



NOTE :
After removing the part, remove remaining solder from the pattern.

2. How to install Chip parts

[Resistors, capacitors, etc.]

(1) Apply solder to the pattern as indicated in the figure.



(2) Grasp the chip part with tweezers and place it on the solder. Then heat and melt the solder at both ends of the chip part.



[Transistors, diodes, variable resistors, etc.]

(1) Apply solder to the pattern as indicated in the figure.
(2) Grasp the chip part with tweezers and place it on the solder.
(3) First solder lead **A** as indicated in the figure.



(4) Then solder leads **B** and **C**.



SECTION 4
ADJUSTMENT

4.1 ADJUSTMENT PREPARATION

(1) **There are 2 ways of adjusting this TV : One is with the REMOTE CONTROL UNIT and the other is the conventional method using adjustment parts and components.**
(2) **The adjustment using the REMOTE CONTROL UNIT is made on the basis of the initial setting values. The setting values which adjust the screen to the optimum condition can be different from the initial setting values.**
(3) Make sure that connection is correctly made AC to AC power source.
(4) Turn on the power of the TV and measuring instruments for warming up for at least 30 minutes before starting adjustments.
(5) If the receive or input signal is not specified, use the most appropriate signal for adjustment.
(6) Never touch the parts (such as variable resistors, transformers and condensers) not shown in the adjustment items of this service adjustment.

4.2 PRESET SETTING BEFORE ADJUSTMENTS

Unless otherwise specified in the adjustment items, preset the following functions with the REMOTE CONTROL UNIT.

Item	Preset value
VIDEO STATUS	STANDARD
PICTURE adjustment	All 00
COLOR TEMPERATURE	LOW
VSM	OFF
SOUND adjustment	All 00
A.H.S.	OFF
Smart Sound	OFF
ASPECT	4 : 3

4.3 MEASURING INSTRUMENT AND FIXTURES

- DC voltmeter (or digital voltmeter)
- DC power supply
- Oscilloscope
- Signal generator (Pattern generator) [NTSC]
- TV audio multiplex signal generator
- Remote control unit

4.4 ADJUSTMENT ITEMS

■CHECK ITEM
- B1 VOLTAGE check
- HV POTENTIAL check
- X-RAY PROTECTOR OPERATION-1 check
- X-RAY PROTECTOR OPERATION-2 check

■FOCUS
- FOCUS adjustment

■DEFLECTION CIRCUIT [2.TV-Micro Service]
- V. SIZE / V. POSITION (4:3) adjustment
- V. SIZE / V. POSITION (16:9) adjustment
- H. POSITION / H. SIZE / SIDE PIN (4:3) adjustment
- H. POSITION / H. SIZE / SIDE PIN (16:9) adjustment

■VIDEO CIRCUIT [2.TV-Micro Service]
- WHITE BALANCE(High Light & Low Light) adjustment
- SUB BRIGHT adjustment
- SUB CONTRAST adjustment
- SUB COLOR adjustment
- SUB TINT adjustment

■MTS CIRCUIT [1.Digital Service]
- MTS INPUT LEVEL adjustment
- MTS SEPARATION adjustment

4.5 ADJUSTMENT LOCATIONS



4.6 SERVICE MODE

4.6.1 BASIC OPERATION OF SERVICE MODE

Operate the SERVICE MODE with the REMOTE CONTROL UNIT.

4.6.1.1 HOW TO ENTER THE SERVICE MODE

(1) Set to **"0 minutes"** using the **[SLEEP TIMER]** key.
(2) While **"0 minutes"** is displayed, press the **[VIDEO STATUS]** key and **[DISPLAY]** key simultaneously.
(3) Enter the SERVICE MODE (Fig.1)



Fig.1

4.6.1.2 HOW TO EXIT THE SERVICE MODE

Press the **[MENU]** key to exit the SERVICE MODE.

4.6.1.3 HOW TO STORE OF SETTING VALUE

When adjustment is completed, press the **[MUTING]** key to memorize the adjustment value.

NOTE:

If not to do it, adjustment data is not memorized to the memory IC. And if exit the adjustment mode before memorize the data, the adjustment value which you change is canceled.

4.6.1.4 SERVICE MODE SELECT KEY LOCATION



4.6.2 SERVICE MODE MENU FLOW CHART



4.6.3 DESCRIPTION OF STATUS DISPLAY

The status display on the upper part of the SERVICE MODE screen is common (to all models).

4.6.3.1 DIGITAL SERVICE MODE

1. Adjust



(1) SIGNAL SYSTEM

The signal displayed on the screen is displayed.

NTSC : 525i (Composite / S-video input)
525I : 525i (Component input)
D525I : ATSC 525i
D525P : ATSC 525p
D750P : ATSC 750p
D1125I : ATSC 1125i

(2) SCREEN MODE

State of the ASPECT is displayed.

43-4:3 : 4 : 3 (Input signal 4 : 3)
43-16:9 : 16 : 9 (Input signal 4 : 3)
16-16:9 : 16 : 9 (Input signal 16 : 9)
16-4:3 : 4 : 3 (Input signal 16 : 9)
16-ZOOM : HD ZOOM (Input signal 16 : 9)

(3) VIDEO STATUS

State of the VIDEO STATUS is displayed.

STANDARD : STANDARD
DYNAMIC : DYNAMIC
THEATER : THEATER
GAME : GAME

(4) WHITE BALANCE

State of the WHITE BALANCE is displayed.

H : HIGH
L : LOW

(5) SETTING ITEM NAME

Setting item name are displayed. For the setting item names to be displayed, refer to "INITIAL SETTING VALUE OF SERVICE MODE".

(6) SETTING ITEM NO.

Setting item numbers are displayed. The setting item numbers to be displayed are listed below.

Item No.	Setting item
A001 - A010	Audio system setting

■SELECTION OF SETTING ITEM

- **[CH+]** / **[CH-]** key.
  Change the setting items up/ down.

A001... ↔ A010

(7) SETTING VALUE (DATA)

The SETTING VALUE is displayed.

■CHANGE OF SETTING VALUE (DATA)

- **[VOL+]** / **[VOL-]** key.
  Change the setting values up/down.

■MEMORY OF SETTING VALUE (DATA)

Changed setting value is memorized by pressing **[MUTING]** key.

2. Memory Edit

Data in the EEPROM is edited on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.



3. Edit Config

Setting value in the digital module is edited and confirmed on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

EDIT CONFIG MODE



4. All reset

Data in the EEPROM is all reset on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

ALL RESET MODE



5. Select Channel Map

Channel map is forcibly rewritten on this screen.[Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

SELECT CHANNEL MAP MODE



6. Clear Channel Map

Channel map is cleared on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

CLEAR CHANNEL MAP MODE



7. Digital Tuning Test

Digital channel tuning is tested on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

DIGITAL TUNING TEST MODE



4.6.3.2 TV-MICRO SERVICE MODE

1. Adjust



(1) SIGNAL SYSTEM

The signal displayed on the screen is displayed.

NTSC : 525i (Composite / S-video input)
525I : 525i (Component input)
D525I : ATSC 525i
D525P : ATSC 525p
D750P : ATSC 750p
D1125I : ATSC 1125i

(2) SCREEN MODE

State of the ASPECT is displayed.

43-4:3 : 4 : 3 (Input signal 4 : 3)
43-16:9 : 16 : 9 (Input signal 4 : 3)
16-16:9 : 16 : 9 (Input signal 16 : 9)
16-4:3 : 4 : 3 (Input signal 16 : 9)
16-ZOOM : HD ZOOM (Input signal 16 : 9)

(3) VIDEO STATUS

State of the VIDEO STATUS is displayed.

STANDARD : STANDARD
DYNAMIC : DYNAMIC
THEATER : THEATER
GAME : GAME

(4) WHITE BALANCE

State of the WHITE BALANCE is displayed.

H : HIGH
L : LOW

(5) SETTING ITEM NAME

Setting item name are displayed. For the setting item names to be displayed, refer to "INITIAL SETTING VALUE OF SERVICE MODE".

(6) SETTING ITEM NO.

Setting item numbers are displayed. The setting item numbers to be displayed are listed below.

Item No.	Setting item
S001 - S045	Video system setting
D001 - D033	Deflection system
F001 - F003	Factory system setting

■SELECTION OF SETTING ITEM

- **[CH+]** / **[CH-]** key.
  Change the setting items up/ down.

  S001... ↔ D001... ↔ F001...↔ S001...

- **[SLEEP TIMER]** key.
  Switch to the next items.

  S001 → D001 → F001 → S001

(7) SETTING VALUE (DATA)

The SETTING VALUE is displayed.

■CHANGE OF SETTING VALUE (DATA)

- **[VOL+]** / **[VOL-]** key.
  Change the setting values up/down.

■MEMORY OF SETTING VALUE (DATA)

Changed setting value is memorized by pressing **[MUTING]** key.

2. White Balance

White balance data is adjusted on this screen.



BRIGHTNESS

[VOL+] key : BRIGHT is up
[VOL-] key : BRIGHT is down

DRIVE

[2] key : DRIVE R is up
[5] key : DRIVE R is down
[3] key : DRIVE B is up
[6] key : DRIVE B is down

CUTOFF

[1] key : HORIZONTAL LINE on
[4] key : HORIZONTAL LINE off
[7] key : CUTOFF G is up
[TUNE] key : CUTOFF G is down
[8] key : CUTOFF R is up
[0] key : CUTOFF R is down
[9] key : CUTOFF B is up
[RETURN+] key : CUTOFF B is down

■MEMORY OF SETTING VALUE (DATA)

Changed setting value is memorized by pressing **[MUTING]** key.

3. Memory Edit

Data in the EEPROM is edited on this screen. [Do not adjust]

CAUTION:

This mode is not used in the ADJUSTMENT. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

MEMORY EDIT MODE



4.7 INITIAL SETTING VALUE OF SERVICE MODE

(1) Adjustment of the SERVICE MODE is made on the basis of the initial setting values ; however, the new setting values which set the screen in its optimum condition may differ from the initial setting.
(2) Do not change the initial setting values of the setting items NOT LISTED IN ADJUSTMENT PROCEDURE.
(3) --- : This mark described in each table shows "Cannot adjust it."

4.7.1 [1. Digital Service]

4.7.1.1 SOUND SETTING

No.	Setting item	Variable range	Initial setting value
A001	IN LEVEL	0 - 15	6
A002	LOW SEP	0 - 63	30
A003	HIGH SEP	0 - 63	30
A004	BASS OFS	-128 - 127	0
A005	TREB OFS	-128 - 127	0

No.	Setting item	Variable range	Initial setting value
A006	AHS MVE	-128 - 127	-4
A007	AHS MSC	-128 - 127	-2
A008	AGC FLAT	0 - 3	1
A009	BBE BASS	-128 - 127	-1
A010	BBE TREB	-128 - 127	1

4.7.2 [2. TV-Micro Service]

4.7.2.1 VIDEO SETTING

No.	Setting item	Variable range	Initial setting value					
			AV-27F577/R AV-27F577/S			AV-32F577/R AV-32F577/Y AV-32F577/Z		
			RF					
			STANDARD		THEATER	STANDARD		THEATER
			4 : 3	16 : 9	4 : 3	4 : 3	16 : 9	4 : 3
S001	BRIGHT	000 - 127	064	---	---	064	---	---
S002	PICTURE	000 - 127	045	---	---	047	---	---
S003	COLOR	000 - 127	054	---	---	050	---	---
S004	TINT	000 - 127	063	---	---	063	---	---
S005	DETAIL	000 - 063	035	---	---	045	---	---
S006	BRIGHT+-	-128 - +127	---	±000	±000	---	±000	±000
S007	PICT+-	-128 - +127	---	-006	±000	---	-008	±000
S008	COLOR+-	-128 - +127	---	±000	±000	---	±000	±000
S009	TINT+-	-128 - +127	---	±000	±000	---	±000	±000
S010	DETAIL+-	-128 - +127	---	---	±000	---	---	±000

No.	Setting item	Variable range	Initial setting value				
			EXTERNAL (S / COMPOSITE)		EXTERNAL (COMPONENT)		ATSC
			AV-27F577/R AV-27F577/S	AV-32F577/R AV-32F577/Y AV-32F577/Z	AV-27F577/R AV-27F577/S	AV-32F577/R AV-32F577/Y AV-32F577/Z	
			STANDARD				
			4 : 3				
S003	COLOR	000 - 127	---	---	048	043	---
S004	TINT	000 - 127	---	---	068	068	---
S005	DETAIL	000 - 063	040	045	040	040	040
S006	BRIGHT+-	-128 - +127	±000	±000	±000	±000	+006
S007	PICT+-	-128 - +127	±000	±000	±000	±000	±000
S008	COLOR+-	-128 - +127	-004	-004	---	---	-007
S009	TINT+-	-128 - +127	+003	+003	---	---	+014

No.	Setting item	Variable range	Initial setting value							
			AV-27F577/R AV-27F577/S							
			RF / EXTERNAL (S / COMPOSITE)				EXTERNAL (COMPONENT) / ATSC			
			STANDARD		THEATER		STANDARD		THEATER	
			LOW	HIGH	LOW	HIGH	LOW	HIGH	LOW	HIGH
S011	R CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S012	G CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S013	B CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S014	R DRIVE	000 - 127	064	---	---	---	---	---	---	---
S015	B DRIVE	000 - 127	064	---	---	---	---	---	---	---
S016	R CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S017	G CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S018	B CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S019	R DRV +-	-128 - +127	---	+005	+013	+007	±000	---	---	---
S020	B DRV +-	-128 - +127	---	+006	-025	-009	±000	---	---	---
S021	NTSC MAT	000 - 003	003	003	001	001	002	002	001	001
S022	BLACK ST	000 - 003	001	---	001	---	---	---	---	---
S023	DC REST	000 - 001	001	---	001	---	---	---	---	---
S024	DCRSW	000 - 001	001	---	001	---	---	---	---	---

No.	Setting item	Variable range	Initial setting value							
			AV-32F577/R AV-32F577/Y AV-32F577/Z							
			RF / EXTERNAL (S / COMPOSITE)				EXTERNAL (COMPONENT) / ATSC			
			STANDARD		THEATER		STANDARD		THEATER	
			LOW	HIGH	LOW	HIGH	LOW	HIGH	LOW	HIGH
S011	R CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S012	G CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S013	B CUT OFF	000 - 255	030	---	---	---	---	---	---	---
S014	R DRIVE	000 - 127	064	---	---	---	---	---	---	---
S015	B DRIVE	000 - 127	064	---	---	---	---	---	---	---
S016	R CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S017	G CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S018	B CUT +-	-128 - +127	---	±000	±000	±000	±000	---	---	---
S019	R DRV +-	-128 - +127	---	+005	+013	+007	±000	---	---	---
S020	B DRV +-	-128 - +127	---	+006	-025	-009	±000	---	---	---
S021	NTSC MAT	000 - 003	003	003	001	001	002	002	001	001
S022	BLACK ST	000 - 003	001	---	001	---	---	---	---	---
S023	DC REST	000 - 001	001	---	001	---	---	---	---	---
S024	DCRSW	000 - 001	001	---	001	---	---	---	---	---

No.	Setting item	Variable range	Initial setting value			
			RF	EXTERNAL (S / COMPOSITE)	EXTERNAL (COMPONENT)	ATSC
S025	ASY SHRP	000 - 007	004	004	004	004
S026	BPF F0	000 - 001	000	000	---	---
S027	KILR OFF	000 - 001	000	000	---	---
S028	KILR SEN	000 - 001	001	001	---	---

No.	Setting item	Variable range	Initial setting value	
			AV-27F577/R AV-27F577/S	AV-32F577/R AV-32F577/Y AV-32F577/Z
S029	RGB MUTE	000 - 001	000	000
S030	BLUE B	000 - 001	000	000
S031	CMP ABCL	000 - 001	000	000
S032	OSD ABL	000 - 001	000	000
S033	OSD CONT	000 - 063	007	008
S034	SUB CONT	000 - 015	005	005
S035	ABL GAIN	000 - 003	000	000
S036	ABL PNT	000 - 003	003	003
S037	Y GAMMA	000 - 003	001	001
S038	Y MUTE	000 - 001	000	000
S039	SVM GAIN	000 - 003	003	003
S040	SVM PH	000 - 003	002	003
S041	WPL	000 - 001	000	000
S042	COL GMM	000 - 001	000	000
S043	V1 GAIN	000 - 007	004	004
S044	VMOFF DE	-128 - +127	+003	+003
S045	PIP ADJ	000 - 015	004	008

4.7.2.2 DEFLECTION SETTING

No.	Setting item	Variable range	Initial setting value		
			RF	EXTERNAL	ATSC
D001	V FREQ	000 - 003	000	003	003
D002	AFC GAIN	000 - 003	000	002	002

No.	Setting item	Variable range	Initial setting value									
			AV-27F577/R		AV-27F577/S		AV-32F577/R		AV-32F577/Y		AV-32F577/Z	
			4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9
D003	H POSI	000 - 031	022	---	022	---	021	---	019	---	019	---
D004	H POSI+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D005	V PHASE	000 - 007	000	---	000	---	000	---	000	---	000	---
D006	V PH+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D007	V SIZE	000 - 127	107	---	096	---	076	---	045	---	058	---
D008	V SIZE+-	-128 - +127	---	-028	---	-030	---	-027	---	-023	---	-022
D009	V CENTER	000 - 063	032	---	032	---	032	---	032	---	032	---
D010	V CENT+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D011	V S CORR	000 - 015	007	---	007	---	009	---	008	---	009	---
D012	V S CO+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D013	V LIN	000 - 015	010	---	010	---	010	---	012	---	010	---
D014	V LIN+-	-128 - +127	---	±000	---	±000	---	±000	---	-003	---	±000
D015	H SIZE	000 - 063	032	---	032	---	050	---	028	---	049	---
D016	H SIZE+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D017	WVMT TOP	000 - 003	000	000	000	000	000	000	000	000	000	000
D018	WVMT BTM	000 - 003	000	000	000	000	000	000	000	000	000	000
D019	EWCR TOP	000 - 031	017	---	015	---	013	---	011	---	014	---

No.	Setting item	Variable range	Initial setting value									
			AV-27F577/R		AV-27F577/S		AV-32F577/R		AV-32F577/Y		AV-32F577/Z	
			4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9	4 : 3	16 : 9
D020	EWCR T+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D021	EWCR BTM	000 - 031	016	---	013	---	014	---	016	---	010	---
D022	EWCR B+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D023	EW PARA	000 - 063	042	---	027	---	045	---	035	---	037	---
D024	EW PARA+-	-128 - +127	---	-016	---	-010	---	-016	---	-013	---	-012
D025	V EHT	000 - 007	000	---	000	---	000	---	000	---	000	---
D026	V EHT+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D027	H EHT	000 - 007	000	---	000	---	000	---	000	---	000	---
D028	H EHT+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000
D029	TRAPEZ	000 - 063	031	---	029	---	031	---	034	---	032	---
D030	TRAPEZ+-	-128 - +127	---	±000	---	±000	---	±000	---	±000	---	±000

No.	Setting item	Variable range	Initial setting value
D031	V AGC	000 - 001	000
D032	BLANK SW	000 - 001	000
D033	VRMP BI	000 - 001	000

4.7.2.3 FACTORY SETTING

No.	Setting item	Variable range	Initial setting value	
			AV-27F577/R AV-27F577/S	AV-32F577/R AV-32F577/Y AV-32F577/Z
F001	(NO DISPLAY)	000 - 255	039	042
F002	(NO DISPLAY)	000 - 255	090	090
F003	(NO DISPLAY)	000 - 001	001	001

4.8 ADJUSTMENT PROCEDURE

4.8.1 CHECK ITEM

<table>
<tr><th>Item</th><th>Measuring instrument</th><th>Test point</th><th>Adjustment part</th><th>Description</th></tr>
<tr><td>B1 VOLTAGE</td><td>DC voltmeter</td><td>S1 connector
1-pin : TP-E
5-pin : TP-91B
[MAIN PWB]</td><td></td><td>(1) Receive the black and white signal. (color off)
(2) Connect the DC voltmeter to the 1-pin and 5-pin of S1 connector.
(3) Confirm that the voltage is DC134.5V±2V.</td></tr>
<tr><td>HV POTENTIAL</td><td>HV voltmeter</td><td>CRT anode

Chassis GND</td><td>SCREEN VR
[In HVT]</td><td rowspan="2">(1) Receive any broadcast.
(2) Turn the SCREEN VR to make cut-off screen (black screen).
(3) Connect the earth clip of HV voltmeter to chassis GND.
(4) Connect the probe of HV voltmeter to CRT anode.
(5) Confirm that the voltage is within a value as shown left table.
NOTE:
Remove the probe before removing the earth clip.</td></tr>
<tr><td colspan="4"><table><tr><th>Model</th><th>27 inch</th><th>32 inch</th></tr><tr><td>VOLTAGE</td><td>30.0kV±1.3kV</td><td>31.4kV±1.3kV</td></tr></table></td></tr>
<tr><td>X-RAY PROTECTOR OPERATION-1</td><td>DC power supply</td><td>S1 connector
1-pin : TP-E
3-pin : X-RAY1
[MAIN PWB]</td><td></td><td rowspan="2">(1) Receive any broadcast.
(2) Apply DC 20V between the 1-pin and 3-pin of S1 connector.
(3) Increase the DC voltage slowly.
(4) Confirm that the screen picture disappeares until the DC voltage as shown left table.
(5) Disconnect the power plug.
(6) Again connect the power plug.
(7) Turn the power switch to on.
(8) Make sure that the normal picture is displayed on the screen.</td></tr>
<tr><td colspan="4"><table><tr><th>Model</th><th>27 inch</th><th>32 inch</th></tr><tr><td>VOLTAGE</td><td>33.2V</td><td>32.25V</td></tr></table></td></tr>
<tr><td>X-RAY PROTECTOR OPERATION-2</td><td>Resistor (1/4W)</td><td>S1 connector
2-pin : X-RAY2
3-pin : X-RAY1
[MAIN PWB]</td><td></td><td rowspan="2">(1) Receive any broadcast.
(2) Refer to the figure, connect the resistor between 2-pin and 3-pin of S1 connector.
(3) Make sure that the screen picture disappeares.
(4) Disconnect the power plug.
(5) Remove the resistor.
(6) Again connect the power plug.
(7) Turn the power switch to on.
(8) Make sure that the normal picture is displayed on the screen.</td></tr>
<tr><td colspan="4">RESISTOR
22.0kΩ±110Ω : AV-27F577/S, AV-27F577/R, AV-27F577/R, AV-32F577/Z
16.3kΩ±100Ω : AV-32F577/Z
 
</td></tr>
</table>

4.8.2 FOCUS

Item	Measuring instrument	Test point	Adjustment part	Description
FOCUS	Signal generator		FOCUS VR [In HVT]	(1) Receive the crosshatch signal. (2) While watching at the screen, adjust the **FOCUS VR** so that the vertical and horizontal lines get the thinnest and sharpest center horizontal line. (3) Make sure that the picture is in focus even when the screen gets darkened.

4.8.3 DEFLECTION CIRCUIT [2.TV-Micro Service]

<table>
<tr><th>Item</th><th>Measuring instrument</th><th>Test point</th><th>Adjustment part</th><th>Description</th></tr>
<tr><td>V. SIZE /
V. POSITION
(4:3)</td><td>Signal generator

Remote control unit</td><td></td><td>[1.Adjust]
D05: V PHASE
D07: V SIZE
D11: VS CORR
D13: V LIN

V. CENTER SW
(S421)
[MAIN PWB]</td><td>(1) Receive the crosshatch signal.
(2) Select the 2.TV-Micro Service from the SERVICE MODE.
(3) Select the 1. Adjust.
(4) Select < D05 > (V PHASE).
(5) Confirm that the value of < D05 > is 0.
(6) Adjust V. CENTER SW to agree the vertical center with the display center.
(7) Select < D07 > (V SIZE).
(8) Adjust < D07 > so that the vertical screen size becomes 92% of the vertical picture size.
(9) Press the [MUTING] key to memorize the set value.
NOTE:
• Bottom is to be located within the 85%-95% range.
• When vertical linearity is not even, adjust < D13 > (V LIN) and < D11 > (VS CORR) to vertical linearity.</td></tr>
<tr><td colspan="3">Screen size
Picture size 100%</td></tr>
<tr><td>V. SIZE /
V. POSITION
(16:9)</td><td>Signal generator

Remote control unit</td><td></td><td rowspan="2">[1.Adjust]
D08: V SIZE+-
D14: V LIN+-</td><td rowspan="2">• V. SIZE / V. POSITION (4:3) adjustment should be finished.
(1) Receive the black and white signal (color off).
(2) Select the ASPECT to 16:9 mode.
(3) Select the 2.TV-Micro Service from the SERVICE MODE.
(4) Select the 1. Adjust.
(5) Confirm that the width of V. BLANKING is equal to adjustment value (B).
(6) If the value (B) is not correct, adjust < D08 > (V SIZE+-) and < D14 > (V LIN+-) to be same to adjustment value (B).
(7) Press the [MUTING] key to memorize the set value.
NOTE :
• When you change the VERTICAL adjustment value of the regular mode (4:3), review the adjustment of 16:9 mode again.</td></tr>
<tr><td colspan="3">B
[B=B']
B'
<table><tr><th>Adjust point</th><th>Setting value</th></tr><tr><td rowspan="2">B</td><td>50 mm (27 inch models)</td></tr><tr><td>60 mm (32 inch models)</td></tr></table></td></tr>
<tr><td>H. SIZE /
H. POSITION /
SIDE PIN
(4:3)</td><td>Signal generator

Remote control unit</td><td></td><td>[1.Adjust]
D03: H POSI
D15: H SIZE
D23: EW PARA
D19: EWCR TOP
D21: EWCR BTM</td><td>• FORCUS adjustment should be finished.
• V. SIZE / V. POSITION adjustment should be finished.
(1) Receive the crosshatch signal.
(2) Select the 2.TV-Micro Service from the SERVICE MODE.
(3) Select the 1. Adjust.
(4) Select < D03 > (H POSI).
(5) Adjust < D03 > so that the left width and right width of the crosshatch screen become equal.
(6) Select < D15 > (H SIZE).
(7) Adjust < D15 > so that the horizontal screen size becomes 90% of the horizontal picture size.
(8) Select < D23 > (EW PARA).
(9) Adjust < D23 > to vertical line at both side to become straight.
(10) If it is necessary, readjust step 3 to 9.
(11) Press the [MUTING] key to memorize the set value.
NOTE:
If it is not straight at the vertical upper and bottom corner line, adjust the upper and bottom conrner pin by < D19 > (EWCR TOP) and < D21 > (EWCR BTM).</td></tr>
<tr><td colspan="3">Screen size
Picture size 100%</td></tr>
</table>

Item	Measuring instrument	Test point	Adjustment part	Description
H. POSITION / H. SIZE / SIDE PIN (16:9)	Signal generator Remote control unit		[1.Adjust] D16: H SIZE+- D04: H POSI+- D24: EW PARA+- D20: EWCR T+- D22: EWCR B+-	• FORCUS adjustment should be finished. • V. SIZE / V. POSITION adjustment should be finished. • H. SIZE / H. POSITION / SIDE PIN adjustment should be finished. (Regular size(4:3)). (1) Receive the crosshatch signal. (2) Select the ASPECT to 16:9 mode. (3) Select the **2.TV-Micro Service** from the SERVICE MODE. (4) Select the **1. Adjust**. (5) Confirm both sides of crosshatch to be the adjustment value **90%**. (6) If the value is not correct, adjust **< D16 >** (H SIZE+-) and **< D04 >** (H POSI+-) so that the horizontal screen size becomes 90% of the horizontal picture size. (7) Confirm the second vertical line from left and right to be straight. (8) If it is not straight, adjust to be straight by **< D24 >** (EW PARA+-), **< D20 >** (EWCR T+-) and **< D22 >** (EWCR B+-). (9) Press the **[MUTING]** key to memorize the set value. **NOTE :** • Review the adjustment of 16:9 mode again when you change the SIDE PIN adjustment value of regular (4:3) mode.
				

4.8.4 VIDEO CIRCUIT [2.TV-Micro Service]

<table>
<tr><th>Item</th><th>Measuring instrument</th><th>Test point</th><th>Adjustment part</th><th>Description</th></tr>
<tr><td>WHITE BALANCE (LOW LIGHT)</td><td>Signal generator

Remote control unit</td><td></td><td>[1.Adjust]
S01: BRIGHT
S11: R CUTOFF
S12: G CUTOFF
S13: B CUTOFF

[2.White Blance]

SCREEN VR [in HVT]</td><td>(1) Receive the black and white signal (color off).
(2) Set VIDEO STATUS to "STANDARD".
(3) Select COLOR TEMPERATURE to "LOW".
(4) Select the 2.TV-Micro Service from the SERVICE MODE.
(5) Select the 1. Adjust.
(6) Set the initial setting value of < S11 > (R CUTOFF), < S12 > (G CUTOFF), < S13 > (B CUTOFF) and < S01 > (BRIGHT).
(7) Return to the 2.TV-Micro Service MENU.
(8) Select the 2. White Balance.
(9) Display a single horizontal line by pressing the [1] key.
(10) Turn the SCREEN VR all the way to the left.
(11) Turn the SCREEN VR gradually to the right from the left until either one of the red, blue or green colors appears faintly.
(12) Adjust the two colors which did not appear until the single horizontal line becomes white by using the [7] to [0] keys, [TUNE] and [RETURN+].
(13) Turn the SCREEN VR until the single horizontal line is displayed faintly.
(14) Press the [MUTING] key to memorize the set value.
(15) Press the [4] key to cancel the single horizontal line mode.
(16) Adjust the BRIGHT level so that the black component shines white slightly by the [VOL+] / [VOL-] key.
(17) Confirm that whether the color ingredient of R, G, or B is visible to the black component, which shines white slightly.
(18) When the color ingredient can be seen, two colors other than a visible color are adjusted, and it is made to look white.
(19) Press the [MUTING] key to memorize the set value.</td></tr>
<tr><td colspan="3"> 
</td></tr>
<tr><td>WHITE BALANCE (HIGH LIGHT)</td><td>Signal generator

Remote control unit</td><td></td><td>[1.Adjust]
S14: R DRIVE
S15: B DRIVE

[2.White Blance]</td><td>• WHITE BALANCE(LOW LIGHT) adjustment should be finished.
(1) Receive the black and white signal (color off).
(2) Set VIDEO STATUS to "STANDARD".
(3) Select COLOR TEMPERATURE to "LOW".
(4) Select the 2.TV-Micro Service from the SERVICE MODE.
(5) Select the 1. Adjust.
(6) Set the initial setting value of < S14 > (R DRIVE) and < S15 > (B DRIVE).
(7) Return to the 2.TV-Micro Service MENU.
(8) Select the 2. White Balance.
(9) Adjust the screen until it becomes white by using the [2], [3], [5] and [6] keys.
(10) Press the [MUTING] key to memorize the set value.</td></tr>
<tr><td colspan="3"> 
</td></tr>
</table>

Item	Measuring instrument	Test point	Adjustment part	Description
SUB BRIGHT	Remote control unit		[1.Adjust] S01: BRIGHT	• WHITE BALANCE adjustment should be finished. (1) Receive any broadcast. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S01 >** (BRIGHT). (7) Set the initial setting value of **< S01 >**. (8) If the brightness is not the best with the initial setting value, make fine adjustment of **< S01 >** until you get the optimum brightness. (9) Press the **[MUTING]** key to memorize the set value.
SUB CONTRAST	Remote control unit		[1.Adjust] S02: PICTURE	• SUB BRIGHT adjustment should be finished. (1) Receive any broadcast. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S02 >** (PICTURE). (7) Set the initial setting value of **< S02 >**. (8) If the contrast is not the best with the initial setting value, make fine adjustment of the **< S02 >** until you get the optimum contrast. (9) Press the **[MUTING]** key to memorize the set value.
SUB COLOR	Remote control unit		[1.Adjust] S03 : COLOR	**[Method of adjustment without measuring instrument]** • SUB CONTRAST adjustment should be finished. (1) Receive any broadcast. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S03 >**(COLOR). (7) Set the initial setting value of the **< S03 >**. (8) If the color is not the best with the initial setting values, make fine adjustment until you get the best color. (9) Press the **[MUTING]** key to memorize the set value.
	Signal generator Oscilloscope Remote control unit	TP-B TP-E [CRT SOCKET PWB]	[1.Adjust] S03 : COLOR	**[Method of adjustment using measuring instrument]** • SUB CONTRAST adjustment should be finished. (1) Input the full color bar signal includes the 75% white. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S03 >**(COLOR). (7) Set the initial setting value of the **< S03 >**. (8) Connect the oscilloscope between TP-B and TP-E. (9) Adjust **< S03 >** and bring the voltage of **(A)** in the illustration to **+17V**. (voltage difference between white and blue). (10) Press the **[MUTING]** key to memorize the set value.
				

Item	Measuring instrument	Test point	Adjustment part	Description
SUB TINT	Remote control unit		[1.Adjust] S04 : TINT	**[Method of adjustment without measuring instrument]** • SUB CONTRAST adjustment should be finished. (1) Receive any broadcast. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S04 >**(TINT). (7) Set the initial setting value of the **< S04 >**. (8) If the tint is not the best with the initial setting values, make fine adjustment until you get the best tint. (9) Press the **[MUTING]** key to memorize the set value.
	Signal generator Oscilloscope Remote control unit	TP-B TP-E [CRT SOCKET PWB]	[1.Adjust] S04 : TINT	**[Method of adjustment using measuring instrument]** • SUB CONTRAST adjustment should be finished. (1) Input the full color bar signal includes the 75% white. (2) Set VIDEO STATUS to **"STANDARD"**. (3) Select COLOR TEMPERATURE to **"LOW"**. (4) Select the **2.TV-Micro Service** from the SERVICE MODE. (5) Select the **1. Adjust**. (6) Select **< S04 >**(TINT). (7) Set the initial setting value of the **< S04 >**. (8) Connect the oscilloscope between TP-B and TP-E. (9) Adjust **< S04 >** and bring the voltage of **(B)** in the illustration to **+17V**. (voltage difference between white and magenta). (10) Press the **[MUTING]** key to memorize the set value.
				

4.8.5 MTS CIRCUIT [1.Digital Service]

Item	Measuring instrument	Test point	Adjustment part	Description
MTS INPUT LEVEL	Remote control unit		[1.Adjust] A01: IN LEVEL	(1) Receive any broadcast. (2) Select the **1.Digital Service** from the SERVICE MODE. (3) Select the **1.Adjust**. (4) Select the **< A01 >** (IN LEVEL). (5) Set the initial setting value of **< A01 >**. (6) Press the **[MUTING]** key to memorize the set value.
MTS SEPARATION	TV audio multiplex signal generator Oscilloscope Remote control unit	R OUT L OUT [AUDIO OUT]	[1.Adjust] A02: LOW SEP A03: HIGH SEP	(1) Input the stereo L signal (300 Hz) from the TV audio multiplex signal generator to the antenna terminal. (2) Connect an oscilloscope to R OUT pin of the AUDIO OUT, and display one cycle portion of the 300 Hz signal. (3) Select the **1.Digital Service** from the SERVICE MODE. (4) Select the **1.Adjust**. (5) Select the **< A02 >** (LOW SEP). (6) Set the initial setting value of **< A02 >**. (7) Adjust the **< A02 >** so that the stroke element of the 300Hz signal will become minimum. (8) Press the **[MUTING]** key to memorize the set value. (9) Input the stereo R signal (3kHz) and change the connection of the oscilloscope to L OUT pin of the AUDIO OUT. (10) Similarly adjust **< A03 >** (HIGH SEP). (11) Press the **[MUTING]** key to memorize the set value.
				

SECTION 5
TROUBLESHOOTING

5.1 SELF CHECK FEATURE

5.1.1 OUTLINE

This unit comes with the "Self check" feature, which checks the operational state of the circuit and displays/saves it during failure. Diagnosis is performed when power is turned on, and information input to the main microcomputer is monitored at all time. Failure detection is based on input state of I^2C bus and the various control lines connected to the main microcomputer.

5.1.2 HOW TO ENTER THE SELF CHECK MODE

(1) Set to "**0 minutes**" using the **[SLEEP TIMER]** key.
(2) While **"0 minutes"** is displayed, press the **[VIDEO STATUS]** key and **[DISPLAY]** key simultaneously, then enter the SERVICE MODE.
(3) Press the **[4]** key (4.Diagnostics) in the SERVICE MENU SCREEN. (Fig.1)
(4) Press the **[3]** key (3.Self check) in the DIAGNOSTICS MODE screen. (Fig.2)
(5) The SELF CHECK MODE screen is displayed. (Fig.3)
(6) Press the **[VOL+]** / **[VOL-]** key to switch between the first page and the second page.

NOTE:

When a number key other than the **[4]** key is pressed in the SERVICE MENU SCREEN, the other relevant screen may be displayed.
This is not used in the SELF CHECK MODE. Press the **[BACK]** key to return to the SERVICE MENU SCREEN.

5.1.3 HOW TO EXIT THE SELF CHECK MODE

TO SAVE FAILURE HISTORY:

Turn off the power by unplugging the AC power cord plug when in the SELF CHECK MODE.

TO CLEAR (RESET) FAILURE HISTORY:

Turn off the power by pressing the key on the remote control unit when in the SELF CHECK MODE.

5.1.4 FAILURE HISTORY

Failure history can be counted up to 9 times for each item. When the number exceeds 9, display will remain as 9. Failure history will be stored in the memory unless it has been deleted.

5.1.5 POINTS TO NOTE WHEN USING THE SELF CHECK FEATURE

In addition to circuit failures (abnormal operation), the following cases may also be diagnosed as "Abnormal" and displayed and counted as "NG".

(1) Temporary defective transmissions across circuits due to pulse interruptions
(2) Misalignment in the on/off timing of power for I^2C bus (VCC) when turning on/off the main power.

Diagnosis may be impeded if a large number of items are displayed as "NG". As such, start Self check check only after 3 seconds in the case of receivers and 5 seconds in the case of panels upon turning on the power. If recurrences are expected, ensure to clear (reset) the failure history and record the new diagnostic reults.



5.1.6 DETAILS

Self check is performed for the following items:

5.1.6.1 PAGE 1 OF SCREEN

Detection item	Display	Detection content	Diagnosis signal (line)	Detection timing
X-ray protection	X-RAY	Not used.	---	---
B1 over-current protection	OCP	Not used.	---	---
Low bias line short protection	LOB	Not used.	---	---
Timer (clock)	TIM	The power frequency is changed as follows: 50Hz → 60Hz / 60Hz→50Hz. IC201 [MAIN PWB]	AC_IN	Detection starts 3 seconds after the power is turned on. Periodically check the power frequency by counting the AC pulse and monitor whether or not the frequency is changed.
Photo ditect	PHOTO	Not used.	---	---
DTVM and TVM communication	Hostlink	Communication error between the digital TV microcomputer and the TV microcomputer is detected. IC201 [MAIN PWB]	SDA	Check communication errors by counting the number of reset exception handling.
Fan lock	FAN	Not used.	---	---

5.1.6.2 PAGE 2 OF SCREEN

Detection item	Display	Detection content	Diagnosis signal (line)	Detection timing
US audio multiplexing decoder	MTS	Confirmation of reply of ACK signal which uses I2C communication.	SDA	If it checks whenever I2C communication is performed and no reply of ACK signal an error will be counted.
Tone/volume control	TONE	Same as above.	SDA	Same as above.
AV select switch	AVSW	Same as above.	SDA	Same as above.
Component signal select switch	CompSW	Not used.	---	---
A-D converter for component signal	ADC	Confirmation of reply of ACK signal which uses I2C communication.	SDA	If it checks whenever I2C communication is performed and no reply of ACK signal an error will be counted.
Tuner	TUNER	Same as above.	SDA	Same as above.
A-D converter for audio	Audio ADC	Not used.	---	---
Digital input	HDMI	Not used.	---	---
RGB/Def process	RGB/DEF	Confirmation of reply of ACK signal which uses I2C communication. IC201 [MAIN PWB]	SDA	If it checks whenever I2C communication is performed and no reply of ACK signal an error will be counted.
Memory	A-EEPROM	Confirmation of reply of ACK signal which uses I2C communication. IC702 [MAIN PWB]	SDA	Same as above.

JVC
Victor Company of Japan, Limited
CRT Display Category 12, 3-chome, Moriya-cho, Kanagawa-ku, Yokohama-city, Kanagawa-prefecture, 221-8528, Japan

(No.YA387)

Printed in Japan
VPT

PARTS LIST

CAUTION

- The parts identified by the ⚠ symbol are important for the safety . Whenever replacing these parts, be sure to use specified ones to secure the safety.
- The parts not indicated in this Parts List and those which are filled with lines --- in the Parts No. columns will not be supplied.
- P.W. BOARD Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied.

ABBREVIATIONS OF RESISTORS, CAPACITORS AND TOLERANCES

RESISTORS		CAPACITORS	
CR	Carbon Resistor	C CAP.	Ceramic Capacitor
FR	Fusible Resistor	E CAP.	Electrolytic Capacitor
PR	Plate Resistor	M CAP.	Mylar Capacitor
VR	Variable Resistor	CH CAP.	Chip Capacitor
HV R	High Voltage Resistor	HV CAP.	High Voltage Capacitor
MF R	Metal Film Resistor	MF CAP.	Metalized Film Capacitor
MG R	Metal Glazed Resistor	MM CAP.	Metalized Mylar Capacitor
MP R	Metal Plate Resistor	MP CAP.	Metalized Polystyrol Capacitor
OM R	Metal Oxide Film Resistor	PP CAP.	Polypropylene Capacitor
CMF R	Coating Metal Film Resistor	PS CAP.	Polystyrol Capacitor
UNF R	Non-Flammable Resistor	TF CAP.	Thin Film Capacitor
CH V R	Chip Variable Resistor	MPP CAP.	Metalized Polypropylene Capacitor
CH MG R	Chip Metal Glazed Resistor	TAN. CAP.	Tantalum Capacitor
COMP. R	Composition Resistor	CH C CAP.	Chip Ceramic Capacitor
LPTC R	Linear Positive Temperature Coefficient Resistor	BP E CAP.	Bi-Polar Electrolytic Capacitor
		CH AL E CAP.	Chip Aluminum Electrolytic Capacitor
		CH AL BP CAP.	Chip Aluminum Bi-Polar Capacitor
		CH TAN. E CAP.	Chip Tantalum Electrolytic Capacitor
		CH AL BP E CAP.	Chip Tantalum Bi-Polar Electrolytic Capacitor

RESISTORS									
F	G	J	K	M	N	R	H	Z	P
±1%	±2%	±5%	±10%	±20%	±30%	+30% -10%	+50% -10%	+80% -20%	+100% -0%

CONTENTS

USING P.W. BOARD & REMOTE CONTROL UNIT 3-3
EXPLODED VIEW PARTS LIST -1 3-4
EXPLODED VIEW -1 3-5

PRINTED WIRING BOARD PARTS LIST [AV-27F577/R] 3-6
MAIN P.W. BOARD ASS'Y (SGJ-1308A-M2) 3-6
CRT SOCKET P.W. BOARD ASS'Y (SGJ-3304A-M2) 3-8
AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2) 3-9
FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2) 3-10
LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2) 3-10
USB P.W. BOARD ASS'Y (SGJ-8302A-M2) 3-10
L/F P.W. BOARD ASS'Y (SGJ-9302A-M2) 3-10
ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2) 3-10

PRINTED WIRING BOARD PARTS LIST [AV-27F577/S] 3-11
MAIN P.W. BOARD ASS'Y (SGJ-1302A-M2) 3-11
CRT SOCKET P.W. BOARD ASS'Y (SGJ-3302A-M2) 3-13
AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2) 3-14
FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2) 3-14
LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2) 3-14
USB P.W. BOARD ASS'Y (SGJ-8302A-M2) 3-14
L/F P.W. BOARD ASS'Y (SGJ-9302A-M2) 3-14
ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2) 3-14

PRINTED WIRING BOARD PARTS LIST [AV-32F577/R] 3-15
MAIN P.W. BOARD ASS'Y (SGJ-1313A-M2) 3-15
CRT SOCKET P.W. BOARD ASS'Y (SGJ-3305A-M2) 3-17
AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2) 3-18
FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2) 3-18
LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2) 3-18
USB P.W. BOARD ASS'Y (SGJ-8302A-M2) 3-18
L/F P.W. BOARD ASS'Y (SGJ-9301A-M2) 3-18
ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2) 3-18

PRINTED WIRING BOARD PARTS LIST [AV-32F577/Y] 3-19
MAIN P.W. BOARD ASS'Y (SGJ-1301A-M2) 3-19
CRT SOCKET P.W. BOARD ASS'Y (SGJ-3301A-M2) 3-21
AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2) 3-22
FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2) 3-22
LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2) 3-22
USB P.W. BOARD ASS'Y (SGJ-8302A-M2) 3-22
L/F P.W. BOARD ASS'Y (SGJ-9301A-M2) 3-22
ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2) 3-22

PRINTED WIRING BOARD PARTS LIST [AV-32F577/Z] 3-23
MAIN P.W. BOARD ASS'Y (SGJ-1307A-M2) 3-23
CRT SOCKET P.W. BOARD ASS'Y (SGJ-3303A-M2) 3-25
AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2) 3-26
FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2) 3-26
LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2) 3-26
USB P.W. BOARD ASS'Y (SGJ-8302A-M2) 3-26
L/F P.W. BOARD ASS'Y (SGJ-9301A-M2) 3-26
ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2) 3-26
REMOTE CONTROL UNIT PARTS LIST (RM-C1290G-1C) 3-27
PACKING 3-27
PACKING PARTS LIST 3-27

USING P.W. BOARD & REMOTE CONTROL UNIT

P.W.B ASS'Y name	P.W.B ASS'Y No.				
	AV-27F577/R	AV-27F577/S	AV-32F577/R	AV-32F577/Y	AV-32F577/Z
MAIN P.W.B	SGJ-1308A-M2	SGJ-1302A-M2	SGJ-1313A-M2	SGJ-1301A-M2	SGJ-1307A-M2
CRT SOCKET P.W.B	SGJ-3304A-M2	SGJ-3302A-M2	SGJ-3305A-M2	SGJ-3301A-M2	SGJ-3303A-M2
AV SW P.W.B	SGJ-5301A-M2	←	←	←	←
FRONT CONTROL P.W.B	SGJ-6301A-M2	←	←	←	←
LED&POWER SW P.W.B	SGJ-7301A-M2	←	←	←	←
USB P.W.B	SGJ-8302A-M2	←	←	←	←
L/F P.W.B	SGJ-9302A-M2	←	SGJ-9301A-M2	←	←
ATSC TUNER MODULE P.W.B	SSD-2302A-M2	←	←	←	←
REMOTE CONTROL UNIT	RM-C1290G-1C	←	←	←	←

EXPLODED VIEW PARTS LIST -1

⚠	Ref.No.	Part No.	Part Name	Description	Local
⚠	V01	A68ELH021X201	PICTURE TUBE (ITC)	Inc.DEF YOKE, PC MAGNET, WEDGE	AV-27F577R
⚠	V01	A68QCP693X003	PICTURE TUBE (ITC)	Inc.DEF YOKE, PC MAGNET, WEDGE	AV-27F577S
⚠	V01	A80ALB20X09	PICTURE TUBE (ITC)	Inc.DEF YOKE, PC MAGNET, WEDGE	AV-32F577R
⚠	V01	A80AKS90X03	PICTURE TUBE (ITC)	Inc.DEF YOKE, PC MAGNET, WEDGE	AV-32F577Y
⚠	V01	A80ERF182X17L	PICTURE TUBE (ITC)	Inc.DEF YOKE, PC MAGNET, WEDGE	AV-32F577Z
⚠	L01	QQW0090-001	DEG COIL		AV-27F577R,AV-27F577S
⚠	L01	QQW0116-001	DEG COIL		AV-32F577R,AV-32F577Y
⚠	L01	QQW0176-001	DEG COIL		AV-32F577Z
⚠	T502	QQH0175-001	FB TRANSFER		
	1	CM48006-010-C	JVC MARK		
	2	LC30191-003A-A	REMOCON WINDOW		
	3	LC20628-001D-A	DOOR		
	4	CM48229-00A-C	DOOR LATCH		
	5	LC31238-004A-A	OPERATION SHEET		
	6	LC31237-001B-A	POWER KNOB		
	7	CM36481-002A-A	SPRING		
⚠	8	LC10878-018A-A	FRONT CABINET ASSY		AV-27F577R,AV-27F577S
⚠	8	LC11048-023A-A	FRONT CABINET ASSY		AV-32F577R,AV-32F577Y,AV-32F577Z
	9	LC20217-004B-A	CONTROL KNOB		
	10	A48457-4-S	SPRING		
	11	WJY0016-001A-E	E-BRAIDED ASSY		AV-27F577R,AV-27F577S
	11	WJY0016-002A-E	E-BRAIDED ASSY		AV-32F577R,AV-32F577Y,AV-32F577Z
	12	WJY0013-003A-E	E-BRAIDED ASSY		
⚠	13	LC10880-002A-A	REAR COVER		AV-27F577R,AV-27F577S
⚠	13	LC11042-002A-A	REAR COVER		AV-32F577R,AV-32F577Y,AV-32F577Z
	14	QYSBSFG4016ZA	TAP SCREW	M4 x 16mm(x12)	
⚠	15	LC22070-001B-A	AV TERMINAL BOARD		
	16	QYSBSB3010ZA	TAP SCREW	M3 x 10mm(x4)	
⚠	17	QMPD200-200-JC	POWER CORD(US/CA)	2m BLACK	
⚠	18	LC20106-001D-A	POWER CORD CLAMP		
⚠	19	LC10883-003A-A	CHASSIS BASE		
	20	QAS0101-001	SPEAKER	SP01/SP02(x2)	
	21	GQ40014-002A-A	TAPPING SCREW	(x8)	AV-27F577R,AV-27F577S
	22	QYSBSB4012ZA	TAP SCREW	M4 x 12mm(x4)	AV-32F577R,AV-32F577Y,AV-32F577Z
	23	LC20629-001B-A	SPEAKER HOLDER	(x2)	AV-32F577R,AV-32F577Y,AV-32F577Z
	24	LC40226-005A-H	SPACER	(x4)	AV-32F577R,AV-32F577Y,AV-32F577Z
	25	LC41029-002A-A	TAPPING SCREW	(x4)	AV-32F577R,AV-32F577Y,AV-32F577Z
	26	WJJ0475-001A-E	SPEAKER WIRE	SP - MAIN CN00M	AV-27F577R,AV-27F577S
	26	WJJ0475-002A-E	SPEAKER WIRE	SP - MAIN CN00M	AV-32F577R,AV-32F577Y,AV-32F577Z
	27	WJJ0711-001A-E	SIN CR C-C WIRE	ATSC TUNER MODULE - USB CN800L	
⚠	101	SGJ-1308A-M2	MAIN PWB		AV-27F577R
⚠	101	SGJ-1302A-M2	MAIN PWB		AV-27F577S
⚠	101	SGJ-1313A-M2	MAIN PWB		AV-32F577R
⚠	101	SGJ-1301A-M2	MAIN PWB		AV-32F577Y
⚠	101	SGJ-1307A-M2	MAIN PWB		AV-32F577Z
⚠	102	SGJ-3304A-M2	CRT SOCKET PWB		AV-27F577R
⚠	102	SGJ-3302A-M2	CRT SOCKET PWB		AV-27F577S
⚠	102	SGJ-3305A-M2	CRT SOCKET PWB		AV-32F577R
⚠	102	SGJ-3301A-M2	CRT SOCKET PWB		AV-32F577Y
⚠	102	SGJ-3303A-M2	CRT SOCKET PWB		AV-32F577Z
⚠	103	SGJ-5301A-M2	AV SW PWB		
⚠	104	SGJ-6301A-M2	FRONT CONTROL PWB		
⚠	105	SGJ-7301A-M2	LED&POWER SW PWB		
⚠	106	SGJ-9302A-M2	L/F PWB		AV-27F577R,AV-27F577S
⚠	106	SGJ-9301A-M2	L/F PWB		AV-32F577R,AV-32F577Y,AV-32F577Z
⚠	107	SGJ-8302A-M2	USB PWB		
⚠	108	SSD-2302A-M2	ATSC TUNER MODULE PWB		

EXPLODED VIEW -1



PRINTED WIRING BOARD PARTS LIST [AV-27F577/R]

MAIN P.W. BOARD ASS'Y (SGJ-1308A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC101	CXA2094Q-X	IC		
IC201	TM8812CSDNG6H60	IC(MCU)		
IC421	LA78041	IC		
IC601	NJW1143AV-W	IC		
IC651	LA42072NL	IC		
IC702	ATE08-27F577R	IC	(SERVICE)	
IC703	S-80840CLNB-G-W	IC		
IC704	S78L05-T	IC		
IC851	PQ1CG2032FZ	IC		
IC852	S7809PI	IC		
IC853	PQ05RD21SSJH	IC		
IC855	PQ070XF01SZH	IC		
IC856	MP2263DN-C053-X	IC		
⚠IC911	STR-G9626-F3	IC		
⚠IC921	SE135N	IC		
Q001	2SK1374-X	MOS FET		
Q002	2SK1374-X	MOS FET		
Q003	2SK1374-X	MOS FET		
Q004	2SK1374-X	MOS FET		
Q005	RT1N440C-X	TRANSISTOR		
Q352	2SC3928A/QR/-X	TRANSISTOR		
Q501	2SC4212/Z1/	TRANSISTOR		
⚠Q511	TT2202-YD	POWER TRANST		
⚠Q531	2SC2785/JH/-T	TRANSISTOR		
Q532	2SA1530A/QR/-X	TRANSISTOR		
Q541	2SA1530A/QR/-X	TRANSISTOR		
Q542	2SA1530A/QR/-X	TRANSISTOR		
Q543	2SD1267A/QP/	POW TRANSISTOR		
Q671	RT1N441C-X	TRANSISTOR		
Q682	2SA1530A/QR/-X	TRANSISTOR		
Q683	RT1N441C-X	TRANSISTOR		
Q684	2SC3928A/QR/-X	TRANSISTOR		
Q701	2SA1530A/QR/-X	TRANSISTOR		
Q730	RT1N441C-X	TRANSISTOR		
Q951	2SD1383K/AB/-X	SI TRANSISTOR		
Q971	2SA1208/ST/Z1-T	TRANSISTOR		
D308	MTZJ5.1B-T2	Z DIODE		
D309	MTZJ5.1B-T2	Z DIODE		
D310	MTZJ5.1B-T2	Z DIODE		
D352	MTZJ9.1C-T2	Z DIODE		
D353	1SS133-T2	SI DIODE		
D354	MTZJ3.3A-T2	Z DIODE		
D421	1N4003SG-T2	SI DIODE		
D422	MTZJ75-T2	Z DIODE		
D501	RH3G-F1	SI DIODE		
D502	RU3AM-LFC4	SI DIODE		
D521	FR105GT-T3	SI DIODE		
D523	FR105GT-T3	SI DIODE		
D525	1SS81-T5	SI DIODE		
D526	1SS81-T5	SI DIODE		
D527	1SR124-400A-T2	SI DIODE		
D529	MTZJ9.1C-T2	Z DIODE		
⚠D531	MA4068N/Z1/-T2	Z DIODE		
D535	1SS133-T2	SI DIODE		
D681	1SS133-T2	SI DIODE		
D682	1SS133-T2	SI DIODE		
D683	1SS133-T2	SI DIODE		
D684	1SS133-T2	SI DIODE		
D701	1SS133-T2	SI DIODE		
D705	1SS133-T2	SI DIODE		
D730	1SS133-T2	SI DIODE		
D851	EC31QS04-X	SB DIODE		
D852	1SS133-T2	SI DIODE		
D855	1SS133-T2	SI DIODE		
D856	EC30HA03L-X	SB DIODE		
D857	EC30HA03L-X	SB DIODE		
D861	PTZ3.9B-X	Z DIODE		
D862	PTZ3.9B-X	Z DIODE		
⚠D901	GSIB460	BRIDGE DIODE		
D910	MA700A-T2	SB DIODE		
D911	FR105GT-T3	SI DIODE		
D912	FR105GT-T3	SI DIODE		
D913	1SS133-T2	SI DIODE		
D914	1SS133-T2	SI DIODE		
D915	SARS01-T2	FR DIODE		
D917	MTZJ30A-T2	Z DIODE		
D918	MTZJ5.1C-T2	Z DIODE		
D920	1SS133-T2	SI DIODE		
D931	RU4AM-LFT2	SI DIODE		
D933	HER202G-FL	SI DIODE		
D935	HER202G-FL	SI DIODE		
D938	HER202G-FL	SI DIODE		
D941	MTZJ33A-T2	Z DIODE		
D945	MTZJ9.1B-T2	Z DIODE		
D952	1SS133-T2	SI DIODE		
D953	1SS133-T2	SI DIODE		
D954	1N4003SG-T2	SI DIODE		
D955	1N4003SG-T2	SI DIODE		
D956	1N4003SG-T2	SI DIODE		
D957	1N4003SG-T2	SI DIODE		
D972	MTZJ15C-T2	Z DIODE		
D973	1SS133-T2	SI DIODE		
C009	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C101	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C102	NCB31HK-562X	C CAPACITOR	5600pF 50V K	
C103	NCB31EK-123X	C CAPACITOR	0.012uF 25V K	
C104	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C105	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C106	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C107	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C108	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C109	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C110	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C111	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C112	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C113	NCB31HK-272X	C CAPACITOR	2700pF 50V K	
C114	NCB31HK-473X	C CAPACITOR	0.047uF 50V K	
C115	QETN1HM-335Z	E CAPACITOR	3.3uF 50V M	
C116	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C117	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C118	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C119	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C120	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C121	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C202	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C203	NCB31HK-152X	C CAPACITOR	1500pF 50V K	
C221	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C222	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C237	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C241	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C242	NCB21AK-225X	C CAPACITOR	2.2uF 10V K	
C243	QETN0JM-227Z	E CAPACITOR	220uF 6.3V M	
C244	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C281	QFVF1HJ-474Z	MF CAPACITOR	0.47uF 50V J	
C282	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C283	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C284	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C285	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C286	NCB21CK-474X	C CAPACITOR	0.47uF 16V K	
C287	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C288	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C289	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C290	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C291	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C301	NCZ1064-225X	C CAPACITOR	2.2uF	
C302	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	
C352	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
C354	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C360	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C391	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C392	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C422	QFN32AK-102Z	M CAPACITOR	1000pF 100V K	
C424	QETN1VM-107Z	E CAPACITOR	100uF 35V M	
C425	QETN1VM-477Z	E CAPACITOR	470uF 35V M	
C427	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C428	QETM1EM-228	E CAPACITOR	2200uF 25V M	
C431	QFLC2AK-563Z	M CAPACITOR	0.056uF 100V K	
C433	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
C435	NCB31HK-183X	C CAPACITOR	0.018uF 50V K	
C440	QCS32HJ-100Z	C CAPACITOR	10pF 500V J	
C501	QCB32HK-151Z	C CAPACITOR	150pF 500V K	
C502	QCB32HK-331Z	C CAPACITOR	330pF 500V K	
C503	QEHR2CM-105Z	E CAPACITOR	1uF 160V M	
C504	QEZ0203-107	E CAPACITOR	100uF 160V M	
C507	QEM61HK-475Z	E CAPACITOR	4.7uF 50V K	
C508	QEM61HK-475Z	E CAPACITOR	4.7uF 50V K	
⚠C510	QFZ0200-482	MPP CAPACITOR	4800pF 1.5kV H	
⚠C513	QFZ0196-113	MPP CAPACITOR	0.011uF 1.5kV H	
C514	QFP32GJ-183	PP CAPACITOR	0.018uF 400V J	
C515	QFZ0197-404	MPP CAPACITOR	0.4uF 250V J	
C516	QCB32HK-561Z	C CAPACITOR	560pF 500V K	
C521	QETN2EM-106Z	E CAPACITOR	10uF 250V M	
C523	QEHR1VM-477Z	E CAPACITOR	470uF 35V M	
C525	QETN1VM-107Z	E CAPACITOR	100uF 35V M	
C526	QFV21HJ-824Z	MF CAPACITOR	0.82uF 50V J	
C527	QFLC2AJ-103Z	M CAPACITOR	0.01uF 100V J	
C531	QCB32HK-471Z	C CAPACITOR	470pF 500V K	
C533	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C621	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	

⚠Ref No.	Part No.	Part Name	Description Local
C623	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C624	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C625	NCB31HK-822X	C CAPACITOR	8200pF 50V K
C627	NCB31CK-105X	C CAPACITOR	1uF 16V K
C628	NCB31CK-105X	C CAPACITOR	1uF 16V K
C629	NCB31CK-105X	C CAPACITOR	1uF 16V K
C630	NCB31CK-105X	C CAPACITOR	1uF 16V K
C631	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C633	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C634	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C635	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C636	QETN1HM-105Z	E CAPACITOR	1uF 50V M
C637	NCB31CK-105X	C CAPACITOR	1uF 16V K
C638	NCB31CK-105X	C CAPACITOR	1uF 16V K
C651	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C652	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C653	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C654	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C655	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C656	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C661	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C662	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C663	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C666	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C671	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C683	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C684	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C701	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C702	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C703	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C704	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C705	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C706	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C708	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C709	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C710	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C711	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C712	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C728	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C730	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C807	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C851	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C852	NCB31EK-104X	C CAPACITOR	0.1uF 25V K
C853	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C854	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C856	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C857	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C858	QEZ0256-128	E CAPACITOR	1200uF 10V M
C861	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C865	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C866	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C868	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C869	QCZ0397-106Z	C CAPACITOR	10uF 25V M
C871	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C874	NCB31EK-273X	C CAPACITOR	0.027uF 25V K
C876	QEZ0256-128	E CAPACITOR	1200uF 10V M
C880	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
⚠C905	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C907	QEZ0644-567	E CAPACITOR	560uF 200V K
⚠C908	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C912	QCZ0340-222	C CAPACITOR	2200pF 2kV K
C913	QFLC1HJ-471Z	M CAPACITOR	470pF 50V J
C914	QETN1HM-107Z	E CAPACITOR	100uF 50V M
C916	NDC31HJ-331X	C CAPACITOR	330pF 50V J
C917	NCB31HK-182X	C CAPACITOR	1800pF 50V K
C918	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C919	QFP32GJ-103	PP CAPACITOR	0.01uF 400V J
C931	QEZ0203-227	E CAPACITOR	220uF 160V M
C932	QETN1CM-108Z	E CAPACITOR	1000uF 16V M
C933	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C934	NDC31HJ-221X	C CAPACITOR	220pF 50V J
C935	QETN1VM-108Z	E CAPACITOR	1000uF 35V M
C937	QCZ0340-102	C CAPACITOR	1000pF 2kV K
C938	QETN1EM-227Z	E CAPACITOR	220uF 25V M
C939	QCB32HK-152Z	C CAPACITOR	1500pF 500V K
C941	QCB32HK-102Z	C CAPACITOR	1000pF 500V K
C942	QEHR1HM-105Z	E CAPACITOR	1uF 50V M
C943	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C951	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C952	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C971	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C972	QETN1EM-476Z	E CAPACITOR	47uF 25V M
⚠C998	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
⚠C999	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
R001	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R002	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R003	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R004	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R005	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R006	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R007	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R008	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R101	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R102	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R103	NRSA63J-105X	MG RESISTOR	1MΩ 1/16W J
R104	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R105	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R106	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R107	NRSA63D-623X	MG RESISTOR	62kΩ 1/16W D
R108	NRSA63J-332X	MG RESISTOR	3.3kΩ 1/16W J
R109	NRSA63D-302X	MG RESISTOR	3kΩ 1/16W D
R110	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R201	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R227	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R281	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J
R282	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R283	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R286	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R287	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R288	NRSA02J-471X	MG RESISTOR	470Ω 1/10W J
R289	NRSA63J-154X	MG RESISTOR	150kΩ 1/16W J
R290	NRSA02J-561X	MG RESISTOR	560Ω 1/10W J
R292	NRSA63J-124X	MG RESISTOR	120kΩ 1/16W J
R293	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J
R294	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R295	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R296	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R301	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R302	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R303	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R304	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R305	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R306	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R318	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R319	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R354	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R355	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R356	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R359	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R421	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R423	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R424	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R426	NRSA63J-183X	MG RESISTOR	18kΩ 1/16W J
R427	QRT029J-1R5	MF RESISTOR	1.5Ω 2W J
R429	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J
R431	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J
R432	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R433	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R434	QRL029J-181	OMF RESISTOR	180Ω 2W J
R435	QRE121J-102Y	C RESISTOR	1kΩ 1/2W J
R441	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R502	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R503	QRE121J-103Y	C RESISTOR	10kΩ 1/2W J
R504	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R505	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R511	QRE121J-220Y	C RESISTOR	22Ω 1/2W J
R512	QRE121J-681Y	C RESISTOR	680Ω 1/2W J
R516	QRZ0221-2R0	OMF RESISTOR	2Ω 7W K
R524	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R526	QRE121J-272Y	C RESISTOR	2.7kΩ 1/2W J
R527	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R528	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R529	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
⚠R531	QRE121J-391Y	C RESISTOR	390Ω 1/2W J
R532	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R533	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R534	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
⚠R535	NRVA02D-272X	CMF RESISTOR	2.7kΩ 1/10W D
R536	QRE121J-470Y	C RESISTOR	47Ω 1/2W J
R537	NRVA02D-752X	CMF RESISTOR	7.5kΩ 1/10W D
R538	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
R543	QRE121J-122Y	C RESISTOR	1.2kΩ 1/2W J
R544	QRE121J-392Y	C RESISTOR	3.9kΩ 1/2W J
R545	QRE121J-822Y	C RESISTOR	8.2kΩ 1/2W J
R546	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
R547	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R548	QRE121J-152Y	C RESISTOR	1.5kΩ 1/2W J
R553	QRL039J-390	OMF RESISTOR	39Ω 3W J
⚠R554	QRK126J-150X	UNF C RESISTOR	15Ω 1/2W J
R555	QRT029J-3R3	MF RESISTOR	3.3Ω 2W J
R621	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R624	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R625	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R631	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R638	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R639	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R651	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R652	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J

⚠Ref No.	Part No.	Part Name	Description	Local
R653	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R654	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R661	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	
R662	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R663	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R664	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R672	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R683	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R685	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R686	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R687	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R688	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R689	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R690	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R691	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R701	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R702	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R704	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R705	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R706	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R707	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R708	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R709	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R710	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R711	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R716	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R718	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R729	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R731	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R732	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R733	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R734	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R735	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R736	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R738	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R739	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R740	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R769	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R772	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R811	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R816	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R821	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R827	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R852	NRSA63D-123X	MG RESISTOR	12kΩ 1/16W D	
R853	NRSA63D-182X	MG RESISTOR	1.8kΩ 1/16W D	
R854	NRSA63D-122X	MG RESISTOR	1.2kΩ 1/16W D	
R855	QRL029J-820	OMF RESISTOR	82Ω 2W J	
R858	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R860	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	
R861	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R862	NRSA63D-332X	MG RESISTOR	3.3kΩ 1/16W D	
R863	NRSA63D-103X	MG RESISTOR	10kΩ 1/16W D	
R865	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R879	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R880	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R881	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J	
R901	QRF074K-1R2	UNF WW RESISTOR	1.2Ω 7W K	
R909	QRG01GJ-470	OMF RESISTOR	47Ω 1W J	
R911	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R912	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R913	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
⚠R914	QRK126J-681X	UNF C RESISTOR	680Ω 1/2W J	
R915	QRK129J-6R8	UNF C RESISTOR	6.8Ω 1/2W J	
⚠R917	QRK126J-332X	UNF C RESISTOR	3.3kΩ 1/2W J	
R918	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R919	QRE121J-684Y	C RESISTOR	680kΩ 1/2W J	
R924	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R930	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R940	QRE121J-181Y	C RESISTOR	180Ω 1/2W J	
R941	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R942	QRT039J-R68	MF RESISTOR	0.68Ω 3W J	
R950	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R951	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R952	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R953	QRE121J-820Y	C RESISTOR	82Ω 1/2W J	
R972	NRVA02D-122X	CMF RESISTOR	1.2kΩ 1/10W D	
R973	NRVA02D-332X	CMF RESISTOR	3.3kΩ 1/10W D	
R975	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R977	QRE121J-473Y	C RESISTOR	47kΩ 1/2W J	
R978	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
L001	QQL244K-6R8Z	PEAKING COIL	6.8uH K	
L241	QQL244K-220Z	PEAKING COIL	22uH K	
L391	QQL244K-220Z	PEAKING COIL	22uH K	
L511	QQR1165-001	LINEARITY COIL		
L512	QQLZ036-821	COIL	820uH K	
L521	QQLZ026-360	COIL	36uH	
L704	QQL244K-220Z	PEAKING COIL	22uH K	
L705	QQL244K-220Z	PEAKING COIL	22uH K	

⚠Ref No.	Part No.	Part Name	Description	Local
L851	QQR1401-001	CHOKE COIL		
L853	QQL26AK-330Z	CHOKE COIL	33uH K	
L854	QQL26AK-470Z	CHOKE COIL	47uH K	
L855	QQL26AK-100Z	CHOKE COIL	10uH K	
L860	QQL28AK-150	COIL	15uH K	
L861	QQR1401-001	CHOKE COIL		
L931	QQL26AK-470Z	CHOKE COIL	47uH K	
L933	QQL26AK-470Z	CHOKE COIL	47uH K	
L937	QQL26AK-470Z	CHOKE COIL	47uH K	
L940	QQR0582-001Z	FERRITE BEADS		
T501	QQR1414-001	DRIVE TRANSF		
⚠T921	QQS0376-001	SW TRANSF		
CN001	QGB1221J1-80	CONNECTOR	B-B (1-80)	
CN002	QGB1505J1-35	CONNECTOR	B-B (1-35)	
CN00F	QJB003-032213-E	SIN ID C-B WIRE		
CN00W	WJK0200-004A-E	E-SI C WIRE C-B		
⚠CP936	ICP-N70-T	IC PROTECTOR	2.5A	
⚠FR525	QRZ9017-4R7	FUSI RESISTOR	4.7Ω 1/4W J	
K002	QQR0621-002Z	FERRITE BEADS		
K004	QQR0621-002Z	FERRITE BEADS		
K007	NQR0499-002X	FERRITE BEADS		
K008	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
K401	QQR0621-002Z	FERRITE BEADS		
K912	QQR0582-001Z	FERRITE BEADS		
K916	QQR0582-001Z	FERRITE BEADS		
K917	QQR0582-001Z	FERRITE BEADS		
K918	QQR0582-001Z	FERRITE BEADS		
K920	QQR1139-001	FERRITE BEADS		
K931	QQR0582-001Z	FERRITE BEADS		
K932	QQR0582-001Z	FERRITE BEADS		
K933	QQR0582-001Z	FERRITE BEADS		
K935	QQR0582-001Z	FERRITE BEADS		
K937	QQR0582-001Z	FERRITE BEADS		
⚠PC921	PS2581AL1/QW/	PHOTO COUPLER		
⚠RY951	QSK0085-001	RELAY		
S421	QSW1142-001	LEVER SWITCH	V.CENTER	
⚠TH901	QAD0132-3R0	P THERMISTOR	3Ω	
X701	QAX0767-001Z	CRYSTAL	8.000000MHz	

CRT SOCKET P.W. BOARD ASS'Y (SGJ-3304A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
Q3103	2SC3928A/QR/-X	TRANSISTOR		
Q3107	2SA2005/DE/	POW TRANSISTOR		
Q3108	2SC5511/DE/	POW TRANSISTOR		
Q3109	2SC3928A/QR/-X	TRANSISTOR		
Q3304	2SC4544-LB	POW TRANSISTOR		
Q3305	2SC4544-LB	POW TRANSISTOR		
Q3306	2SC4544-LB	POW TRANSISTOR		
Q3351	2SA1530A/QR/-X	TRANSISTOR		
D3105	RH1S-T3	SI DIODE		
D3106	RH1S-T3	SI DIODE		
D3331	1SS133-T2	SI DIODE		
D3351	1SS133-T2	SI DIODE		
D3352	1SS133-T2	SI DIODE		
D3353	1SS133-T2	SI DIODE		
D3354	1SS133-T2	SI DIODE		
C3101	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C3113	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3114	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3115	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3117	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3118	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C3119	QETN1AM-107Z	E CAPACITOR	100uF 10V M	
C3120	QETN1AM-337Z	E CAPACITOR	330uF 10V M	
C3121	QCS32HJ-151Z	C CAPACITOR	150pF 500V J	
C3127	NDC31HJ-471X	C CAPACITOR	470pF 50V J	
C3301	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3302	NDC31HJ-391X	C CAPACITOR	390pF 50V J	
C3303	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3323	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C3331	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3332	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3333	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3351	QETN1CM-477Z	E CAPACITOR	470uF 16V M	
C3363	QCZ0121-102	C CAPACITOR	1000pF 3KV Z	
R3115	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3116	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3122	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
R3123	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3124	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3125	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	

⚠Ref No.	Part No.	Part Name	Description	Local
R3126	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3127	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3128	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3129	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3130	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3131	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3132	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R3134	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3136	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R3139	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3142	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R3143	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3144	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3145	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3146	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3148	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3301	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3302	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3303	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3304	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3305	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3306	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3307	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3308	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3309	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3310	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3311	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3312	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3313	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3314	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3315	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3325	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3326	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3327	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3331	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3332	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3333	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3334	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R3335	NRSA63J-391X	MG RESISTOR	390Ω 1/16W J	
R3351	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	
R3354	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
L3304	QQL244K-470Z	PEAKING COIL	47uH K	
CN300A	WJA0029-001A-E	E-SI ID WIRE		
CN300E	QJB003-073226-E	SIN ID C-B WIRE		
CN30E2	QUB130-38A6AS-E	SIN TWIST WIRE		
CN30E4	QUB130-38A6AS-E	SIN TWIST WIRE		
K3104	QQR1114-001Z	FERRITE BEADS		
K3105	QQR1114-001Z	FERRITE BEADS		
⚠SK3001	QNZ0536-002	CRT SOCKET		

AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC5001	CXA2089Q-X	IC		
Q5001	2SC3928A/QR/-X	TRANSISTOR		
Q5002	2SC3928A/QR/-X	TRANSISTOR		
Q5003	2SC3928A/QR/-X	TRANSISTOR		
Q5004	2SA1530A/QR/-X	TRANSISTOR		
Q5005	2SA1530A/QR/-X	TRANSISTOR		
Q5006	2SA1530A/QR/-X	TRANSISTOR		
Q5007	2SA1530A/QR/-X	TRANSISTOR		
Q5008	2SA1530A/QR/-X	TRANSISTOR		
Q5009	2SA1530A/QR/-X	TRANSISTOR		
Q5601	RT6N230C-X	DIGI TRANSISTOR		
Q5602	RT6N230C-X	DIGI TRANSISTOR		
Q5603	2SA1530A/QR/-X	TRANSISTOR		
D5001	MTZJ9.1C-T2	Z DIODE		
D5002	MTZJ9.1C-T2	Z DIODE		
D5003	MTZJ9.1C-T2	Z DIODE		
D5007	MTZJ9.1C-T2	Z DIODE		
D5008	MTZJ9.1C-T2	Z DIODE		
D5009	MTZJ9.1C-T2	Z DIODE		
D5010	MTZJ9.1C-T2	Z DIODE		
D5011	MTZJ9.1C-T2	Z DIODE		
D5017	MTZJ9.1C-T2	Z DIODE		
D5018	MTZJ9.1C-T2	Z DIODE		
D5019	MTZJ9.1C-T2	Z DIODE		
D5601	MTZJ9.1C-T2	Z DIODE		
D5602	MTZJ9.1C-T2	Z DIODE		
C5001	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C5002	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5003	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5004	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C5005	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C5006	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5007	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5008	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5009	QENC1CM-106Z	BP E CAPACITOR	10uF 16V M	
C5010	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C5011	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C5012	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5013	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5014	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5015	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5016	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5017	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5018	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5019	NCF31CZ-104X	C CAPACITOR	0.1uF 16V Z	
C5020	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5021	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5022	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5023	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5024	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C5025	QETN1CM-476Z	E CAPACITOR	47uF 16V M	
C5026	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C5027	NCF31CZ-104X	C CAPACITOR	0.1uF 16V Z	
C5028	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C5029	NDC31HJ-151X	C CAPACITOR	150pF 50V J	
C5030	NDC31HJ-101X	C CAPACITOR	100pF 50V J	
C5031	NDC31HJ-220X	C CAPACITOR	22pF 50V J	
C5032	NDC31HJ-271X	C CAPACITOR	270pF 50V J	
C5033	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C5034	NDC31HJ-330X	C CAPACITOR	33pF 50V J	
C5035	NDC31HJ-271X	C CAPACITOR	270pF 50V J	
C5036	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C5037	NDC31HJ-330X	C CAPACITOR	33pF 50V J	
C5601	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C5602	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
R5001	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5002	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5003	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5004	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R5005	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R5006	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5007	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
R5008	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J	
R5009	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J	
R5010	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5011	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5012	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5013	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5014	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5015	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
R5016	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J	
R5017	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J	
R5018	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5019	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5020	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5021	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5022	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R5023	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
R5024	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J	
R5025	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J	
R5026	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5027	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5028	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5029	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5030	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R5031	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R5032	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5033	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5034	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5035	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5036	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5037	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5038	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5039	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5040	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5041	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5042	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5043	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5044	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5045	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5046	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R5047	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5048	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5049	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R5050	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R5051	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5052	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	

⚠Ref No.	Part No.	Part Name	Description	Local
R5053	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5054	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5055	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5056	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5057	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5058	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5059	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R5060	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R5061	NRSA63J-121X	MG RESISTOR	120Ω 1/16W J	
R5062	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R5063	NRSA63J-121X	MG RESISTOR	120Ω 1/16W J	
R5064	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R5065	NRSA63J-121X	MG RESISTOR	120Ω 1/16W J	
R5066	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R5076	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5077	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5078	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5601	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5602	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5603	NRSA63J-823X	MG RESISTOR	82kΩ 1/16W J	
R5604	NRSA63J-823X	MG RESISTOR	82kΩ 1/16W J	
R5605	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R5606	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R5607	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5608	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R5609	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5610	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R5612	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R5613	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
L5001	NQL092K-4R7X	COIL	4.7uH K	
L5002	NQL013K-150X	P COIL	15uH K	
L5003	NQL013K-150X	P COIL	15uH K	
CN5002	QGB1505K1-35	CONNECTOR	B-B (1-35)	
J5001	QNZ0454-001	AV JACK	INPUT-1(S/V/L/R)	
J5002	QNN0349-002	PIN JACK	INPUT-2(COMPONENT)	
J5003	QNN0348-001	PIN JACK	INPUT-2(L/R)	
J5004	QNN0348-001	PIN JACK	AUDIO OUT	

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
C6401	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C6402	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C6403	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
R6401	NRSA63J-750X	MG RESISTOR	75Ω 1/16W J	
R6402	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R6403	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R6701	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J	
R6702	NRSA63J-562X	MG RESISTOR	5.6kΩ 1/16W J	
R6703	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J	
R6704	NRSA63J-562X	MG RESISTOR	5.6kΩ 1/16W J	
CN600B	QJL001-051010-E	SIN CR C-C WIRE		
CN600G	QJB003-064426-E	SIN ID C-B WIRE		
CN600R	QJB003-054610-E	SIN ID C-B WIRE		
J6401	QNN0706-001	PIN JACK	INPUT-3(V)	
J6402	QNN0706-002	PIN JACK	INPUT-3(L)	
J6403	QNN0707-003	PIN JACK	INPUT-3(R)	
LC6401	QQR1459-001	EMI F. COIL		
LC6402	QQR1459-001	EMI F. COIL		
LC6403	QQR1459-001	EMI F. COIL		
S6702	QSW0619-003Z	PUSH SWITCH	MENU	
S6703	QSW0619-003Z	PUSH SWITCH	CH-	
S6704	QSW0619-003Z	PUSH SWITCH	CH+	
S6705	QSW0619-003Z	PUSH SWITCH	VOL-	
S6706	QSW0619-003Z	PUSH SWITCH	VOL+	

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC7701	GP1UM281QKVF	IR DETECT UNIT		
Q7701	RT1P241C-X	DIGI TRANSISTOR		
D7701	LG22440	LED	POWER	
C7701	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
R7701	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J	
R7702	NRSA63J-561X	MG RESISTOR	560Ω 1/16W J	
R7703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R7704	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
S7701	QSW0847-001	TACT SWITCH	POWER	

USB P.W. BOARD ASS'Y (SGJ-8302A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC8001	TPS2041BD-X	IC		
IC8501	QNZ0727-001	OPT CONNECTOR		
D8001	EDZC6.8B-X	Z DIODE		
D8002	EDZC6.8B-X	Z DIODE		
D8003	EDZC6.8B-X	Z DIODE		
D8004	EDZC6.8B-X	Z DIODE		
C8001	NDC31HJ-270X	C CAPACITOR	27pF 50V J	
C8002	NDC31HJ-270X	C CAPACITOR	27pF 50V J	
C8003	NDC31HJ-150X	C CAPACITOR	15pF 50V J	
C8004	NDC31HJ-150X	C CAPACITOR	15pF 50V J	
C8005	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C8006	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C8007	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C8501	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
R8001	NRSA63J-330X	MG RESISTOR	33Ω 1/16W J	
R8002	NRSA63J-330X	MG RESISTOR	33Ω 1/16W J	
R8501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
CN80E5	QUB190-06FXZ5-E	SIN TWIST WIRE		
J8001	QNZ0851-001	USB CONNECTOR		

L/F P.W. BOARD ASS'Y (SGJ-9302A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
⚠C901	QFZ9072-104	MM CAPACITOR	0.1uF AC250V K	
⚠C902	QFZ9072-473	MM CAPACITOR	0.047uF AC250V K	
⚠C903	QFZ9072-104	MM CAPACITOR	0.1uF AC250V K	
⚠C997	QCZ9079-102	C CAPACITOR	1000pF AC250V M	
⚠R998	QRZ9041-275	C RESISTOR	2.7MΩ 1/2W K	
R999	QRE121J-121Y	C RESISTOR	120Ω 1/2W J	
⚠T951	QQT0355-001	POWER TRANSF		
⚠F901	QMF51N1-5R0-J5	FUSE	5A AC125V	
⚠LF901	QQR0527-003	LINE FILTER		
⚠LF902	QQR0527-003	LINE FILTER		
⚠VA901	QAF0060-621	VARISTOR	620V	

ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
⚠IMD001	SSD-2302A-M2	ATSC TUNER MODULE PWB		

PRINTED WIRING BOARD PARTS LIST [AV-27F577/S]

MAIN P.W. BOARD ASS'Y (SGJ-1302A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC101	CXA2094Q-X	IC		
IC201	TM8812CSDNG6H60	IC(MCU)		
IC421	LA78041	IC		
IC601	NJW1143AV-W	IC		
IC651	LA42072NL	IC		
IC702	ATE08-27F577S	IC	(SERVICE)	
IC703	S-80840CLNB-G-W	IC		
IC704	S78L05-T	IC		
IC851	PQ1CG2032FZ	IC		
IC852	S7809PI	IC		
IC853	PQ05RD21SSJH	IC		
IC855	PQ070XF01SZH	IC		
IC856	MP2263DN-C053-X	IC		
⚠IC911	STR-G9626-F3	IC		
⚠IC921	SE135N	IC		
Q001	2SK1374-X	MOS FET		
Q002	2SK1374-X	MOS FET		
Q003	2SK1374-X	MOS FET		
Q004	2SK1374-X	MOS FET		
Q005	RT1N440C-X	TRANSISTOR		
Q352	2SC3928A/QR/-X	TRANSISTOR		
Q501	2SC4212/Z1/	TRANSISTOR		
⚠Q511	TT2202-YD	POWER TRANST		
⚠Q531	2SC2785/JH/-T	TRANSISTOR		
Q532	2SA1530A/QR/-X	TRANSISTOR		
Q541	2SA1530A/QR/-X	TRANSISTOR		
Q542	2SA1530A/QR/-X	TRANSISTOR		
Q543	2SD1267A/QP/	POW TRANSISTOR		
Q671	RT1N441C-X	TRANSISTOR		
Q682	2SA1530A/QR/-X	TRANSISTOR		
Q683	RT1N441C-X	TRANSISTOR		
Q684	2SC3928A/QR/-X	TRANSISTOR		
Q701	2SA1530A/QR/-X	TRANSISTOR		
Q730	RT1N441C-X	TRANSISTOR		
Q951	2SD1383K/AB/-X	SI TRANSISTOR		
Q971	2SA1208/ST/Z1-T	TRANSISTOR		
D308	MTZJ5.1B-T2	Z DIODE		
D309	MTZJ5.1B-T2	Z DIODE		
D310	MTZJ5.1B-T2	Z DIODE		
D352	MTZJ9.1C-T2	Z DIODE		
D353	1SS133-T2	SI DIODE		
D354	MTZJ3.3A-T2	Z DIODE		
D421	1N4003SG-T2	SI DIODE		
D422	MTZJ75-T2	Z DIODE		
D501	RH3G-F1	SI DIODE		
D502	RU3AM-LFC4	SI DIODE		
D521	FR105GT-T3	SI DIODE		
D523	FR105GT-T3	SI DIODE		
D525	1SS81-T5	SI DIODE		
D526	1SS81-T5	SI DIODE		
D527	1SR124-400A-T2	SI DIODE		
D529	MTZJ9.1C-T2	Z DIODE		
⚠D531	MA4068N/Z1/-T2	Z DIODE		
D535	1SS133-T2	SI DIODE		
D681	1SS133-T2	SI DIODE		
D682	1SS133-T2	SI DIODE		
D683	1SS133-T2	SI DIODE		
D684	1SS133-T2	SI DIODE		
D701	1SS133-T2	SI DIODE		
D705	1SS133-T2	SI DIODE		
D730	1SS133-T2	SI DIODE		
D851	EC31QS04-X	SB DIODE		
D852	1SS133-T2	SI DIODE		
D855	1SS133-T2	SI DIODE		
D856	EC30HA03L-X	SB DIODE		
D857	EC30HA03L-X	SB DIODE		
D861	PTZ3.9B-X	Z DIODE		
D862	PTZ3.9B-X	Z DIODE		
⚠D901	GSIB460	BRIDGE DIODE		
D910	MA700A-T2	SB DIODE		
D911	FR105GT-T3	SI DIODE		
D912	FR105GT-T3	SI DIODE		
D913	1SS133-T2	SI DIODE		
D914	1SS133-T2	SI DIODE		
D915	SARS01-T2	FR DIODE		
D917	MTZJ30A-T2	Z DIODE		
D918	MTZJ5.1C-T2	Z DIODE		
D920	1SS133-T2	SI DIODE		
D931	RU4AM-LFT2	SI DIODE		
D933	HER202G-FL	SI DIODE		
D935	HER202G-FL	SI DIODE		
D938	HER202G-FL	SI DIODE		
D941	MTZJ33A-T2	Z DIODE		
D945	MTZJ9.1B-T2	Z DIODE		
D952	1SS133-T2	SI DIODE		
D953	1SS133-T2	SI DIODE		
D954	1N4003SG-T2	SI DIODE		
D955	1N4003SG-T2	SI DIODE		
D956	1N4003SG-T2	SI DIODE		
D957	1N4003SG-T2	SI DIODE		
D972	MTZJ15C-T2	Z DIODE		
D973	1SS133-T2	SI DIODE		
C009	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C101	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C102	NCB31HK-562X	C CAPACITOR	5600pF	50V K
C103	NCB31EK-123X	C CAPACITOR	0.012uF	25V K
C104	NCB31CK-105X	C CAPACITOR	1uF	16V K
C105	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C106	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C107	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C108	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C109	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C110	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C111	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C112	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C113	NCB31HK-272X	C CAPACITOR	2700pF	50V K
C114	NCB31HK-473X	C CAPACITOR	0.047uF	50V K
C115	QETN1HM-335Z	E CAPACITOR	3.3uF	50V M
C116	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C117	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C118	NCB31CK-105X	C CAPACITOR	1uF	16V K
C119	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C120	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C121	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C202	NCB21AK-105X	C CAPACITOR	1uF	10V K
C203	NCB31HK-152X	C CAPACITOR	1500pF	50V K
C221	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C222	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C237	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C241	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C242	NCB21AK-225X	C CAPACITOR	2.2uF	10V K
C243	QETN0JM-227Z	E CAPACITOR	220uF	6.3V M
C244	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C281	QFVF1HJ-474Z	MF CAPACITOR	0.47uF	50V J
C282	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C283	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C284	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C285	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C286	NCB21CK-474X	C CAPACITOR	0.47uF	16V K
C287	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C288	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C289	NCB21AK-105X	C CAPACITOR	1uF	10V K
C290	NCB21AK-105X	C CAPACITOR	1uF	10V K
C291	NCB21AK-105X	C CAPACITOR	1uF	10V K
C301	NCZ1064-225X	C CAPACITOR	2.2uF	
C302	NCB31EK-104X	C CAPACITOR	0.1uF	25V K
C352	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C354	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C360	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C391	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C392	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C422	QFN32AK-102Z	M CAPACITOR	1000pF	100V K
C424	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C425	QETN1VM-477Z	E CAPACITOR	470uF	35V M
C427	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C428	QETM1EM-228	E CAPACITOR	2200uF	25V M
C431	QFLC2AK-563Z	M CAPACITOR	0.056uF	100V K
C433	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C435	NCB31HK-183X	C CAPACITOR	0.018uF	50V K
C440	QCS32HJ-100Z	C CAPACITOR	10pF	500V J
C501	QCB32HK-151Z	C CAPACITOR	150pF	500V K
C502	QCB32HK-331Z	C CAPACITOR	330pF	500V K
C503	QEHR2CM-105Z	E CAPACITOR	1uF	160V M
C504	QEZ0203-107	E CAPACITOR	100uF	160V M
C507	QEM61HK-475Z	E CAPACITOR	4.7uF	50V K
C508	QEM61HK-475Z	E CAPACITOR	4.7uF	50V K
⚠C510	QFZ0200-482	MPP CAPACITOR	4800pF	1.5kV H
⚠C513	QFZ0196-113	MPP CAPACITOR	0.011uF	1.5kV H
C514	QFP32GJ-183	PP CAPACITOR	0.018uF	400V J
C515	QFZ0197-404	MPP CAPACITOR	0.4uF	250V J
C516	QCB32HK-561Z	C CAPACITOR	560pF	500V K
C521	QETN2EM-106Z	E CAPACITOR	10uF	250V M
C523	QEHR1VM-477Z	E CAPACITOR	470uF	35V M
C525	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C526	QFV21HJ-824Z	MF CAPACITOR	0.82uF	50V J
C527	QFLC2AJ-103Z	M CAPACITOR	0.01uF	100V J
C531	QCB32HK-471Z	C CAPACITOR	470pF	500V K
C533	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C621	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M

⚠Ref No.	Part No.	Part Name	Description Local
C623	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C624	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C625	NCB31HK-822X	C CAPACITOR	8200pF 50V K
C627	NCB31CK-105X	C CAPACITOR	1uF 16V K
C628	NCB31CK-105X	C CAPACITOR	1uF 16V K
C629	NCB31CK-105X	C CAPACITOR	1uF 16V K
C630	NCB31CK-105X	C CAPACITOR	1uF 16V K
C631	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C633	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C634	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C635	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C636	QETN1HM-105Z	E CAPACITOR	1uF 50V M
C637	NCB31CK-105X	C CAPACITOR	1uF 16V K
C638	NCB31CK-105X	C CAPACITOR	1uF 16V K
C651	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C652	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C653	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C654	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C655	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C656	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C661	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C662	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C663	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C666	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C671	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C683	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C684	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C701	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C702	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C703	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C704	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C705	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C706	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C708	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C709	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C710	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C711	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C712	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C728	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C730	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C807	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C851	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C852	NCB31EK-104X	C CAPACITOR	0.1uF 25V K
C853	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C854	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C856	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C857	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C858	QEZ0256-128	E CAPACITOR	1200uF 10V M
C861	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C865	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C866	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C868	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C869	QCZ0397-106Z	C CAPACITOR	10uF 25V M
C871	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C874	NCB31EK-273X	C CAPACITOR	0.027uF 25V K
C876	QEZ0256-128	E CAPACITOR	1200uF 10V M
C880	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
⚠C905	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C907	QEZ0644-567	E CAPACITOR	560uF 200V K
⚠C908	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C912	QCZ0340-222	C CAPACITOR	2200pF 2kV K
C913	QFLC1HJ-471Z	M CAPACITOR	470pF 50V J
C914	QETN1HM-107Z	E CAPACITOR	100uF 50V M
C916	NDC31HJ-331X	C CAPACITOR	330pF 50V J
C917	NCB31HK-182X	C CAPACITOR	1800pF 50V K
C918	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C919	QFP32GJ-103	PP CAPACITOR	0.01uF 400V J
C931	QEZ0203-227	E CAPACITOR	220uF 160V M
C932	QETN1CM-108Z	E CAPACITOR	1000uF 16V M
C933	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C934	NDC31HJ-221X	C CAPACITOR	220pF 50V J
C935	QETN1VM-108Z	E CAPACITOR	1000uF 35V M
C937	QCZ0340-102	C CAPACITOR	1000pF 2kV K
C938	QETN1EM-227Z	E CAPACITOR	220uF 25V M
C939	QCB32HK-152Z	C CAPACITOR	1500pF 500V K
C941	QCB32HK-102Z	C CAPACITOR	1000pF 500V K
C942	QEHR1HM-105Z	E CAPACITOR	1uF 50V M
C943	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C951	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C952	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C971	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C972	QETN1EM-476Z	E CAPACITOR	47uF 25V M
⚠C998	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
⚠C999	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
R001	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R002	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R003	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R004	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R005	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J

⚠Ref No.	Part No.	Part Name	Description Local
R006	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R007	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R008	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R101	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R102	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R103	NRSA63J-105X	MG RESISTOR	1MΩ 1/16W J
R104	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R105	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R106	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R107	NRSA63D-623X	MG RESISTOR	62kΩ 1/16W D
R108	NRSA63J-332X	MG RESISTOR	3.3kΩ 1/16W J
R109	NRSA63D-302X	MG RESISTOR	3kΩ 1/16W D
R110	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R201	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R227	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R281	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J
R282	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R283	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R286	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R287	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R288	NRSA02J-471X	MG RESISTOR	470Ω 1/10W J
R289	NRSA63J-154X	MG RESISTOR	150kΩ 1/16W J
R290	NRSA02J-561X	MG RESISTOR	560Ω 1/10W J
R292	NRSA63J-124X	MG RESISTOR	120kΩ 1/16W J
R293	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J
R294	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R295	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R296	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R301	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R302	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R303	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R304	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R305	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R306	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R318	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R319	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R354	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R355	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R356	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R359	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R421	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R423	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R424	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R426	NRSA63J-183X	MG RESISTOR	18kΩ 1/16W J
R427	QRT029J-1R5	MF RESISTOR	1.5Ω 2W J
R429	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J
R431	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J
R432	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R433	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R434	QRL029J-181	OMF RESISTOR	180Ω 2W J
R435	QRE121J-102Y	C RESISTOR	1kΩ 1/2W J
R441	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R502	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R503	QRE121J-103Y	C RESISTOR	10kΩ 1/2W J
R504	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R505	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R511	QRE121J-220Y	C RESISTOR	22Ω 1/2W J
R512	QRE121J-681Y	C RESISTOR	680Ω 1/2W J
R516	QRZ0221-2R0	OMF RESISTOR	2Ω 7W K
R524	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R526	QRE121J-272Y	C RESISTOR	2.7kΩ 1/2W J
R527	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R528	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R529	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
⚠R531	QRE121J-391Y	C RESISTOR	390Ω 1/2W J
R532	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R533	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R534	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
⚠R535	NRVA02D-272X	CMF RESISTOR	2.7kΩ 1/10W D
R536	QRE121J-470Y	C RESISTOR	47Ω 1/2W J
R537	NRVA02D-752X	CMF RESISTOR	7.5kΩ 1/10W D
R538	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
R543	QRE121J-122Y	C RESISTOR	1.2kΩ 1/2W J
R544	QRE121J-392Y	C RESISTOR	3.9kΩ 1/2W J
R545	QRE121J-822Y	C RESISTOR	8.2kΩ 1/2W J
R546	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
R547	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R548	QRE121J-152Y	C RESISTOR	1.5kΩ 1/2W J
R553	QRL039J-390	OMF RESISTOR	39Ω 3W J
⚠R554	QRK126J-150X	UNF C RESISTOR	15Ω 1/2W J
R555	QRT029J-3R3	MF RESISTOR	3.3Ω 2W J
R621	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R624	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R625	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R631	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R638	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R639	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R651	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R652	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J

⚠Ref No.	Part No.	Part Name	Description Local
R653	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R654	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R661	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R662	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R663	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R664	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R672	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R683	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R685	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R686	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R687	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R688	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R689	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J
R690	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R691	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J
R701	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R702	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R704	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R705	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R706	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R707	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R708	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R709	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R710	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R711	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R716	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R718	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R729	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R731	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R732	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R733	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R734	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R735	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R736	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R738	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R739	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R740	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R769	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J
R772	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R811	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R816	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R821	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R827	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R852	NRSA63D-123X	MG RESISTOR	12kΩ 1/16W D
R853	NRSA63D-182X	MG RESISTOR	1.8kΩ 1/16W D
R854	NRSA63D-122X	MG RESISTOR	1.2kΩ 1/16W D
R855	QRL029J-820	OMF RESISTOR	82Ω 2W J
R858	QRT029J-R18	MF RESISTOR	0.18Ω 2W J
R860	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J
R861	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R862	NRSA63D-332X	MG RESISTOR	3.3kΩ 1/16W D
R863	NRSA63D-103X	MG RESISTOR	10kΩ 1/16W D
R865	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R879	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D
R880	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D
R881	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R901	QRF074K-1R2	UNF WW RESISTOR	1.2Ω 7W K
R909	QRG01GJ-470	OMF RESISTOR	47Ω 1W J
R911	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R912	QRT029J-R18	MF RESISTOR	0.18Ω 2W J
R913	QRT029J-R15	MF RESISTOR	0.15Ω 2W J
⚠R914	QRK126J-681X	UNF C RESISTOR	680Ω 1/2W J
R915	QRK129J-6R8	UNF C RESISTOR	6.8Ω 1/2W J
⚠R917	QRK126J-332X	UNF C RESISTOR	3.3kΩ 1/2W J
R918	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J
R919	QRE121J-684Y	C RESISTOR	680kΩ 1/2W J
R924	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J
R930	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R940	QRE121J-181Y	C RESISTOR	180Ω 1/2W J
R941	QRL029J-183	OMF RESISTOR	18kΩ 2W J
R942	QRT039J-R68	MF RESISTOR	0.68Ω 3W J
R950	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R951	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J
R952	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R953	QRE121J-820Y	C RESISTOR	82Ω 1/2W J
R972	NRVA02D-122X	CMF RESISTOR	1.2kΩ 1/10W D
R973	NRVA02D-332X	CMF RESISTOR	3.3kΩ 1/10W D
R975	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R977	QRE121J-473Y	C RESISTOR	47kΩ 1/2W J
R978	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
L001	QQL244K-6R8Z	PEAKING COIL	6.8uH K
L241	QQL244K-220Z	PEAKING COIL	22uH K
L391	QQL244K-220Z	PEAKING COIL	22uH K
L511	QQR1165-001	LINEARITY COIL	
L512	QQLZ036-821	COIL	820uH K
L521	QQLZ026-760	COIL	76uH
L704	QQL244K-220Z	PEAKING COIL	22uH K
L705	QQL244K-220Z	PEAKING COIL	22uH K
L851	QQR1401-001	CHOKE COIL	
L853	QQL26AK-330Z	CHOKE COIL	33uH K
L854	QQL26AK-470Z	CHOKE COIL	47uH K
L855	QQL26AK-100Z	CHOKE COIL	10uH K
L860	QQL28AK-150	COIL	15uH K
L861	QQR1401-001	CHOKE COIL	
L931	QQL26AK-470Z	CHOKE COIL	47uH K
L933	QQL26AK-470Z	CHOKE COIL	47uH K
L937	QQL26AK-470Z	CHOKE COIL	47uH K
L940	QQR0582-001Z	FERRITE BEADS	
T501	QQR1414-001	DRIVE TRANSF	
⚠T921	QQS0376-001	SW TRANSF	
CN001	QGB1221J1-80	CONNECTOR	B-B (1-80)
CN002	QGB1505J1-35	CONNECTOR	B-B (1-35)
CN00F	QJB003-032213-E	SIN ID C-B WIRE	
CN00W	WJK0200-004A-E	E-SI C WIRE C-B	
⚠CP936	ICP-N70-T	IC PROTECTOR	2.5A
⚠FR525	QRZ9017-4R7	FUSI RESISTOR	4.7Ω 1/4W J
K002	QQR0621-002Z	FERRITE BEADS	
K004	QQR0621-002Z	FERRITE BEADS	
K007	NQR0499-002X	FERRITE BEADS	
K008	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
K401	QQR0621-002Z	FERRITE BEADS	
K912	QQR0582-001Z	FERRITE BEADS	
K916	QQR0582-001Z	FERRITE BEADS	
K917	QQR0582-001Z	FERRITE BEADS	
K918	QQR0582-001Z	FERRITE BEADS	
K920	QQR1139-001	FERRITE BEADS	
K931	QQR0582-001Z	FERRITE BEADS	
K932	QQR0582-001Z	FERRITE BEADS	
K933	QQR0582-001Z	FERRITE BEADS	
K935	QQR0582-001Z	FERRITE BEADS	
K937	QQR0582-001Z	FERRITE BEADS	
⚠PC921	PS2581AL1/QW/	PHOTO COUPLER	
⚠RY951	QSK0085-001	RELAY	
S421	QSW1142-001	LEVER SWITCH	V.CENTER
⚠TH901	QAD0132-3R0	P THERMISTOR	3Ω
X701	QAX0767-001Z	CRYSTAL	8.000000MHz

CRT SOCKET P.W. BOARD ASS'Y (SGJ-3302A-M2)

⚠Ref No.	Part No.	Part Name	Description Local
Q3103	2SC3928A/QR/-X	TRANSISTOR	
Q3107	2SA2005/DE/	POW TRANSISTOR	
Q3108	2SC5511/DE/	POW TRANSISTOR	
Q3109	2SC3928A/QR/-X	TRANSISTOR	
Q3304	2SC4544-LB	POW TRANSISTOR	
Q3305	2SC4544-LB	POW TRANSISTOR	
Q3306	2SC4544-LB	POW TRANSISTOR	
Q3351	2SA1530A/QR/-X	TRANSISTOR	
D3105	RH1S-T3	SI DIODE	
D3106	RH1S-T3	SI DIODE	
D3331	1SS133-T2	SI DIODE	
D3351	1SS133-T2	SI DIODE	
D3352	1SS133-T2	SI DIODE	
D3353	1SS133-T2	SI DIODE	
D3354	1SS133-T2	SI DIODE	
C3101	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C3113	QETN2CM-106Z	E CAPACITOR	10uF 160V M
C3114	QCB32HK-472Z	C CAPACITOR	4700pF 500V K
C3115	QCB32HK-472Z	C CAPACITOR	4700pF 500V K
C3117	QETN2CM-106Z	E CAPACITOR	10uF 160V M
C3118	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C3119	QETN1AM-107Z	E CAPACITOR	100uF 10V M
C3120	QETN1AM-337Z	E CAPACITOR	330uF 10V M
C3121	QCS32HJ-151Z	C CAPACITOR	150pF 500V J
C3127	NDC31HJ-471X	C CAPACITOR	470pF 50V J
C3301	NDC31HJ-561X	C CAPACITOR	560pF 50V J
C3302	NDC31HJ-391X	C CAPACITOR	390pF 50V J
C3303	NDC31HJ-561X	C CAPACITOR	560pF 50V J
C3323	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C3331	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3332	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3333	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3351	QETN1CM-477Z	E CAPACITOR	470uF 16V M
C3363	QCZ0121-102	C CAPACITOR	1000pF 3KV Z
R3115	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J
R3116	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J
R3122	QRT029J-R15	MF RESISTOR	0.15Ω 2W J
R3123	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J
R3124	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J
R3125	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J

⚠Ref No.	Part No.	Part Name	Description	Local
R3126	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3127	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3128	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3129	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3130	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3131	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3132	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R3134	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3136	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R3139	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3142	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R3143	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3144	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3145	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3146	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3148	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3301	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3302	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3303	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3304	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3305	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3306	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3307	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3308	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3309	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3310	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3311	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3312	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3313	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3314	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3315	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3325	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3326	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3327	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3331	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3332	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3333	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3334	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R3335	NRSA63J-391X	MG RESISTOR	390Ω 1/16W J	
R3351	NRSA63J-821X	MG RESISTOR	820Ω 1/16W J	
R3354	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
L3304	QQL244K-470Z	PEAKING COIL	47uH K	
CN300A	WJA0029-001A-E	E-SI ID WIRE		
CN300E	QJB003-073226-E	SIN ID C-B WIRE		
CN30E2	QUB130-38A6AS-E	SIN TWIST WIRE		
CN30E4	QUB130-38A6AS-E	SIN TWIST WIRE		
K3104	QQR1114-001Z	FERRITE BEADS		
K3105	QQR1114-001Z	FERRITE BEADS		
⚠SK3001	QNZ0536-002	CRT SOCKET		

AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2)

REFER TO PARTS LIST IN PAGE 3-9 FOR THIS P.W. BOARD.

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

USB P.W. BOARD ASS'Y (SGJ-8302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

L/F P.W. BOARD ASS'Y (SGJ-9302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

PRINTED WIRING BOARD PARTS LIST [AV-32F577/R]

MAIN P.W. BOARD ASS'Y (SGJ-1313A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC101	CXA2094Q-X	IC		
IC201	TM8812CSDNG6H60	IC(MCU)		
IC421	LA78041	IC		
IC601	NJW1143AV-W	IC		
IC651	LA42072NL	IC		
IC702	ATE08-32F577R	IC	(SERVICE)	
IC703	S-80840CLNB-G-W	IC		
IC704	S78L05-T	IC		
IC851	PQ1CG2032FZ	IC		
IC852	S7809PI	IC		
IC853	PQ05RD21SSJH	IC		
IC855	PQ070XF01SZH	IC		
IC856	MP2263DN-C053-X	IC		
⚠IC911	STR-G9626-F3	IC		
⚠IC921	SE135N	IC		
Q001	2SK1374-X	MOS FET		
Q002	2SK1374-X	MOS FET		
Q003	2SK1374-X	MOS FET		
Q004	2SK1374-X	MOS FET		
Q005	RT1N440C-X	TRANSISTOR		
Q352	2SC3928A/QR/-X	TRANSISTOR		
Q501	2SC4212/Z1/	TRANSISTOR		
⚠Q511	TT2202-YD	POWER TRANST		
⚠Q531	2SC2785/JH/-T	TRANSISTOR		
Q532	2SA1530A/QR/-X	TRANSISTOR		
Q541	2SA1530A/QR/-X	TRANSISTOR		
Q542	2SA1530A/QR/-X	TRANSISTOR		
Q543	2SD1267A/QP/	POW TRANSISTOR		
Q671	RT1N441C-X	TRANSISTOR		
Q682	2SA1530A/QR/-X	TRANSISTOR		
Q683	RT1N441C-X	TRANSISTOR		
Q684	2SC3928A/QR/-X	TRANSISTOR		
Q701	2SA1530A/QR/-X	TRANSISTOR		
Q730	RT1N441C-X	TRANSISTOR		
Q951	2SD1383K/AB/-X	SI TRANSISTOR		
Q971	2SA1208/ST/Z1-T	TRANSISTOR		
D308	MTZJ5.1B-T2	Z DIODE		
D309	MTZJ5.1B-T2	Z DIODE		
D310	MTZJ5.1B-T2	Z DIODE		
D352	MTZJ9.1C-T2	Z DIODE		
D353	1SS133-T2	SI DIODE		
D354	MTZJ3.3A-T2	Z DIODE		
D421	1N4003SG-T2	SI DIODE		
D422	MTZJ75-T2	Z DIODE		
D501	RH3G-F1	SI DIODE		
D502	RU3AM-LFC4	SI DIODE		
D521	FR105GT-T3	SI DIODE		
D523	FR105GT-T3	SI DIODE		
D525	1SS81-T5	SI DIODE		
D526	1SS81-T5	SI DIODE		
D527	1SR124-400A-T2	SI DIODE		
D529	MTZJ9.1C-T2	Z DIODE		
⚠D531	MA4068N/Z1/-T2	Z DIODE		
D535	1SS133-T2	SI DIODE		
D681	1SS133-T2	SI DIODE		
D682	1SS133-T2	SI DIODE		
D683	1SS133-T2	SI DIODE		
D684	1SS133-T2	SI DIODE		
D701	1SS133-T2	SI DIODE		
D705	1SS133-T2	SI DIODE		
D730	1SS133-T2	SI DIODE		
D851	EC31QS04-X	SB DIODE		
D852	1SS133-T2	SI DIODE		
D855	1SS133-T2	SI DIODE		
D856	EC30HA03L-X	SB DIODE		
D857	EC30HA03L-X	SB DIODE		
D861	PTZ3.9B-X	Z DIODE		
D862	PTZ3.9B-X	Z DIODE		
⚠D901	GSIB460	BRIDGE DIODE		
D910	MA700A-T2	SB DIODE		
D911	FR105GT-T3	SI DIODE		
D912	FR105GT-T3	SI DIODE		
D913	1SS133-T2	SI DIODE		
D914	1SS133-T2	SI DIODE		
D915	SARS01-T2	FR DIODE		
D917	MTZJ30A-T2	Z DIODE		
D918	MTZJ5.1C-T2	Z DIODE		
D920	1SS133-T2	SI DIODE		
D931	RU4AM-LFT2	SI DIODE		
D933	HER202G-FL	SI DIODE		
D935	HER202G-FL	SI DIODE		
D938	HER202G-FL	SI DIODE		
D941	MTZJ33A-T2	Z DIODE		
D945	MTZJ9.1B-T2	Z DIODE		
D952	1SS133-T2	SI DIODE		
D953	1SS133-T2	SI DIODE		
D954	1N4003SG-T2	SI DIODE		
D955	1N4003SG-T2	SI DIODE		
D956	1N4003SG-T2	SI DIODE		
D957	1N4003SG-T2	SI DIODE		
D972	MTZJ15C-T2	Z DIODE		
D973	1SS133-T2	SI DIODE		
C009	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C101	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C102	NCB31HK-562X	C CAPACITOR	5600pF 50V K	
C103	NCB31EK-123X	C CAPACITOR	0.012uF 25V K	
C104	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C105	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C106	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C107	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C108	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C109	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C110	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C111	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C112	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C113	NCB31HK-272X	C CAPACITOR	2700pF 50V K	
C114	NCB31HK-473X	C CAPACITOR	0.047uF 50V K	
C115	QETN1HM-335Z	E CAPACITOR	3.3uF 50V M	
C116	QENC1EM-475Z	BP E CAPACITOR	4.7uF 25V M	
C117	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C118	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C119	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C120	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C121	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C202	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C203	NCB31HK-152X	C CAPACITOR	1500pF 50V K	
C221	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C222	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C237	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C241	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C242	NCB21AK-225X	C CAPACITOR	2.2uF 10V K	
C243	QETN0JM-227Z	E CAPACITOR	220uF 6.3V M	
C244	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C281	QFVF1HJ-474Z	MF CAPACITOR	0.47uF 50V J	
C282	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C283	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C284	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C285	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C286	NCB21CK-474X	C CAPACITOR	0.47uF 16V K	
C287	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C288	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C289	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C290	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C291	NCB21AK-105X	C CAPACITOR	1uF 10V K	
C301	NCZ1064-225X	C CAPACITOR	2.2uF	
C302	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	
C352	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
C354	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C360	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C391	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C392	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C422	QFN32AK-102Z	M CAPACITOR	1000pF 100V K	
C424	QETN1VM-107Z	E CAPACITOR	100uF 35V M	
C425	QETN1VM-477Z	E CAPACITOR	470uF 35V M	
C427	QETN1HM-225Z	E CAPACITOR	2.2uF 50V M	
C428	QETM1EM-228	E CAPACITOR	2200uF 25V M	
C431	QFLC2AK-563Z	M CAPACITOR	0.056uF 100V K	
C433	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
C435	NCB31HK-183X	C CAPACITOR	0.018uF 50V K	
C440	QCS32HJ-100Z	C CAPACITOR	10pF 500V J	
C501	QCB32HK-151Z	C CAPACITOR	150pF 500V K	
C502	QCB32HK-331Z	C CAPACITOR	330pF 500V K	
C503	QEHR2CM-105Z	E CAPACITOR	1uF 160V M	
C504	QEZ0203-107	E CAPACITOR	100uF 160V M	
C507	QEZ0195-475Z	E CAPACITOR	4.7uF 50V M	
⚠C510	QFZ0200-382	MPP CAPACITOR	3800pF 1.5kV H	
⚠C513	QFZ0198-133	MPP CAPACITOR	0.013uF 1.5kV H	
C514	QFP32JJ-183	PP CAPACITOR	0.018uF 630V J	
C515	QFZ0197-474	MPP CAPACITOR	0.47uF 250V J	
C516	QCB32HK-561Z	C CAPACITOR	560pF 500V K	
C521	QETN2EM-106Z	E CAPACITOR	10uF 250V M	
C523	QEHR1VM-108Z	E CAPACITOR	1000uF 35V M	
C525	QETN1VM-107Z	E CAPACITOR	100uF 35V M	
C526	QFV21HJ-824Z	MF CAPACITOR	0.82uF 50V J	
C527	QFLC2AJ-103Z	M CAPACITOR	0.01uF 100V J	
C533	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C621	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C623	NCB31HK-102X	C CAPACITOR	1000pF 50V K	
C624	NCB31CK-334X	C CAPACITOR	0.33uF 16V K	

⚠Ref No.	Part No.	Part Name	Description	Local
C625	NCB31HK-822X	C CAPACITOR	8200pF 50V K	
C627	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C628	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C629	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C630	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C631	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C633	NCB31HK-102X	C CAPACITOR	1000pF 50V K	
C634	NCB31CK-334X	C CAPACITOR	0.33uF 16V K	
C635	QETN1CM-476Z	E CAPACITOR	47uF 16V M	
C636	QETN1HM-105Z	E CAPACITOR	1uF 50V M	
C637	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C638	NCB31CK-105X	C CAPACITOR	1uF 16V K	
C651	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C652	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C653	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C654	QETN1EM-477Z	E CAPACITOR	470uF 25V M	
C655	QETN1EM-108Z	E CAPACITOR	1000uF 25V M	
C656	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C661	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C662	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M	
C663	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C666	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C671	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C683	QETN1EM-107Z	E CAPACITOR	100uF 25V M	
C684	QETN1CM-476Z	E CAPACITOR	47uF 16V M	
C701	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C702	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C703	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C704	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C705	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C706	NCB31HK-102X	C CAPACITOR	1000pF 50V K	
C708	NDC31HJ-220X	C CAPACITOR	22pF 50V J	
C709	NDC31HJ-220X	C CAPACITOR	22pF 50V J	
C710	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C711	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C712	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C728	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C730	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C807	NCB31CK-104X	C CAPACITOR	0.1uF 16V K	
C851	QETN1EM-477Z	E CAPACITOR	470uF 25V M	
C852	NCB31EK-104X	C CAPACITOR	0.1uF 25V K	
C853	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C854	QETN1EM-107Z	E CAPACITOR	100uF 25V M	
C856	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C857	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C858	QEZ0256-128	E CAPACITOR	1200uF 10V M	
C861	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C865	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C866	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C868	QETN1EM-477Z	E CAPACITOR	470uF 25V M	
C869	QCZ0397-106Z	C CAPACITOR	10uF 25V M	
C871	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
C874	NCB31EK-273X	C CAPACITOR	0.027uF 25V K	
C876	QEZ0256-128	E CAPACITOR	1200uF 10V M	
C880	NCB31HK-103X	C CAPACITOR	0.01uF 50V K	
⚠C905	QCZ9054-102	C CAPACITOR	1000pF AC250V Z	
C907	QEZ0644-567	E CAPACITOR	560uF 200V K	
⚠C908	QCZ9054-102	C CAPACITOR	1000pF AC250V Z	
C912	QCZ0340-222	C CAPACITOR	2200pF 2kV K	
C913	QFLC1HJ-471Z	M CAPACITOR	470pF 50V J	
C914	QETN1HM-107Z	E CAPACITOR	100uF 50V M	
C916	NDC31HJ-331X	C CAPACITOR	330pF 50V J	
C917	NCB31HK-182X	C CAPACITOR	1800pF 50V K	
C918	NCB31HK-104X	C CAPACITOR	0.1uF 50V K	
C919	QFP32GJ-103	PP CAPACITOR	0.01uF 400V J	
C931	QEZ0203-227	E CAPACITOR	220uF 160V M	
C932	QETN1CM-108Z	E CAPACITOR	1000uF 16V M	
C933	QETN1EM-108Z	E CAPACITOR	1000uF 25V M	
C934	NDC31HJ-221X	C CAPACITOR	220pF 50V J	
C935	QETN1VM-108Z	E CAPACITOR	1000uF 35V M	
C937	QCZ0340-102	C CAPACITOR	1000pF 2kV K	
C938	QETN1EM-227Z	E CAPACITOR	220uF 25V M	
C939	QCB32HK-152Z	C CAPACITOR	1500pF 500V K	
C941	QCB32HK-102Z	C CAPACITOR	1000pF 500V K	
C942	QEHR1HM-105Z	E CAPACITOR	1uF 50V M	
C943	QETN1CM-227Z	E CAPACITOR	220uF 16V M	
C951	QETN1EM-477Z	E CAPACITOR	470uF 25V M	
C952	QETN1CM-227Z	E CAPACITOR	220uF 16V M	
C971	QETN1CM-107Z	E CAPACITOR	100uF 16V M	
C972	QETN1EM-476Z	E CAPACITOR	47uF 25V M	
⚠C998	QCZ9074-103	C CAPACITOR	0.01uF AC250V M	
⚠C999	QCZ9074-103	C CAPACITOR	0.01uF AC250V M	
R001	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R002	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R003	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R004	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R005	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R006	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R007	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R008	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R101	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R102	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R103	NRSA63J-105X	MG RESISTOR	1MΩ 1/16W J	
R104	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R105	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R106	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J	
R107	NRSA63D-623X	MG RESISTOR	62kΩ 1/16W D	
R108	NRSA63J-332X	MG RESISTOR	3.3kΩ 1/16W J	
R109	NRSA63D-302X	MG RESISTOR	3kΩ 1/16W D	
R110	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R201	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J	
R227	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R281	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R282	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R283	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R286	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R287	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R288	NRSA02J-471X	MG RESISTOR	470Ω 1/10W J	
R289	NRSA63J-154X	MG RESISTOR	150kΩ 1/16W J	
R290	NRSA02J-561X	MG RESISTOR	560Ω 1/10W J	
R292	NRSA63J-124X	MG RESISTOR	120kΩ 1/16W J	
R293	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J	
R294	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R295	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R296	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R301	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R302	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R303	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R304	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R305	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R306	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R318	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R319	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R354	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R355	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R356	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R359	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R421	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	
R423	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J	
R424	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J	
R426	NRSA63J-183X	MG RESISTOR	18kΩ 1/16W J	
R427	QRT029J-1R2	MF RESISTOR	1.2Ω 2W J	
R428	QRE121J-120Y	C RESISTOR	12Ω 1/2W J	
R429	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J	
R431	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J	
R432	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R433	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J	
R434	QRL029J-221	OMF RESISTOR	220Ω 2W J	
R435	QRE121J-821Y	C RESISTOR	820Ω 1/2W J	
R441	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R456	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R502	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J	
R503	QRE121J-103Y	C RESISTOR	10kΩ 1/2W J	
R504	QRL039J-152	OMF RESISTOR	1.5kΩ 3W J	
R505	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J	
R511	QRE121J-220Y	C RESISTOR	22Ω 1/2W J	
R512	QRE121J-681Y	C RESISTOR	680Ω 1/2W J	
R516	QRZ0221-2R0	OMF RESISTOR	2Ω 7W K	
R524	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R526	QRE121J-272Y	C RESISTOR	2.7kΩ 1/2W J	
R527	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J	
R528	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J	
R529	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
⚠R531	QRE121J-391Y	C RESISTOR	390Ω 1/2W J	
R532	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J	
R533	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R534	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
⚠R535	NRVA02D-272X	CMF RESISTOR	2.7kΩ 1/10W D	
R536	QRE121J-470Y	C RESISTOR	47Ω 1/2W J	
R537	NRVA02D-752X	CMF RESISTOR	7.5kΩ 1/10W D	
R538	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
R543	QRE121J-122Y	C RESISTOR	1.2kΩ 1/2W J	
R544	QRE121J-392Y	C RESISTOR	3.9kΩ 1/2W J	
R545	QRE121J-822Y	C RESISTOR	8.2kΩ 1/2W J	
R546	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R547	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R548	QRE121J-152Y	C RESISTOR	1.5kΩ 1/2W J	
R553	QRL039J-330	OMF RESISTOR	33Ω 3W J	
⚠R554	QRK126J-220X	UNF C RESISTOR	22Ω 1/2W J	
R555	QRT029J-2R2	MF RESISTOR	2.2Ω 2W J	
R621	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R624	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R625	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R631	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R638	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R639	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R651	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	
R652	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	

⚠Ref No.	Part No.	Part Name	Description Local
R653	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R654	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R661	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R662	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R663	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R664	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J
R672	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R683	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R685	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R686	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R687	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J
R688	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R689	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J
R690	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R691	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J
R701	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R702	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R704	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R705	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R706	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R707	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R708	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R709	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R710	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R711	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R716	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R718	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R729	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R731	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R732	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R733	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R734	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R735	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R736	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R738	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R739	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R740	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R769	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J
R772	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R811	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R816	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R821	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R827	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R852	NRSA63D-123X	MG RESISTOR	12kΩ 1/16W D
R853	NRSA63D-182X	MG RESISTOR	1.8kΩ 1/16W D
R854	NRSA63D-122X	MG RESISTOR	1.2kΩ 1/16W D
R855	QRL029J-820	OMF RESISTOR	82Ω 2W J
R858	QRT029J-R18	MF RESISTOR	0.18Ω 2W J
R860	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J
R861	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R862	NRSA63D-332X	MG RESISTOR	3.3kΩ 1/16W D
R863	NRSA63D-103X	MG RESISTOR	10kΩ 1/16W D
R865	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R879	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D
R880	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D
R881	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R901	QRF074K-1R2	UNF WW RESISTOR	1.2Ω 7W K
R909	QRG01GJ-470	OMF RESISTOR	47Ω 1W J
R911	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R912	QRT029J-R18	MF RESISTOR	0.18Ω 2W J
R913	QRT029J-R15	MF RESISTOR	0.15Ω 2W J
⚠R914	QRK126J-681X	UNF C RESISTOR	680Ω 1/2W J
R915	QRK129J-6R8	UNF C RESISTOR	6.8Ω 1/2W J
⚠R917	QRK126J-332X	UNF C RESISTOR	3.3kΩ 1/2W J
R918	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J
R919	QRE121J-684Y	C RESISTOR	680kΩ 1/2W J
R924	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J
R930	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R940	QRE121J-181Y	C RESISTOR	180Ω 1/2W J
R941	QRL029J-183	OMF RESISTOR	18kΩ 2W J
R942	QRT039J-R68	MF RESISTOR	0.68Ω 3W J
R950	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R951	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J
R952	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R953	QRE121J-820Y	C RESISTOR	82Ω 1/2W J
R972	NRVA02D-102X	CMF RESISTOR	1kΩ 1/10W D
R973	NRVA02D-332X	CMF RESISTOR	3.3kΩ 1/10W D
R975	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J
R977	QRE121J-473Y	C RESISTOR	47kΩ 1/2W J
R978	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
L001	QQL244K-6R8Z	PEAKING COIL	6.8uH K
L241	QQL244K-220Z	PEAKING COIL	22uH K
L391	QQL244K-220Z	PEAKING COIL	22uH K
L511	QQR1027-003	LINEARITY COIL	
L512	QQLZ036-821	COIL	820uH K
L521	QQLZ018-340	COIL	34uH
L704	QQL244K-220Z	PEAKING COIL	22uH K
L705	QQL244K-220Z	PEAKING COIL	22uH K
L851	QQR1401-001	CHOKE COIL	
L853	QQL26AK-330Z	CHOKE COIL	33uH K
L854	QQL26AK-470Z	CHOKE COIL	47uH K
L855	QQL26AK-100Z	CHOKE COIL	10uH K
L860	QQL28AK-150	COIL	15uH K
L861	QQR1401-001	CHOKE COIL	
L931	QQL26AK-470Z	CHOKE COIL	47uH K
L933	QQL26AK-470Z	CHOKE COIL	47uH K
L937	QQL26AK-470Z	CHOKE COIL	47uH K
L940	QQR0582-001Z	FERRITE BEADS	
T501	QQR1414-001	DRIVE TRANSF	
⚠T921	QQS0376-001	SW TRANSF	
CN001	QGB1221J1-80	CONNECTOR	B-B (1-80)
CN002	QGB1505J1-35	CONNECTOR	B-B (1-35)
CN00F	QJB003-032213-E	SIN ID C-B WIRE	
CN00W	WJK0200-004A-E	E-SI C WIRE C-B	
⚠CP936	ICP-N70-T	IC PROTECTOR	2.5A
⚠FR525	QRZ9017-4R7	FUSI RESISTOR	4.7Ω 1/4W J
K002	QQR0621-002Z	FERRITE BEADS	
K004	QQR0621-002Z	FERRITE BEADS	
K007	NQR0499-002X	FERRITE BEADS	
K008	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
K401	QQR0621-002Z	FERRITE BEADS	
K912	QQR0582-001Z	FERRITE BEADS	
K916	QQR0582-001Z	FERRITE BEADS	
K917	QQR0582-001Z	FERRITE BEADS	
K918	QQR0582-001Z	FERRITE BEADS	
K920	QQR1139-001	FERRITE BEADS	
K931	QQR0582-001Z	FERRITE BEADS	
K932	QQR0582-001Z	FERRITE BEADS	
K933	QQR0582-001Z	FERRITE BEADS	
K935	QQR0582-001Z	FERRITE BEADS	
K937	QQR0582-001Z	FERRITE BEADS	
⚠PC921	PS2581AL1/QW/	PHOTO COUPLER	
⚠RY951	QSK0085-001	RELAY	
S421	QSW1142-001	LEVER SWITCH	V.CENTER
⚠TH901	QAD0132-3R0	P THERMISTOR	3Ω
X701	QAX0767-001Z	CRYSTAL	8.000000MHz

CRT SOCKET P.W. BOARD ASS'Y (SGJ-3305A-M2)

⚠Ref No.	Part No.	Part Name	Description Local
Q3103	2SC3928A/QR/-X	TRANSISTOR	
Q3107	2SA2005/DE/	POW TRANSISTOR	
Q3108	2SC5511/DE/	POW TRANSISTOR	
Q3109	2SC3928A/QR/-X	TRANSISTOR	
Q3304	2SC4544-LB	POW TRANSISTOR	
Q3305	2SC4544-LB	POW TRANSISTOR	
Q3306	2SC4544-LB	POW TRANSISTOR	
Q3351	2SA1530A/QR/-X	TRANSISTOR	
D3105	RH1S-T3	SI DIODE	
D3106	RH1S-T3	SI DIODE	
D3331	1SS133-T2	SI DIODE	
D3351	1SS133-T2	SI DIODE	
D3352	1SS133-T2	SI DIODE	
D3353	1SS133-T2	SI DIODE	
D3354	1SS133-T2	SI DIODE	
C3101	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C3113	QETN2CM-106Z	E CAPACITOR	10uF 160V M
C3114	QCB32HK-472Z	C CAPACITOR	4700pF 500V K
C3115	QCB32HK-472Z	C CAPACITOR	4700pF 500V K
C3117	QETN2CM-106Z	E CAPACITOR	10uF 160V M
C3118	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C3119	QETN1AM-107Z	E CAPACITOR	100uF 10V M
C3120	QETN1AM-337Z	E CAPACITOR	330uF 10V M
C3121	QCS32HJ-151Z	C CAPACITOR	150pF 500V J
C3127	NDC31HJ-471X	C CAPACITOR	470pF 50V J
C3301	NDC31HJ-561X	C CAPACITOR	560pF 50V J
C3302	NDC31HJ-391X	C CAPACITOR	390pF 50V J
C3303	NDC31HJ-561X	C CAPACITOR	560pF 50V J
C3323	QETN1CM-477Z	E CAPACITOR	470uF 16V M
C3331	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3332	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3333	NDC31HJ-181X	C CAPACITOR	180pF 50V J
C3351	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C3363	QCZ0121-102	C CAPACITOR	1000pF 3KV Z
R3115	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J
R3116	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J
R3122	QRT029J-R15	MF RESISTOR	0.15Ω 2W J
R3123	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J
R3124	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J
R3125	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J

⚠Ref No.	Part No.	Part Name	Description	Local
R3126	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3127	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3128	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3129	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3130	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3131	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3132	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R3134	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3136	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R3139	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3142	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R3143	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3144	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3145	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3146	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3148	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3301	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3302	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3303	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3304	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3305	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3306	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3307	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3308	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3309	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3310	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3311	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3312	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3313	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3314	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3315	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3325	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3326	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3327	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3331	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3332	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3333	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3334	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R3335	NRSA63J-391X	MG RESISTOR	390Ω 1/16W J	
R3351	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3354	NRSA63J-561X	MG RESISTOR	560Ω 1/16W J	
R3355	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
L3304	QQL244K-470Z	PEAKING COIL	47uH K	
CN300A	WJA0029-002A-E	E-SI ID WIRE		
CN300E	QJB003-074022-E	SIN ID C-B WIRE		
CN30E2	QUB130-46A6AS-E	SIN TWIST WIRE		
CN30E4	QUB130-46A6AS-E	SIN TWIST WIRE		
K3104	QQR1114-001Z	FERRITE BEADS		
K3105	QQR1114-001Z	FERRITE BEADS		
⚠SK3001	QNZ0536-002	CRT SOCKET		

AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2)

REFER TO PARTS LIST IN PAGE 3-9 FOR THIS P.W. BOARD.

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

USB P.W. BOARD ASS'Y (SGJ-8302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

L/F P.W. BOARD ASS'Y (SGJ-9301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
⚠C901	QFZ9072-104	MM CAPACITOR	0.1uF AC250V K	
⚠C902	QFZ9072-473	MM CAPACITOR	0.047uF AC250V K	
⚠C903	QFZ9072-104	MM CAPACITOR	0.1uF AC250V K	
⚠C997	QCZ9079-102	C CAPACITOR	1000pF AC250V M	
⚠R998	QRZ9041-275	C RESISTOR	2.7MΩ 1/2W K	
R999	QRE121J-121Y	C RESISTOR	120Ω 1/2W J	
⚠T951	QQT0355-001	POWER TRANSF		
⚠F901	QMF51N1-5R0-J5	FUSE	5A AC125V	
⚠LF901	QQR0527-003	LINE FILTER		
⚠LF902	QQR0527-003	LINE FILTER		
⚠VA901	QAF0060-621	VARISTOR	620V	

ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

PRINTED WIRING BOARD PARTS LIST [AV-32F577/Y]

MAIN P.W. BOARD ASS'Y (SGJ-1301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC101	CXA2094Q-X	IC		
IC201	TM8812CSDNG6H60	IC(MCU)		
IC421	LA78041	IC		
IC601	NJW1143AV-W	IC		
IC651	LA42072NL	IC		
IC702	ATE08-32F577Y	IC	(SERVICE)	
IC703	S-80840CLNB-G-W	IC		
IC704	S78L05-T	IC		
IC851	PQ1CG2032FZ	IC		
IC852	S7809PI	IC		
IC853	PQ05RD21SSJH	IC		
IC855	PQ070XF01SZH	IC		
IC856	MP2263DN-C053-X	IC		
⚠IC911	STR-G9626-F3	IC		
⚠IC921	SE135N	IC		
Q001	2SK1374-X	MOS FET		
Q002	2SK1374-X	MOS FET		
Q003	2SK1374-X	MOS FET		
Q004	2SK1374-X	MOS FET		
Q005	RT1N440C-X	TRANSISTOR		
Q352	2SC3928A/QR/-X	TRANSISTOR		
Q501	2SC4212/Z1/	TRANSISTOR		
⚠Q511	TT2202-YD	POWER TRANST		
⚠Q531	2SC2785/JH/-T	TRANSISTOR		
Q532	2SA1530A/QR/-X	TRANSISTOR		
Q541	2SA1530A/QR/-X	TRANSISTOR		
Q542	2SA1530A/QR/-X	TRANSISTOR		
Q543	2SD1267A/QP/	POW TRANSISTOR		
Q671	RT1N441C-X	TRANSISTOR		
Q682	2SA1530A/QR/-X	TRANSISTOR		
Q683	RT1N441C-X	TRANSISTOR		
Q684	2SC3928A/QR/-X	TRANSISTOR		
Q701	2SA1530A/QR/-X	TRANSISTOR		
Q730	RT1N441C-X	TRANSISTOR		
Q951	2SD1383K/AB/-X	SI TRANSISTOR		
Q971	2SA1208/ST/Z1-T	TRANSISTOR		
D308	MTZJ5.1B-T2	Z DIODE		
D309	MTZJ5.1B-T2	Z DIODE		
D310	MTZJ5.1B-T2	Z DIODE		
D352	MTZJ9.1C-T2	Z DIODE		
D353	1SS133-T2	SI DIODE		
D354	MTZJ3.3A-T2	Z DIODE		
D421	1N4003SG-T2	SI DIODE		
D422	MTZJ75-T2	Z DIODE		
D501	RH3G-F1	SI DIODE		
D502	RU3AM-LFC4	SI DIODE		
D521	FR105GT-T3	SI DIODE		
D523	FR105GT-T3	SI DIODE		
D525	1SS81-T5	SI DIODE		
D526	1SS81-T5	SI DIODE		
D527	1SR124-400A-T2	SI DIODE		
D529	MTZJ9.1C-T2	Z DIODE		
⚠D531	MA4068N/Z1/-T2	Z DIODE		
D535	1SS133-T2	SI DIODE		
D681	1SS133-T2	SI DIODE		
D682	1SS133-T2	SI DIODE		
D683	1SS133-T2	SI DIODE		
D684	1SS133-T2	SI DIODE		
D701	1SS133-T2	SI DIODE		
D705	1SS133-T2	SI DIODE		
D730	1SS133-T2	SI DIODE		
D851	EC31QS04-X	SB DIODE		
D852	1SS133-T2	SI DIODE		
D855	1SS133-T2	SI DIODE		
D856	EC30HA03L-X	SB DIODE		
D857	EC30HA03L-X	SB DIODE		
D861	PTZ3.9B-X	Z DIODE		
D862	PTZ3.9B-X	Z DIODE		
⚠D901	GSIB460	BRIDGE DIODE		
D910	MA700A-T2	SB DIODE		
D911	FR105GT-T3	SI DIODE		
D912	FR105GT-T3	SI DIODE		
D913	1SS133-T2	SI DIODE		
D914	1SS133-T2	SI DIODE		
D915	SARS01-T2	FR DIODE		
D917	MTZJ30A-T2	Z DIODE		
D918	MTZJ5.1C-T2	Z DIODE		
D920	1SS133-T2	SI DIODE		
D931	RU4AM-LFT2	SI DIODE		
D933	HER202G-FL	SI DIODE		
D935	HER202G-FL	SI DIODE		
D938	HER202G-FL	SI DIODE		
D941	MTZJ33A-T2	Z DIODE		
D945	MTZJ9.1B-T2	Z DIODE		
D952	1SS133-T2	SI DIODE		
D953	1SS133-T2	SI DIODE		
D954	1N4003SG-T2	SI DIODE		
D955	1N4003SG-T2	SI DIODE		
D956	1N4003SG-T2	SI DIODE		
D957	1N4003SG-T2	SI DIODE		
D972	MTZJ15C-T2	Z DIODE		
D973	1SS133-T2	SI DIODE		
C009	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C101	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C102	NCB31HK-562X	C CAPACITOR	5600pF	50V K
C103	NCB31EK-123X	C CAPACITOR	0.012uF	25V K
C104	NCB31CK-105X	C CAPACITOR	1uF	16V K
C105	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C106	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C107	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C108	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C109	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C110	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C111	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C112	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C113	NCB31HK-272X	C CAPACITOR	2700pF	50V K
C114	NCB31HK-473X	C CAPACITOR	0.047uF	50V K
C115	QETN1HM-335Z	E CAPACITOR	3.3uF	50V M
C116	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C117	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C118	NCB31CK-105X	C CAPACITOR	1uF	16V K
C119	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C120	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C121	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C202	NCB21AK-105X	C CAPACITOR	1uF	10V K
C203	NCB31HK-152X	C CAPACITOR	1500pF	50V K
C221	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C222	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C237	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C241	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C242	NCB21AK-225X	C CAPACITOR	2.2uF	10V K
C243	QETN0JM-227Z	E CAPACITOR	220uF	6.3V M
C244	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C281	QFVF1HJ-474Z	MF CAPACITOR	0.47uF	50V J
C282	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C283	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C284	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C285	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C286	NCB21CK-474X	C CAPACITOR	0.47uF	16V K
C287	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C288	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C289	NCB21AK-105X	C CAPACITOR	1uF	10V K
C290	NCB21AK-105X	C CAPACITOR	1uF	10V K
C291	NCB21AK-105X	C CAPACITOR	1uF	10V K
C301	NCZ1064-225X	C CAPACITOR	2.2uF	
C302	NCB31EK-104X	C CAPACITOR	0.1uF	25V K
C352	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C354	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C360	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C391	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C392	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C422	QFN32AK-102Z	M CAPACITOR	1000pF	100V K
C424	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C425	QETN1VM-477Z	E CAPACITOR	470uF	35V M
C427	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C428	QETM1EM-228	E CAPACITOR	2200uF	25V M
C431	QFLC2AK-563Z	M CAPACITOR	0.056uF	100V K
C433	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C435	NCB31HK-183X	C CAPACITOR	0.018uF	50V K
C440	QCS32HJ-100Z	C CAPACITOR	10pF	500V J
C501	QCB32HK-151Z	C CAPACITOR	150pF	500V K
C502	QCB32HK-331Z	C CAPACITOR	330pF	500V K
C503	QEHR2CM-105Z	E CAPACITOR	1uF	160V M
C504	QEZ0203-107	E CAPACITOR	100uF	160V M
C507	QEZ0195-475Z	E CAPACITOR	4.7uF	50V M
⚠C510	QFZ0200-422	MPP CAPACITOR	4200pF	1.5kV H
⚠C513	QFZ0198-133	MPP CAPACITOR	0.013uF	1.5kV H
C514	QFP32JJ-183	PP CAPACITOR	0.018uF	630V J
C515	QFZ0197-474	MPP CAPACITOR	0.47uF	250V J
C516	QCB32HK-561Z	C CAPACITOR	560pF	500V K
C521	QETN2EM-106Z	E CAPACITOR	10uF	250V M
C523	QEHR1VM-108Z	E CAPACITOR	1000uF	35V M
C525	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C526	QFV21HJ-824Z	MF CAPACITOR	0.82uF	50V J
C527	QFLC2AJ-103Z	M CAPACITOR	0.01uF	100V J
C533	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C621	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C623	NCB31HK-102X	C CAPACITOR	1000pF	50V K
C624	NCB31CK-334X	C CAPACITOR	0.33uF	16V K

⚠Ref No.	Part No.	Part Name	Description Local
C625	NCB31HK-822X	C CAPACITOR	8200pF 50V K
C627	NCB31CK-105X	C CAPACITOR	1uF 16V K
C628	NCB31CK-105X	C CAPACITOR	1uF 16V K
C629	NCB31CK-105X	C CAPACITOR	1uF 16V K
C630	NCB31CK-105X	C CAPACITOR	1uF 16V K
C631	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C633	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C634	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C635	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C636	QETN1HM-105Z	E CAPACITOR	1uF 50V M
C637	NCB31CK-105X	C CAPACITOR	1uF 16V K
C638	NCB31CK-105X	C CAPACITOR	1uF 16V K
C651	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C652	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C653	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C654	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C655	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C656	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C661	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C662	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C663	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C666	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C671	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C683	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C684	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C701	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C702	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C703	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C704	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C705	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C706	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C708	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C709	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C710	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C711	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C712	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C728	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C730	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C807	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C851	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C852	NCB31EK-104X	C CAPACITOR	0.1uF 25V K
C853	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C854	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C856	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C857	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C858	QEZ0256-128	E CAPACITOR	1200uF 10V M
C861	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C865	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C866	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C868	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C869	QCZ0397-106Z	C CAPACITOR	10uF 25V M
C871	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C874	NCB31EK-273X	C CAPACITOR	0.027uF 25V K
C876	QEZ0256-128	E CAPACITOR	1200uF 10V M
C880	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
⚠C905	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C907	QEZ0644-567	E CAPACITOR	560uF 200V K
⚠C908	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C912	QCZ0340-222	C CAPACITOR	2200pF 2kV K
C913	QFLC1HJ-471Z	M CAPACITOR	470pF 50V J
C914	QETN1HM-107Z	E CAPACITOR	100uF 50V M
C916	NDC31HJ-331X	C CAPACITOR	330pF 50V J
C917	NCB31HK-182X	C CAPACITOR	1800pF 50V K
C918	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C919	QFP32GJ-103	PP CAPACITOR	0.01uF 400V J
C931	QEZ0203-227	E CAPACITOR	220uF 160V M
C932	QETN1CM-108Z	E CAPACITOR	1000uF 16V M
C933	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C934	NDC31HJ-221X	C CAPACITOR	220pF 50V J
C935	QETN1VM-108Z	E CAPACITOR	1000uF 35V M
C937	QCZ0340-102	C CAPACITOR	1000pF 2kV K
C938	QETN1EM-227Z	E CAPACITOR	220uF 25V M
C939	QCB32HK-152Z	C CAPACITOR	1500pF 500V K
C941	QCB32HK-102Z	C CAPACITOR	1000pF 500V K
C942	QEHR1HM-105Z	E CAPACITOR	1uF 50V M
C943	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C951	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C952	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C971	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C972	QETN1EM-476Z	E CAPACITOR	47uF 25V M
⚠C998	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
⚠C999	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
R001	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R002	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R003	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R004	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R005	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R006	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R007	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J

⚠Ref No.	Part No.	Part Name	Description Local
R008	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R101	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R102	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R103	NRSA63J-105X	MG RESISTOR	1MΩ 1/16W J
R104	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R105	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R106	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R107	NRSA63D-623X	MG RESISTOR	62kΩ 1/16W D
R108	NRSA63J-332X	MG RESISTOR	3.3kΩ 1/16W J
R109	NRSA63D-302X	MG RESISTOR	3kΩ 1/16W D
R110	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R201	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R227	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R281	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J
R282	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R283	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R286	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R287	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R288	NRSA02J-471X	MG RESISTOR	470Ω 1/10W J
R289	NRSA63J-154X	MG RESISTOR	150kΩ 1/16W J
R290	NRSA02J-561X	MG RESISTOR	560Ω 1/10W J
R292	NRSA63J-124X	MG RESISTOR	120kΩ 1/16W J
R293	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J
R294	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R295	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R296	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R301	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R302	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R303	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R304	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R305	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R306	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R318	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R319	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R354	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R355	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R356	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R359	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R421	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R423	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R424	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R426	NRSA63J-183X	MG RESISTOR	18kΩ 1/16W J
R427	QRT029J-1R2	MF RESISTOR	1.2Ω 2W J
R428	QRE121J-120Y	C RESISTOR	12Ω 1/2W J
R429	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J
R431	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J
R432	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R433	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R434	QRL029J-221	OMF RESISTOR	220Ω 2W J
R435	QRE121J-102Y	C RESISTOR	1kΩ 1/2W J
R441	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R502	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R503	QRE121J-103Y	C RESISTOR	10kΩ 1/2W J
R504	QRL039J-152	OMF RESISTOR	1.5kΩ 3W J
R505	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R511	QRE121J-220Y	C RESISTOR	22Ω 1/2W J
R512	QRE121J-681Y	C RESISTOR	680Ω 1/2W J
R516	QRZ0221-2R0	OMF RESISTOR	2Ω 7W K
R524	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R526	QRE121J-272Y	C RESISTOR	2.7kΩ 1/2W J
R527	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R528	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R529	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
⚠R531	QRE121J-391Y	C RESISTOR	390Ω 1/2W J
R532	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R533	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R534	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
⚠R535	NRVA02D-272X	CMF RESISTOR	2.7kΩ 1/10W D
R536	QRE121J-470Y	C RESISTOR	47Ω 1/2W J
R537	NRVA02D-752X	CMF RESISTOR	7.5kΩ 1/10W D
R538	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
R543	QRE121J-122Y	C RESISTOR	1.2kΩ 1/2W J
R544	QRE121J-392Y	C RESISTOR	3.9kΩ 1/2W J
R545	QRE121J-822Y	C RESISTOR	8.2kΩ 1/2W J
R546	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
R547	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R548	QRE121J-152Y	C RESISTOR	1.5kΩ 1/2W J
R553	QRL039J-330	OMF RESISTOR	33Ω 3W J
⚠R554	QRK126J-220X	UNF C RESISTOR	22Ω 1/2W J
R555	QRT029J-2R2	MF RESISTOR	2.2Ω 2W J
R621	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R624	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R625	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R631	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R638	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R639	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R651	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R652	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R653	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J

⚠Ref No.	Part No.	Part Name	Description	Local
R654	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R661	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	
R662	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R663	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R664	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R672	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R683	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R685	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R686	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R687	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R688	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R689	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R690	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R691	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R701	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R702	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R704	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R705	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R706	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R707	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R708	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R709	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R710	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R711	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R716	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R718	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R729	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R731	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R732	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R733	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R734	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R735	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R736	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R738	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R739	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R740	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R769	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R772	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R811	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R816	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R821	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R827	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R852	NRSA63D-123X	MG RESISTOR	12kΩ 1/16W D	
R853	NRSA63D-182X	MG RESISTOR	1.8kΩ 1/16W D	
R854	NRSA63D-122X	MG RESISTOR	1.2kΩ 1/16W D	
R855	QRL029J-820	OMF RESISTOR	82Ω 2W J	
R858	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R860	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	
R861	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R862	NRSA63D-332X	MG RESISTOR	3.3kΩ 1/16W D	
R863	NRSA63D-103X	MG RESISTOR	10kΩ 1/16W D	
R865	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R879	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R880	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R881	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J	
R901	QRF074K-1R2	UNF WW RESISTOR	1.2Ω 7W K	
R909	QRG01GJ-470	OMF RESISTOR	47Ω 1W J	
R911	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R912	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R913	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
⚠R914	QRK126J-681X	UNF C RESISTOR	680Ω 1/2W J	
R915	QRK129J-6R8	UNF C RESISTOR	6.8Ω 1/2W J	
⚠R917	QRK126J-332X	UNF C RESISTOR	3.3kΩ 1/2W J	
R918	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R919	QRE121J-684Y	C RESISTOR	680kΩ 1/2W J	
R924	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R930	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R940	QRE121J-181Y	C RESISTOR	180Ω 1/2W J	
R941	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R942	QRT039J-R68	MF RESISTOR	0.68Ω 3W J	
R950	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R951	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R952	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R953	QRE121J-820Y	C RESISTOR	82Ω 1/2W J	
R972	NRVA02D-102X	CMF RESISTOR	1kΩ 1/10W D	
R973	NRVA02D-332X	CMF RESISTOR	3.3kΩ 1/10W D	
R975	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R977	QRE121J-473Y	C RESISTOR	47kΩ 1/2W J	
R978	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
L001	QQL244K-6R8Z	PEAKING COIL	6.8uH K	
L241	QQL244K-220Z	PEAKING COIL	22uH K	
L391	QQL244K-220Z	PEAKING COIL	22uH K	
L511	QQR1027-003	LINEARITY COIL		
L512	QQLZ036-821	COIL	820uH K	
L521	QQLZ018-800	COIL	80uH	
L704	QQL244K-220Z	PEAKING COIL	22uH K	
L705	QQL244K-220Z	PEAKING COIL	22uH K	
L851	QQR1401-001	CHOKE COIL		
L853	QQL26AK-330Z	CHOKE COIL	33uH K	
L854	QQL26AK-470Z	CHOKE COIL	47uH K	
L855	QQL26AK-100Z	CHOKE COIL	10uH K	
L860	QQL28AK-150	COIL	15uH K	
L861	QQR1401-001	CHOKE COIL		
L931	QQL26AK-470Z	CHOKE COIL	47uH K	
L933	QQL26AK-470Z	CHOKE COIL	47uH K	
L937	QQL26AK-470Z	CHOKE COIL	47uH K	
L940	QQR0582-001Z	FERRITE BEADS		
T501	QQR1414-001	DRIVE TRANSF		
⚠T921	QQS0376-001	SW TRANSF		
CN001	QGB1221J1-80	CONNECTOR	B-B (1-80)	
CN002	QGB1505J1-35	CONNECTOR	B-B (1-35)	
CN00F	QJB003-032213-E	SIN ID C-B WIRE		
CN00W	WJK0200-004A-E	E-SI C WIRE C-B		
⚠CP936	ICP-N70-T	IC PROTECTOR	2.5A	
⚠FR525	QRZ9017-4R7	FUSI RESISTOR	4.7Ω 1/4W J	
K002	QQR0621-002Z	FERRITE BEADS		
K004	QQR0621-002Z	FERRITE BEADS		
K007	NQR0499-002X	FERRITE BEADS		
K008	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
K401	QQR0621-002Z	FERRITE BEADS		
K912	QQR0582-001Z	FERRITE BEADS		
K916	QQR0582-001Z	FERRITE BEADS		
K917	QQR0582-001Z	FERRITE BEADS		
K918	QQR0582-001Z	FERRITE BEADS		
K920	QQR1139-001	FERRITE BEADS		
K931	QQR0582-001Z	FERRITE BEADS		
K932	QQR0582-001Z	FERRITE BEADS		
K933	QQR0582-001Z	FERRITE BEADS		
K935	QQR0582-001Z	FERRITE BEADS		
K937	QQR0582-001Z	FERRITE BEADS		
⚠PC921	PS2581AL1/QW/	PHOTO COUPLER		
⚠RY951	QSK0085-001	RELAY		
S421	QSW1142-001	LEVER SWITCH	V.CENTER	
⚠TH901	QAD0132-3R0	P THERMISTOR	3Ω	
X701	QAX0767-001Z	CRYSTAL	8.000000MHz	

CRT SOCKET P.W. BOARD ASS'Y (SGJ-3301A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
Q3103	2SC3928A/QR/-X	TRANSISTOR		
Q3107	2SA2005/DE/	POW TRANSISTOR		
Q3108	2SC5511/DE/	POW TRANSISTOR		
Q3109	2SC3928A/QR/-X	TRANSISTOR		
Q3304	2SC4544-LB	POW TRANSISTOR		
Q3305	2SC4544-LB	POW TRANSISTOR		
Q3306	2SC4544-LB	POW TRANSISTOR		
Q3351	2SA1530A/QR/-X	TRANSISTOR		
D3105	RH1S-T3	SI DIODE		
D3106	RH1S-T3	SI DIODE		
D3331	1SS133-T2	SI DIODE		
D3351	1SS133-T2	SI DIODE		
D3352	1SS133-T2	SI DIODE		
D3353	1SS133-T2	SI DIODE		
D3354	1SS133-T2	SI DIODE		
C3101	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C3113	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3114	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3115	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3117	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3118	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C3119	QETN1AM-107Z	E CAPACITOR	100uF 10V M	
C3120	QETN1AM-337Z	E CAPACITOR	330uF 10V M	
C3121	QCS32HJ-151Z	C CAPACITOR	150pF 500V J	
C3127	NDC31HJ-471X	C CAPACITOR	470pF 50V J	
C3301	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3302	NDC31HJ-391X	C CAPACITOR	390pF 50V J	
C3303	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3323	QETN1CM-477Z	E CAPACITOR	470uF 16V M	
C3331	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3332	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3333	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3351	QETN1CM-227Z	E CAPACITOR	220uF 16V M	
C3363	QCZ0121-102	C CAPACITOR	1000pF 3KV Z	
R3115	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3116	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3122	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
R3123	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3124	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3125	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3126	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	

⚠Ref No.	Part No.	Part Name	Description	Local
R3127	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3128	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3129	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3130	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3131	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3132	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R3134	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3136	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R3139	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3142	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R3143	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3144	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3145	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3146	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3148	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3301	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3302	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3303	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3304	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3305	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3306	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3307	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3308	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3309	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3310	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3311	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3312	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3313	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3314	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3315	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3325	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3326	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3327	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3331	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3332	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3333	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3334	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R3335	NRSA63J-391X	MG RESISTOR	390Ω 1/16W J	
R3351	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3354	NRSA63J-561X	MG RESISTOR	560Ω 1/16W J	
R3355	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
L3304	QQL244K-470Z	PEAKING COIL	47uH K	
CN300A	WJA0029-002A-E	E-SI ID WIRE		
CN300E	QJB003-074022-E	SIN ID C-B WIRE		
CN30E2	QUB130-46A6AS-E	SIN TWIST WIRE		
CN30E4	QUB130-46A6AS-E	SIN TWIST WIRE		
K3104	QQR1114-001Z	FERRITE BEADS		
K3105	QQR1114-001Z	FERRITE BEADS		
⚠SK3001	QNZ0536-002	CRT SOCKET		

AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2)

REFER TO PARTS LIST IN PAGE 3-9 FOR THIS P.W. BOARD.

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

USB P.W. BOARD ASS'Y (SGJ-8302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

L/F P.W. BOARD ASS'Y (SGJ-9301A-M2)

REFER TO PARTS LIST IN PAGE 3-18 FOR THIS P.W. BOARD.

ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

PRINTED WIRING BOARD PARTS LIST [AV-32F577/Z]

MAIN P.W. BOARD ASS'Y (SGJ-1307A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
IC101	CXA2094Q-X	IC		
IC201	TM8812CSDNG6H60	IC(MCU)		
IC421	LA78041	IC		
IC601	NJW1143AV-W	IC		
IC651	LA42072NL	IC		
IC702	ATE08-32F577Z	IC	(SERVICE)	
IC703	S-80840CLNB-G-W	IC		
IC704	S78L05-T	IC		
IC851	PQ1CG2032FZ	IC		
IC852	S7809PI	IC		
IC853	PQ05RD21SSJH	IC		
IC855	PQ070XF01SZH	IC		
IC856	MP2263DN-C053-X	IC		
⚠IC911	STR-G9626-F3	IC		
⚠IC921	SE135N	IC		
Q001	2SK1374-X	MOS FET		
Q002	2SK1374-X	MOS FET		
Q003	2SK1374-X	MOS FET		
Q004	2SK1374-X	MOS FET		
Q005	RT1N440C-X	TRANSISTOR		
Q352	2SC3928A/QR/-X	TRANSISTOR		
Q501	2SC4212/Z1/	TRANSISTOR		
⚠Q511	TT2202-YD	POWER TRANST		
⚠Q531	2SC2785/JH/-T	TRANSISTOR		
Q532	2SA1530A/QR/-X	TRANSISTOR		
Q541	2SA1530A/QR/-X	TRANSISTOR		
Q542	2SA1530A/QR/-X	TRANSISTOR		
Q543	2SD1267A/QP/	POW TRANSISTOR		
Q671	RT1N441C-X	TRANSISTOR		
Q682	2SA1530A/QR/-X	TRANSISTOR		
Q683	RT1N441C-X	TRANSISTOR		
Q684	2SC3928A/QR/-X	TRANSISTOR		
Q701	2SA1530A/QR/-X	TRANSISTOR		
Q730	RT1N441C-X	TRANSISTOR		
Q951	2SD1383K/AB/-X	SI TRANSISTOR		
Q971	2SA1208/ST/Z1-T	TRANSISTOR		
D308	MTZJ5.1B-T2	Z DIODE		
D309	MTZJ5.1B-T2	Z DIODE		
D310	MTZJ5.1B-T2	Z DIODE		
D352	MTZJ9.1C-T2	Z DIODE		
D353	1SS133-T2	SI DIODE		
D354	MTZJ3.3A-T2	Z DIODE		
D421	1N4003SG-T2	SI DIODE		
D422	MTZJ75-T2	Z DIODE		
D501	RH3G-F1	SI DIODE		
D502	RU3AM-LFC4	SI DIODE		
D521	FR105GT-T3	SI DIODE		
D523	FR105GT-T3	SI DIODE		
D525	1SS81-T5	SI DIODE		
D526	1SS81-T5	SI DIODE		
D527	1SR124-400A-T2	SI DIODE		
D529	MTZJ9.1C-T2	Z DIODE		
⚠D531	MA4068N/Z1/-T2	Z DIODE		
D535	1SS133-T2	SI DIODE		
D681	1SS133-T2	SI DIODE		
D682	1SS133-T2	SI DIODE		
D683	1SS133-T2	SI DIODE		
D684	1SS133-T2	SI DIODE		
D701	1SS133-T2	SI DIODE		
D705	1SS133-T2	SI DIODE		
D730	1SS133-T2	SI DIODE		
D851	EC31QS04-X	SB DIODE		
D852	1SS133-T2	SI DIODE		
D855	1SS133-T2	SI DIODE		
D856	EC30HA03L-X	SB DIODE		
D857	EC30HA03L-X	SB DIODE		
D861	PTZ3.9B-X	Z DIODE		
D862	PTZ3.9B-X	Z DIODE		
⚠D901	GSIB460	BRIDGE DIODE		
D910	MA700A-T2	SB DIODE		
D911	FR105GT-T3	SI DIODE		
D912	FR105GT-T3	SI DIODE		
D913	1SS133-T2	SI DIODE		
D914	1SS133-T2	SI DIODE		
D915	SARS01-T2	FR DIODE		
D917	MTZJ30A-T2	Z DIODE		
D918	MTZJ5.1C-T2	Z DIODE		
D920	1SS133-T2	SI DIODE		
D931	RU4AM-LFT2	SI DIODE		
D933	HER202G-FL	SI DIODE		
D935	HER202G-FL	SI DIODE		
D938	HER202G-FL	SI DIODE		
D941	MTZJ33A-T2	Z DIODE		
D945	MTZJ9.1B-T2	Z DIODE		
D952	1SS133-T2	SI DIODE		
D953	1SS133-T2	SI DIODE		
D954	1N4003SG-T2	SI DIODE		
D955	1N4003SG-T2	SI DIODE		
D956	1N4003SG-T2	SI DIODE		
D957	1N4003SG-T2	SI DIODE		
D972	MTZJ15C-T2	Z DIODE		
D973	1SS133-T2	SI DIODE		
C009	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C101	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C102	NCB31HK-562X	C CAPACITOR	5600pF	50V K
C103	NCB31EK-123X	C CAPACITOR	0.012uF	25V K
C104	NCB31CK-105X	C CAPACITOR	1uF	16V K
C105	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C106	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C107	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C108	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C109	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C110	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C111	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C112	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C113	NCB31HK-272X	C CAPACITOR	2700pF	50V K
C114	NCB31HK-473X	C CAPACITOR	0.047uF	50V K
C115	QETN1HM-335Z	E CAPACITOR	3.3uF	50V M
C116	QENC1EM-475Z	BP E CAPACITOR	4.7uF	25V M
C117	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C118	NCB31CK-105X	C CAPACITOR	1uF	16V K
C119	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C120	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C121	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C202	NCB21AK-105X	C CAPACITOR	1uF	10V K
C203	NCB31HK-152X	C CAPACITOR	1500pF	50V K
C221	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C222	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C237	NCB31CK-104X	C CAPACITOR	0.1uF	16V K
C241	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C242	NCB21AK-225X	C CAPACITOR	2.2uF	10V K
C243	QETN0JM-227Z	E CAPACITOR	220uF	6.3V M
C244	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C281	QFVF1HJ-474Z	MF CAPACITOR	0.47uF	50V J
C282	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C283	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C284	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C285	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C286	NCB21CK-474X	C CAPACITOR	0.47uF	16V K
C287	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C288	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C289	NCB21AK-105X	C CAPACITOR	1uF	10V K
C290	NCB21AK-105X	C CAPACITOR	1uF	10V K
C291	NCB21AK-105X	C CAPACITOR	1uF	10V K
C301	NCZ1064-225X	C CAPACITOR	2.2uF	
C302	NCB31EK-104X	C CAPACITOR	0.1uF	25V K
C352	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C354	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C360	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C391	QETN1CM-107Z	E CAPACITOR	100uF	16V M
C392	NCB31HK-103X	C CAPACITOR	0.01uF	50V K
C422	QFN32AK-102Z	M CAPACITOR	1000pF	100V K
C424	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C425	QETN1VM-477Z	E CAPACITOR	470uF	35V M
C427	QETN1HM-225Z	E CAPACITOR	2.2uF	50V M
C428	QETM1EM-228	E CAPACITOR	2200uF	25V M
C431	QFLC2AK-563Z	M CAPACITOR	0.056uF	100V K
C433	QETN1EM-476Z	E CAPACITOR	47uF	25V M
C435	NCB31HK-183X	C CAPACITOR	0.018uF	50V K
C440	QCS32HJ-100Z	C CAPACITOR	10pF	500V J
C501	QCB32HK-151Z	C CAPACITOR	150pF	500V K
C502	QCB32HK-331Z	C CAPACITOR	330pF	500V K
C503	QEHR2CM-105Z	E CAPACITOR	1uF	160V M
C504	QEZ0203-107	E CAPACITOR	100uF	160V M
C507	QEZ0195-475Z	E CAPACITOR	4.7uF	50V M
⚠C510	QFZ0200-382	MPP CAPACITOR	3800pF	1.5kV H
⚠C513	QFZ0196-103	MPP CAPACITOR	0.01uF	1.5kV H
C514	QFP32JJ-183	PP CAPACITOR	0.018uF	630V J
C515	QFZ0197-404	MPP CAPACITOR	0.4uF	250V J
C516	QCB32HK-561Z	C CAPACITOR	560pF	500V K
C521	QETN2EM-106Z	E CAPACITOR	10uF	250V M
C523	QEHR1VM-108Z	E CAPACITOR	1000uF	35V M
C525	QETN1VM-107Z	E CAPACITOR	100uF	35V M
C526	QFV21HJ-824Z	MF CAPACITOR	0.82uF	50V J
C527	QFLC2AJ-103Z	M CAPACITOR	0.01uF	100V J
C533	QETN1HM-106Z	E CAPACITOR	10uF	50V M
C621	QETN1HM-475Z	E CAPACITOR	4.7uF	50V M
C623	NCB31HK-102X	C CAPACITOR	1000pF	50V K
C624	NCB31CK-334X	C CAPACITOR	0.33uF	16V K

⚠Ref No.	Part No.	Part Name	Description Local
C625	NCB31HK-822X	C CAPACITOR	8200pF 50V K
C627	NCB31CK-105X	C CAPACITOR	1uF 16V K
C628	NCB31CK-105X	C CAPACITOR	1uF 16V K
C629	NCB31CK-105X	C CAPACITOR	1uF 16V K
C630	NCB31CK-105X	C CAPACITOR	1uF 16V K
C631	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C633	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C634	NCB31CK-334X	C CAPACITOR	0.33uF 16V K
C635	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C636	QETN1HM-105Z	E CAPACITOR	1uF 50V M
C637	NCB31CK-105X	C CAPACITOR	1uF 16V K
C638	NCB31CK-105X	C CAPACITOR	1uF 16V K
C651	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C652	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C653	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C654	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C655	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C656	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C661	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C662	QETN1HM-475Z	E CAPACITOR	4.7uF 50V M
C663	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C666	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C671	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C683	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C684	QETN1CM-476Z	E CAPACITOR	47uF 16V M
C701	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C702	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C703	QETN1HM-106Z	E CAPACITOR	10uF 50V M
C704	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C705	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C706	NCB31HK-102X	C CAPACITOR	1000pF 50V K
C708	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C709	NDC31HJ-220X	C CAPACITOR	22pF 50V J
C710	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C711	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C712	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C728	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C730	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C807	NCB31CK-104X	C CAPACITOR	0.1uF 16V K
C851	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C852	NCB31EK-104X	C CAPACITOR	0.1uF 25V K
C853	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C854	QETN1EM-107Z	E CAPACITOR	100uF 25V M
C856	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C857	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C858	QEZ0256-128	E CAPACITOR	1200uF 10V M
C861	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C865	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C866	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M
C868	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C869	QCZ0397-106Z	C CAPACITOR	10uF 25V M
C871	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
C874	NCB31EK-273X	C CAPACITOR	0.027uF 25V K
C876	QEZ0256-128	E CAPACITOR	1200uF 10V M
C880	NCB31HK-103X	C CAPACITOR	0.01uF 50V K
⚠C905	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C907	QEZ0644-567	E CAPACITOR	560uF 200V K
⚠C908	QCZ9054-102	C CAPACITOR	1000pF AC250V Z
C912	QCZ0340-222	C CAPACITOR	2200pF 2kV K
C913	QFLC1HJ-471Z	M CAPACITOR	470pF 50V J
C914	QETN1HM-107Z	E CAPACITOR	100uF 50V M
C916	NDC31HJ-331X	C CAPACITOR	330pF 50V J
C917	NCB31HK-182X	C CAPACITOR	1800pF 50V K
C918	NCB31HK-104X	C CAPACITOR	0.1uF 50V K
C919	QFP32GJ-103	PP CAPACITOR	0.01uF 400V J
C931	QEZ0203-227	E CAPACITOR	220uF 160V M
C932	QETN1CM-108Z	E CAPACITOR	1000uF 16V M
C933	QETN1EM-108Z	E CAPACITOR	1000uF 25V M
C934	NDC31HJ-221X	C CAPACITOR	220pF 50V J
C935	QETN1VM-108Z	E CAPACITOR	1000uF 35V M
C937	QCZ0340-102	C CAPACITOR	1000pF 2kV K
C938	QETN1EM-227Z	E CAPACITOR	220uF 25V M
C939	QCB32HK-152Z	C CAPACITOR	1500pF 500V K
C941	QCB32HK-102Z	C CAPACITOR	1000pF 500V K
C942	QEHR1HM-105Z	E CAPACITOR	1uF 50V M
C943	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C951	QETN1EM-477Z	E CAPACITOR	470uF 25V M
C952	QETN1CM-227Z	E CAPACITOR	220uF 16V M
C971	QETN1CM-107Z	E CAPACITOR	100uF 16V M
C972	QETN1EM-476Z	E CAPACITOR	47uF 25V M
⚠C998	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
⚠C999	QCZ9074-103	C CAPACITOR	0.01uF AC250V M
R001	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R002	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R003	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R004	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R005	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R006	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R007	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R008	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R101	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R102	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R103	NRSA63J-105X	MG RESISTOR	1MΩ 1/16W J
R104	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R105	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R106	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R107	NRSA63D-623X	MG RESISTOR	62kΩ 1/16W D
R108	NRSA63J-332X	MG RESISTOR	3.3kΩ 1/16W J
R109	NRSA63D-302X	MG RESISTOR	3kΩ 1/16W D
R110	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R201	NRSA63J-223X	MG RESISTOR	22kΩ 1/16W J
R227	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R281	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J
R282	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J
R283	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R286	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R287	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R288	NRSA02J-471X	MG RESISTOR	470Ω 1/10W J
R289	NRSA63J-154X	MG RESISTOR	150kΩ 1/16W J
R290	NRSA02J-561X	MG RESISTOR	560Ω 1/10W J
R292	NRSA63J-124X	MG RESISTOR	120kΩ 1/16W J
R293	NRSA63J-224X	MG RESISTOR	220kΩ 1/16W J
R294	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R295	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R296	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R301	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R302	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R303	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J
R304	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R305	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R306	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R318	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R319	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J
R354	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R355	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R356	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R359	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J
R421	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R423	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R424	NRSA63J-393X	MG RESISTOR	39kΩ 1/16W J
R426	NRSA63J-183X	MG RESISTOR	18kΩ 1/16W J
R427	QRT029J-1R2	MF RESISTOR	1.2Ω 2W J
R428	QRE121J-120Y	C RESISTOR	12Ω 1/2W J
R429	NRSA63J-272X	MG RESISTOR	2.7kΩ 1/16W J
R431	NRSA63J-152X	MG RESISTOR	1.5kΩ 1/16W J
R432	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R433	NRSA63J-681X	MG RESISTOR	680Ω 1/16W J
R434	QRL029J-221	OMF RESISTOR	220Ω 2W J
R435	QRE121J-821Y	C RESISTOR	820Ω 1/2W J
R441	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R501	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R502	NRSA63J-221X	MG RESISTOR	220Ω 1/16W J
R503	QRE121J-103Y	C RESISTOR	10kΩ 1/2W J
R504	QRL039J-152	OMF RESISTOR	1.5kΩ 3W J
R505	QRL039J-182	OMF RESISTOR	1.8kΩ 3W J
R511	QRE121J-220Y	C RESISTOR	22Ω 1/2W J
R512	QRE121J-681Y	C RESISTOR	680Ω 1/2W J
R516	QRZ0221-2R0	OMF RESISTOR	2Ω 7W K
R524	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J
R526	QRE121J-272Y	C RESISTOR	2.7kΩ 1/2W J
R527	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R528	QRE121J-154Y	C RESISTOR	150kΩ 1/2W J
R529	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
⚠R531	QRE121J-391Y	C RESISTOR	390Ω 1/2W J
R532	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J
R533	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
R534	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J
⚠R535	NRVA02D-242X	CMF RESISTOR	2.4kΩ 1/10W D
R536	QRE121J-470Y	C RESISTOR	47Ω 1/2W J
R537	NRVA02D-752X	CMF RESISTOR	7.5kΩ 1/10W D
R538	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J
R543	QRE121J-122Y	C RESISTOR	1.2kΩ 1/2W J
R544	QRE121J-392Y	C RESISTOR	3.9kΩ 1/2W J
R545	QRE121J-153Y	C RESISTOR	15kΩ 1/2W J
R546	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J
R547	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J
R548	QRE121J-152Y	C RESISTOR	1.5kΩ 1/2W J
R553	QRL039J-330	OMF RESISTOR	33Ω 3W J
⚠R554	QRK126J-220X	UNF C RESISTOR	22Ω 1/2W J
R555	QRT029J-2R2	MF RESISTOR	2.2Ω 2W J
R621	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R624	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R625	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R631	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J
R638	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R639	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J
R651	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J
R652	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J
R653	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J

⚠Ref No.	Part No.	Part Name	Description	Local
R654	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R661	NRSA63J-822X	MG RESISTOR	8.2kΩ 1/16W J	
R662	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R663	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R664	QRJ146J-2R2X	UNF C RESISTOR	2.2Ω 1/4W J	
R672	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R683	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R685	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R686	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R687	NRSA63J-153X	MG RESISTOR	15kΩ 1/16W J	
R688	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R689	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R690	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R691	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R701	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R702	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R703	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R704	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R705	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R706	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R707	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R708	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R709	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R710	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R711	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R716	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R718	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R729	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R731	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R732	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R733	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R734	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R735	NRSA63J-104X	MG RESISTOR	100kΩ 1/16W J	
R736	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R738	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R739	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R740	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R769	NRSA63J-682X	MG RESISTOR	6.8kΩ 1/16W J	
R772	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R811	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R816	NRSA63J-472X	MG RESISTOR	4.7kΩ 1/16W J	
R821	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R827	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R852	NRSA63D-123X	MG RESISTOR	12kΩ 1/16W D	
R853	NRSA63D-182X	MG RESISTOR	1.8kΩ 1/16W D	
R854	NRSA63D-122X	MG RESISTOR	1.2kΩ 1/16W D	
R855	QRL029J-820	OMF RESISTOR	82Ω 2W J	
R858	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R860	NRSA02J-0R0X	MG RESISTOR	0Ω 1/10W J	
R861	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R862	NRSA63D-332X	MG RESISTOR	3.3kΩ 1/16W D	
R863	NRSA63D-103X	MG RESISTOR	10kΩ 1/16W D	
R865	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
R879	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R880	NRSA63D-222X	MG RESISTOR	2.2kΩ 1/16W D	
R881	NRSA63J-273X	MG RESISTOR	27kΩ 1/16W J	
R901	QRF074K-1R2	UNF WW RESISTOR	1.2Ω 7W K	
R909	QRG01GJ-470	OMF RESISTOR	47Ω 1W J	
R911	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R912	QRT029J-R18	MF RESISTOR	0.18Ω 2W J	
R913	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
⚠R914	QRK126J-681X	UNF C RESISTOR	680Ω 1/2W J	
R915	QRK129J-6R8	UNF C RESISTOR	6.8Ω 1/2W J	
⚠R917	QRK126J-332X	UNF C RESISTOR	3.3kΩ 1/2W J	
R918	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R919	QRE121J-684Y	C RESISTOR	680kΩ 1/2W J	
R924	QRE121J-222Y	C RESISTOR	2.2kΩ 1/2W J	
R930	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R940	QRE121J-181Y	C RESISTOR	180Ω 1/2W J	
R941	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R942	QRT039J-R68	MF RESISTOR	0.68Ω 3W J	
R950	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
R951	NRSA63J-473X	MG RESISTOR	47kΩ 1/16W J	
R952	NRSA63J-102X	MG RESISTOR	1kΩ 1/16W J	
R953	QRE121J-820Y	C RESISTOR	82Ω 1/2W J	
R972	NRVA02D-102X	CMF RESISTOR	1kΩ 1/10W D	
R973	NRVA02D-332X	CMF RESISTOR	3.3kΩ 1/10W D	
R975	QRE121J-223Y	C RESISTOR	22kΩ 1/2W J	
R977	QRE121J-473Y	C RESISTOR	47kΩ 1/2W J	
R978	NRSA63J-333X	MG RESISTOR	33kΩ 1/16W J	
L001	QQL244K-6R8Z	PEAKING COIL	6.8uH K	
L241	QQL244K-220Z	PEAKING COIL	22uH K	
L391	QQL244K-220Z	PEAKING COIL	22uH K	
L511	QQR1165-001	LINEARITY COIL		
L512	QQLZ036-821	COIL	820uH K	
L521	QQLZ026-860	COIL	86uH	
L704	QQL244K-220Z	PEAKING COIL	22uH K	
L705	QQL244K-220Z	PEAKING COIL	22uH K	
L851	QQR1401-001	CHOKE COIL		
L853	QQL26AK-330Z	CHOKE COIL	33uH K	
L854	QQL26AK-470Z	CHOKE COIL	47uH K	
L855	QQL26AK-100Z	CHOKE COIL	10uH K	
L860	QQL28AK-150	COIL	15uH K	
L861	QQR1401-001	CHOKE COIL		
L931	QQL26AK-470Z	CHOKE COIL	47uH K	
L933	QQL26AK-470Z	CHOKE COIL	47uH K	
L937	QQL26AK-470Z	CHOKE COIL	47uH K	
L940	QQR0582-001Z	FERRITE BEADS		
T501	QQR1414-001	DRIVE TRANSF		
⚠T921	QQS0376-001	SW TRANSF		
CN001	QGB1221J1-80	CONNECTOR	B-B (1-80)	
CN002	QGB1505J1-35	CONNECTOR	B-B (1-35)	
CN00F	QJB003-032213-E	SIN ID C-B WIRE		
CN00W	WJK0200-004A-E	E-SI C WIRE C-B		
⚠CP936	ICP-N70-T	IC PROTECTOR	2.5A	
⚠FR525	QRZ9017-4R7	FUSI RESISTOR	4.7Ω 1/4W J	
K002	QQR0621-002Z	FERRITE BEADS		
K004	QQR0621-002Z	FERRITE BEADS		
K007	NQR0499-002X	FERRITE BEADS		
K008	NRSA63J-0R0X	MG RESISTOR	0Ω 1/16W J	
K401	QQR0621-002Z	FERRITE BEADS		
K912	QQR0582-001Z	FERRITE BEADS		
K916	QQR0582-001Z	FERRITE BEADS		
K917	QQR0582-001Z	FERRITE BEADS		
K918	QQR0582-001Z	FERRITE BEADS		
K920	QQR1139-001	FERRITE BEADS		
K931	QQR0582-001Z	FERRITE BEADS		
K932	QQR0582-001Z	FERRITE BEADS		
K933	QQR0582-001Z	FERRITE BEADS		
K935	QQR0582-001Z	FERRITE BEADS		
K937	QQR0582-001Z	FERRITE BEADS		
⚠PC921	PS2581AL1/QW/	PHOTO COUPLER		
⚠RY951	QSK0085-001	RELAY		
S421	QSW1142-001	LEVER SWITCH	V.CENTER	
⚠TH901	QAD0132-3R0	P THERMISTOR	3Ω	
X701	QAX0767-001Z	CRYSTAL	8.000000MHz	

CRT SOCKET P.W. BOARD ASS'Y (SGJ-3303A-M2)

⚠Ref No.	Part No.	Part Name	Description	Local
Q3103	2SC3928A/QR/-X	TRANSISTOR		
Q3107	2SA2005/DE/	POW TRANSISTOR		
Q3108	2SC5511/DE/	POW TRANSISTOR		
Q3109	2SC3928A/QR/-X	TRANSISTOR		
Q3304	2SC4544-LB	POW TRANSISTOR		
Q3305	2SC4544-LB	POW TRANSISTOR		
Q3306	2SC4544-LB	POW TRANSISTOR		
Q3351	2SA1530A/QR/-X	TRANSISTOR		
D3105	RH1S-T3	SI DIODE		
D3106	RH1S-T3	SI DIODE		
D3331	1SS133-T2	SI DIODE		
D3351	1SS133-T2	SI DIODE		
D3352	1SS133-T2	SI DIODE		
D3353	1SS133-T2	SI DIODE		
D3354	1SS133-T2	SI DIODE		
C3101	QETN1HM-106Z	E CAPACITOR	10uF 50V M	
C3113	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3114	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3115	QCB32HK-472Z	C CAPACITOR	4700pF 500V K	
C3117	QETN2CM-106Z	E CAPACITOR	10uF 160V M	
C3118	QETN0JM-107Z	E CAPACITOR	100uF 6.3V M	
C3119	QETN1AM-107Z	E CAPACITOR	100uF 10V M	
C3120	QETN1AM-337Z	E CAPACITOR	330uF 10V M	
C3121	QCS32HJ-151Z	C CAPACITOR	150pF 500V J	
C3127	NDC31HJ-471X	C CAPACITOR	470pF 50V J	
C3301	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3302	NDC31HJ-391X	C CAPACITOR	390pF 50V J	
C3303	NDC31HJ-561X	C CAPACITOR	560pF 50V J	
C3323	QETN1CM-477Z	E CAPACITOR	470uF 16V M	
C3331	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3332	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3333	NDC31HJ-181X	C CAPACITOR	180pF 50V J	
C3351	QETN1CM-227Z	E CAPACITOR	220uF 16V M	
C3363	QCZ0121-102	C CAPACITOR	1000pF 3KV Z	
R3115	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3116	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3122	QRT029J-R15	MF RESISTOR	0.15Ω 2W J	
R3123	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3124	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3125	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3126	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	

⚠Ref No.	Part No.	Part Name	Description	Local
R3127	NRSA63J-563X	MG RESISTOR	56kΩ 1/16W J	
R3128	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3129	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3130	NRSA63J-820X	MG RESISTOR	82Ω 1/16W J	
R3131	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3132	QRL029J-391	OMF RESISTOR	390Ω 2W J	
R3134	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3136	NRSA63J-392X	MG RESISTOR	3.9kΩ 1/16W J	
R3139	NRSA63J-331X	MG RESISTOR	330Ω 1/16W J	
R3142	NRSA63J-123X	MG RESISTOR	12kΩ 1/16W J	
R3143	NRSA63J-122X	MG RESISTOR	1.2kΩ 1/16W J	
R3144	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3145	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3146	NRSA63J-100X	MG RESISTOR	10Ω 1/16W J	
R3148	NRSA63J-101X	MG RESISTOR	100Ω 1/16W J	
R3301	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3302	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3303	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3304	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3305	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3306	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3307	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3308	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3309	NRSA63J-470X	MG RESISTOR	47Ω 1/16W J	
R3310	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3311	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3312	QRL029J-183	OMF RESISTOR	18kΩ 2W J	
R3313	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3314	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3315	QRL029J-223	OMF RESISTOR	22kΩ 2W J	
R3325	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3326	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3327	QRZ0107-102Z	C RESISTOR	1kΩ 1/2W K	
R3331	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3332	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3333	NRSA63J-222X	MG RESISTOR	2.2kΩ 1/16W J	
R3334	NRSA63J-182X	MG RESISTOR	1.8kΩ 1/16W J	
R3335	NRSA63J-391X	MG RESISTOR	390Ω 1/16W J	
R3351	NRSA63J-151X	MG RESISTOR	150Ω 1/16W J	
R3354	NRSA63J-561X	MG RESISTOR	560Ω 1/16W J	
R3355	NRSA63J-103X	MG RESISTOR	10kΩ 1/16W J	
L3304	QQL244K-470Z	PEAKING COIL	47uH K	
CN300A	WJA0029-002A-E	E-SI ID WIRE		
CN300E	QJB003-074022-E	SIN ID C-B WIRE		
CN30E2	QUB130-46A6AS-E	SIN TWIST WIRE		
CN30E4	QUB130-46A6AS-E	SIN TWIST WIRE		
K3104	QQR1114-001Z	FERRITE BEADS		
K3105	QQR1114-001Z	FERRITE BEADS		
⚠SK3001	QNZ0536-002	CRT SOCKET		

AV SW P.W. BOARD ASS'Y (SGJ-5301A-M2)

REFER TO PARTS LIST IN PAGE 3-9 FOR THIS P.W. BOARD.

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7301A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

USB P.W. BOARD ASS'Y (SGJ-8302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

L/F P.W. BOARD ASS'Y (SGJ-9301A-M2)

REFER TO PARTS LIST IN PAGE 3-18 FOR THIS P.W. BOARD.

ATSC TUNER MODULE P.W. BOARD ASS'Y (SSD-2302A-M2)

REFER TO PARTS LIST IN PAGE 3-10 FOR THIS P.W. BOARD.

REMOTE CONTROL UNIT PARTS LIST (RM-C1290G-1C)

⚠	Ref.No.	Part No.	Part Name	Description	Local
		10030-0006800	BATTERY COVER		

PACKING



PACKING PARTS LIST

⚠	Ref.No.	Part No.	Part Name	Description	Local
	1	LC10181-025C-A	PACKING CASE		AV-27F577R,AV-27F577S
	1	LC10181-026C-A	PACKING CASE		AV-32F577R,AV-32F577Y,AV-32F577Z
	2	LC10884-002B-A	CUSHION ASSY	4pcs in 1set	AV-27F577R,AV-27F577S
	2	LC11049-002B-A	CUSHION ASSY	4pcs in 1set	AV-32F577R,AV-32F577Y,AV-32F577Z
	3	GQ30092-005A-A	LAMINATE FILM BAG		AV-27F577R,AV-27F577S
	3	GQ30092-003A-A	LAMINATE FILM BAG		AV-32F577R,AV-32F577Y,AV-32F577Z
	4	QPA02503505	POLY BAG	25cm x 35cm	
	5	RM-C1290G-1C	REMOTE CONTROL UNIT		
⚠	6	LCT2033-001A-A	INST BOOK	English	
	7	----------	BATTERY	R6P/AA(x2)	
	8	BT-51034-2Q	REGIST. CARD		
	9	----------	WARRANTY CARD	BT-52006-2Q	

JVC

SCHEMATIC DIAGRAMS

COLOR TELEVISION

AV-27F577/R, AV-27F577/S, AV-32F577/R, AV-32F577/Y, AV-32F577/Z

CD-ROM No.SML200605

BASIC CHASSIS
GJ6

I'Art™

DCR

DOLBY DIGITAL

COPYRIGHT © 2006 Victor Company of Japan, Limited.

No.YA387
2006/5

AV-27F577/R, AV-27F577/S, AV-32F577/R, AV-32F577/Y, AV-32F577/Z

STANDARD CIRCUIT DIAGRAM

■ NOTE ON USING CIRCUIT DIAGRAMS

1.SAFETY

The components identified by the ⚠ symbol and shading are critical for safety. For continued safety replace safety ciritical components only with manufactures recommended parts.

2.SPECIFIED VOLTAGE AND WAVEFORM VALUES

The voltage and waveform values have been measured under the following conditions.

(1)Input signal	: Colour bar signal
(2)Setting positions of each knob/button and variable resistor	: Original setting position when shipped
(3)Internal resistance of tester	: DC 20kΩ/V
(4)Oscilloscope sweeping time	: H ⇒ 20μs / div
	: V ⇒ 5ms / div
	: Othters ⇒ Sweeping time is specified
(5)Voltage values	: All DC voltage values

∗ Since the voltage values of signal circuit vary to some extent according to adjustments, use them as reference values.

3.INDICATION OF PARTS SYMBOL [EXAMPLE]

● In the PW board : R1209 → R209

4.INDICATIONS ON THE CIRCUIT DIAGRAM

(1)Resistors

● Resistance value

No unit	: [Ω]
K	: [kΩ]
M	: [MΩ]

● Rated allowable power

No indication	: 1/16 [W]
Others	: As specified

● Type

No indication	: Carbon resistor
OMR	: Oxide metal film resistor
MFR	: Metal film resistor
MPR	: Metal plate resistor
UNFR	: Uninflammable resistor
FR	: Fusible resistor

∗ Composition resistor 1/2 [W] is specified as 1/2S or Comp.

(2)Capacitors

● Capacitance value

1 or higher	: [pF]
less than 1	: [μF]

● Withstand voltage

No indication	: DC50[V]
Others	: DC withstand voltage [V]
AC indicated	: AC withstand voltage [V]

∗ Electrolytic Capacitors

47/50[Example]: Capacitance value [μF]/withstand voltage[V]

● Type

No indication	: Ceramic capacitor
MM	: Metalized mylar capacitor
PP	: Polypropylene capacitor
MPP	: Metalized polypropylene capacitor
MF	: Metalized film capacitor
TF	: Thin film capacitor
BP	: Bipolar electrolytic capacitor
TAN	: Tantalum capacitor

(3)Coils

No unit	: [μH]
Others	: As specified

(4)Power Supply

∗ Respective voltage values are indicated

(5)Test point

(6)Connecting method



(7)Ground symbol

⊥ : LIVE side ground

⏚ : ISOLATED(NEUTRAL) side ground

⏚ : EARTH ground

▽ : DIGITAL ground

5.NOTE FOR REPAIRING SERVICE

This model's power circuit is partly different in the GND. The difference of the GND is shown by the LIVE : (⊥) side GND and the ISOLATED(NEUTRAL) : (⏚) side GND. Therefore, care must be taken for the following points.

(1)Do not touch the LIVE side GND or the LIVE side GND and the ISOLATED(NEUTRAL) side GND simultaneously. if the above caution is not respected, an electric shock may be caused. Therefore, make sure that the power cord is surely removed from the receptacle when, for example, the chassis is pulled out.

(2)Do not short between the LIVE side GND and ISOLATED(NEUTRAL) side GND or never measure with a measuring apparatus measure with a measuring apparatus (oscilloscope, etc.) the LIVE side GND and ISOLATED(NEUTRAL) side GND at the same time. If the above precaution is not respected, a fuse or any parts will be broken.

◆ **Since the circuit diagram is a standard one, the circuit and circuit constants may be subject to change for improvement without any notice.**

NOTE

◆ **Due improvement in performance, some part numbers show in the circuit diagram may not agree with those indicated in the part list.**
When ordering parts, please use the numbers that appear in the Parts List.

CONTENTS

SEMICONDUCTOR SHAPES 2-2
BLOCK DIAGRAM 2-3
CIRCUIT DIAGRAMS 2-5
- MAIN PWB CIRCUIT DIAGRAM 2-5
- AV SW PWB CIRCUIT DIAGRAM 2-9
- CRT SOCKET PWB CIRCUIT DIAGRAM 2-11
- FRONT CONTROL PWB CIRCUIT DIAGRAM 2-13
- LED & POWER SW PWB CIRCUIT DIAGRAM 2-15
- USB PWB CIRCUIT DIAGRAM 2-16
- L/F PWB CIRCUIT DIAGRAM 2-17

PATTERN DIAGRAMS 2-19
- MAIN PWB PATTERN 2-19
- AV SW PWB PATTERN 2-21
- CRT SOCKET PWB PATTERN 2-21
- FRONT CONTROL PWB PATTERN 2-22
- LED & POWER SW PWB PATTERN 2-22
- L/F PWB PATTERN 2-23
- USB PWB PATTERN 2-23

VOLTAGE CHARTS 2-25
WAVEFORMS 2-26

USING P.W. BOARD

PWB ASS'Y name	AV-27F577/R	AV-27F577/S	AV-32F577/R	AV-32F577/Y	AV-32F577/Z
MAIN P.W. BOARD	SGJ-1308A-M2	SGJ-1302A-M2	SGJ-1313A-M2	SGJ-1301A-M2	SGJ-1307A-M2
CRT SOCKET P.W. BOARD	SGJ-3304A-M2	SGJ-3302A-M2	SGJ-3305A-M2	SGJ-3301A-M2	SGJ-3303A-M2
AV SW P.W. BOARD	SGJ-5301A-M2	←	←	←	←
FRONT CONTROL P.W. BOARD	SGJ-6301A-M2	←	←	←	←
LED & POWER SW P.W. BOARD	SGJ-7301A-M2	←	←	←	←
USB P.W. BOARD	SGJ-8302A-M2	←	←	←	←
L/F P.W. BOARD	SGJ-9302A-M2	←	SGJ-9301A-M2	←	←

SEMICONDUCTOR SHAPES

TRANSISTOR

BOTTOM VIEW	FRONT VIEW				TOP VIEW
					CHIP TR 

IC

BOTTOM VIEW	FRONT VIEW			TOP VIEW
				

CHIP IC

TOP VIEW		
		

BLOCK DIAGRAM




CRT SOCKET PWB
R/G/B
Q3304~
Q3306
RGB OUT
CRT
VM
Q3103
Q3107~
Q3109
VM AMP
VM COIL
IC601 AUDIO PROCESS
L/R
AGC
SURROUND
TONE
VOLUME
L/R
IC651
AUDIO OUT
SPEAKER L
SPEAKER R
N CPU/CLOSED CAPTION DECODE/
EO PROCESS/RGB PROCESS/
NC. SEP/DEF PROCESS
RGB SW
CUTOFF
DRIVE
R/G/B
OSD R/G/B/Ys/I
GENERATE
MICOM
SDA0
SCL0
IC702
MEMORY
CLOSED
CAPTION
DECODE
SVM_OUT
EW
PROCESS
EW_OUT
EW
Q541~Q543
SIDE PIN OUT
DY01
DEF. YOKE
SYNC.
SEP
VERTICAL
PROCESS
V_OUT
IC421
V OUT
V
HORIZONTAL
PROCESS
H_OUT
Q511
H OUT
H
T502
FBT
FOCUS
SCREEN
B1
MAIN PWB

CIRCUIT DIAGRAMS

MAIN PWB CIRCUIT DIAGRAM (1/2) SHEET1



NOTE : Refer to the part list for the part number of IC702.



MAIN PWB ASS'Y(1/2)
SGJ-1308A-M2 [AV-27F577/R]
SGJ-1302A-M2 [AV-27F577/S]
SGJ-1313A-M2 [AV-32F577/R]
SGJ-1301A-M2 [AV-32F577/Y]
SGJ-1307A-M2 [AV-32F577/Z]

MAIN PWB CIRCUIT DIAGRAM (2/2) SHEET 2



MAIN PWB ASS'Y(2/2)
SGJ-1308A-M2 [AV-27F577/F
SGJ-1302A-M2 [AV-27F577/S
SGJ-1313A-M2 [AV-32F577/F
SGJ-1301A-M2 [AV-32F577/Y
SGJ-1307A-M2 [AV-32F577/Z


PWB (1/2)
EET 1
IC421 LA78041
V. OUT
THERMAL PROTECTION
PUMP UP
AMP
GND
Vcc
CRT SOCKET PWB
CN300A
SHEET 4
CRT SOCKET PWB
SHEET 4
HB
NC
GND
HEATER
NC
B1
HV
FOCUS
SCREEN
TP-91B
X-RAY1
X-RAY2
GND
V. CENTER
SW
SWITCH
SIDEPIN
SIDEPIN_OUT
H. DRIVE
H. OUT
DEF YOKE
7/R]
7/S]
7/R]
7/Y]
7/Z]

AV SW PWB CIRCUIT DIAGRAM SHEET 3



AV SW PWB ASS'Y
SGJ-5301A-M2



MAIN PWB(1/2)
CN002
SHEET 1

	AV-27MF47RA AV-27MF47SA AV-32MF47RA AV-32MF47ZA AV-32MF47YA AV-27F5779A AV-32F5779A AV-32F5777A AV-32F5771A	AV-32MF47RA AV-32MF47ZA AV-32MF47YA
	SGJ-5301A	SGJ-5302A
J5005	OPEN	QNN0349 -002
R5007	33k	OPEN
R5008	22k	2.2k
R5015	33k	OPEN
R5016	22k	2.2k
R5023	33k	OPEN
R5024	22k	2.2k
IC5002	OPEN	M52055FP-X
R5067	OPEN	75
R5068	OPEN	75
R5069	OPEN	75
R5070	OPEN	100
R5071	OPEN	100
R5072	OPEN	100
R5073	OPEN	100
R5074	OPEN	100
R5075	OPEN	100
R5076	0	OPEN
R5077	0	OPEN
R5078	0	OPEN
C5038	OPEN	10/50
C5039	OPEN	10/50
C5040	OPEN	10/50
C5042	OPEN	47/16
C5043	OPEN	.01
D5014	OPEN	*6
D5015	OPEN	*6
D5016	OPEN	*6

NOTE
0: NRSA63J-0R0X
*1: 2SC3928A/QR/-X
*2: 2SA1530A/QR/-X
*5: MTZJ5.1C-T2
*8: DTC323TK-X
BW: QUY153-050Y

CRT SOCKET PWB CIRCUIT DIAGRAM SHEET 4





CRT SOCKET PWB ASS'Y
SGJ-3304A-M2 [AV-27F577/R]
SGJ-3302A-M2 [AV-27F577/S]
SGJ-3305A-M2 [AV-32F577/R]
SGJ-3301A-M2 [AV-32F577/Y]
SGJ-3303 A-M2 [AV-32F577/Z]

	AV-32MF47YA AV-32MF47YA AV-32F577YA	AV-32MF47ZA AV-32MF47ZA AV-32F577ZA	AV-32MF47RA AV-32MF47RA AV-32F577RA	AV-27MF47SA AV-27F577SA	AV-27MF47RA AV-27F577RA
	SGJ-3301A	SGJ-3303A	SGJ-3305A	SGJ-3302A	SGJ-3304A
V01	A80AKS 90X03	A80ERF 182X17L	A80ALB 20X09	A68QCP 693X003	A68ELH 021X201
CN300E	QJB003 -074022-E	QJB003 -074022-E	QJB003 -074022-E	QJB003 -073226-E	QJB003 -073226-E
CN30E2	QUB130 -46A6AS-E	QUB130 -46A6AS-E	QUB130 -46A6AS-E	QUB130 -38A6AS-E	QUB130 -38A6AS-E
CN300A	WJA0029- 002A-E	WJA0029- 002A-E	WJA0029- 002A-E	WJA0029- 001A-E	WJA0029- 001A-E
C3323	QETN1CM -477Z	QETN1CM -477Z	QETN1CM -477Z	QETN1CM -107Z	QETN1CM -107Z
C3351	QETN1CM -227Z	QETN1CM -227Z	QETN1CM -227Z	QETN1CM -477Z	QETN1CM -477Z
R3351	150	150	150	820	820
R3354	560	560	560	1k	1k
R3355	10k	10k	10k	OPEN	OPEN



NOTE

BW : QUY153-050Y
BW15 : QUY160-150Y
*1 : 2SA1530A/QR/-X
*2 : 2SC3928A/QR/-X
*3 : UN2112-X
*4 : UN2212-X
*5 : 1SS133-T2

FRONT CONTROL PWB CIRCUIT DIAGRAM SHEET 5




Y6401 OPEN
C6401
10/50
LC6401
QQR1459-001
R6401
75
J6401
QNN0706-001
V
Y6402 OPEN
C6402
2.2 /50
R6402
220k
LC6402
QQR1459-001
Y6403
OPEN
Y6404
OPEN
J6402
QNN0706-002
L
C6403
2.2 /50
R6403
220k
LC6403
QQR1459-001
Y6405
OPEN
Y6406
OPEN
J6403
QNN0707-003
R
MENU
CH−
S6702
QSW0619-003Z
S6703
QSW0619-003Z
R6701
2.7k
R6702
5.6k
CH+
VOL−
VOL+
S6704
QSW0619-003Z
S6705
QSW0619-003Z
S6706
QSW0619-003Z
R6703
2.7k
R6704
5.6k

LED & POWER SW PWB CIRCUIT DIAGRAM SHEET 6



USB PWB CIRCUIT DIAGRAM SHEET 7





NOTE

BW: QUY153-050Y


WB ASS'Y
9302A-M2 [AV-27F577/R, AV-27F577/S]
9301A-M2 [AV-32F577/R, AV-32F577/Y, AV-32F577/Z]
R999
120 1/2W
QRE121J-121Y
C997
AC120V
QCZ9079-102
T951
QQT0355-001
1 AC_PULSE1
2 AC_PULSE2
3 GND
MAIN PWB(2/2)
CN00F
SHEET 2
CN900F
QGA2501C5-03Z
Y904
OPEN
Y903
OPEN
LF902
QQR0527-003
C903
QFZ9072-104
or QFZ9075-104
Y902
OPEN
Y901
OPEN
2 AC_OUT
1 AC_OUT
MAIN PWB(2/2)
CN00W
SHEET 2
CN900W
QGA7901C1-02

PATTERN DIAGRAMS

MAIN PWB PATTERN

FRONT



CAUTION :
FOR CONTINUED PROTECTION AGAINST FIRE HAZARD,
REPLACE ONLY WITH SAME TYPE AND RATED FUSE(S)
AND ROHM'S MFR'S TYPE CP(S).



AV SW PWB PATTERN



CRT SOCKET PWB PATTERN



FRONT CONTROL PWB PATTERN



LED & POWER SW PWB PATTERN



L/F PWB PATTERN

FRONT



USB PWB PATTERN

FRONT




-001A
LF PWB
E3
PW
2
1

VOLTAGE CHARTS

<MAIN PWB>
[P.2-13-P.2-14]

MODE PIN NO.	DC (V)
IC101	
1	5
2	0
3	4
4	3.9
5	NC
6	NC
7	NC
8	4
9	3.9
10	0
11	4.3
12	4
13	0
14	1.2
15	1.2
16	NC
17	0
18	3.2
19	NC
20	8.9
21	NC
22	4
23	4
24	2.1
25	3.9
26	NC
27	0
28	4
29	NC
30	NC
31	NC
32	4
33	2
34	4
35	4
36	2
37	3.9
38	NC
39	4
40	NC
41	4
42	4
43	0
44	4
45	4
46	4
47	4
48	5
IC201	
1	0
2	5
3	5
4	0
5	5
6	2.2
7	2
8	0
9	5.1
10	0.1
11	0
12	0
13	1.2
14	1.9
15	8.9
16	6.5
17	3.5
18	4.2
19	3.9
20	0
21	0
22	2.1
23	2.3
24	2.2
25	3.5
26	2.1
27	3.1
28	2.2
29	0
30	2.2
31	6.2
32	0
33	1.9
34	3.5
35	1.6
36	2.5
37	2.9
38	4.8
39	1.7
40	1.6
41	1.8
42	8.9
43	4.4
44	0
45	0
46	5
47	0

MODE PIN NO.	DC (V)
48	0
49	5
50	5
51	5
52	0.1
53	5
54	1.9
55	5
56	0
IC601	
1	4.4
2	NC
3	4.5
4	NC
5	4.5
6	4.5
7	1
8	0.5
9	4.5
10	0
11	0
12	5
13	NC
14	5
15	NC
16	0
17	8.9
18	NC
19	4.4
20	NC
21	NC
22	NC
23	3.1
24	3.1
25	3.1
26	4.5
27	4.5
28	4.5
29	NC
30	4.5
31	NC
32	4.4
IC651	
1	13.5
2	0
3	0
4	0
5	7.8
6	1.1
7	14.1
8	6.6
9	6.5
10	0
11	6.6
12	6.6
13	NC
IC702	
1	0
2	0
3	0
4	0
5	5
6	5
7	0
8	5
IC703	
1	5
2	5
3	NC
4	0
IC704	
1	5
2	0
3	10.4
IC851	
1	15.3
2	3.4
3	0
4	1.2
5	6.7
IC852	
1	15.4
2	0
3	8.9
IC853	
1	7.6
2	4.9
3	0
4	7.6
IC855	
1	3.2
2	2.6
3	0
4	1.2
IC856	
1	6.3
2	7.7

MODE PIN NO.	DC (V)
3	1.3
4	0
5	0.6
6	1.2
7	5.9
8	0.9
Q001	
S	3.2
D	5
G	3.3
Q002	
S	3.2
D	5
G	3.3
Q003	
S	3.3
D	5
G	3.3
Q004	
S	3.3
D	5
G	3.3
Q005	
E	0
C	0
B	3.2
Q352	
E	8.4
C	8.9
B	9
Q671	
E	0
C	7.8
B	0
Q681	
E	0
C	0
B	-0.7
Q682	
E	9.9
C	-0.8
B	10.3
Q683	
E	0
C	0
B	0.1
Q684	
E	0
C	0
B	0.6
Q701	
E	3.7
C	2.5
B	3
Q730	
E	0
C	1.8
B	3.8
CN001	
1	0
2	32
3	4.9
4	4.9
5	4.9
6	0
7	0
8	0
9	0
10	0
11	0
12	0.2
13	2.5
14	4.9
15	8.9
16	8.9
17	0
18	0
19	0
20	3.3
21	3.2
22	3.2
23	3.2
24	3.2
25	0
26	0
27	3.3
28	3.3
29	1.2
30	1.2
31	1.2
32	1.2
33	2.6
34	2.6
35	2.6
36	0
37	0
38	0

MODE PIN NO.	DC (V)
39	0
40	0
41	3.4
42	3.4
43	3.4
44	2.4
45	2.3
46	2.7
47	0
48	0
49	0
50	1.5
51	1.8
52	1.8
53	2.5
54	4.9
55	8.9
56	0
57	0
58	0
59	0
60	3.2
61	0
62	0
63	0
64	0
65	0
66	0
67	3.2
68	3.3
69	1.2
70	1.2
71	1.2
72	1.2
73	2.6
74	2.6
75	2.6
76	0
77	0
78	0
79	0
80	0

[P.2-15-P.2-16]

MODE PIN NO.	DC (V)
IC421	
1	2.6
2	27.6
3	2.6
4	0
5	15
6	28.1
7	2.7
IC911	
1	129.8
2	0.1
3	0
4	18.3
5	1.7
IC921	
1	134.6
2	12.9
3	0
Q501	
E	0
C	64.3
B	0.3
Q511	
E	0
C	133.8
B	0.1
Q531	
E	0
C	9.9
B	0
Q532	
E	9.9
C	0
B	9.9
Q541	
E	4.5
C	0.5
B	3.9
Q542	
E	4.5
C	0
B	3.9
Q543	
E	0
C	14.3
B	0.6
Q951	
E	0
C	0.1
B	1.4
Q971	
E	134.6
C	0.1
B	134.2
PC921	
1	14
2	12.9
3	1.7
4	16.6

<AV SW PWB>
[P.2-17-P.2-18]

MODE PIN NO.	DC (V)
IC5001	
1	3.9
2	4.4
3	3.9
4	4.4
5	4.4
6	0
7	NC
8	3.9
9	4.4
10	0
11	0
12	4.4
13	0
14	4.8
15	3.9
16	4.4
17	3.9
18	4.4
19	4.4
20	0
21	NC
22	4.4
23	3.9
24	4.4
25	0
26	5
27	5
28	4.4
29	0
30	4.5
31	0
32	4.4
33	3.5
34	8.9
35	0
36	3.9
37	4.4
38	4.4
39	4.5
40	NC
41	4.4
42	NC
43	NC
44	0
45	NC
46	4.4
47	3.9
48	4.4
Q5001	
E	2.8
C	8.9
B	3.4
Q5002	
E	2.8
C	8.9
B	3.4
Q5003	
E	2.8
C	8.9
B	3.4
Q5004	
E	2.7
C	0
B	0
Q5005	
E	2.3
C	0
B	1.7
Q5006	
E	2.4
C	0
B	1.7
Q5007	
E	3.4
C	0
B	2.8
Q5008	
E	3.4
C	0
B	2.8
Q5009	
E	3.4
C	0
B	2.8
Q5601	
E	0
C	0
B	-0.4
Q5602	
E	0
C	0
B	-0.4
Q5603	
E	0.1
C	-0.4
B	0

<CRT SOCKET PWB>
[P.2-19-P.2-20]

MODE PIN NO.	DC (V)
Q3103	
E	3.3
C	11.9
B	0
Q3107	
E	132.6
C	69.9
B	132.2
Q3108	
E	4.5
C	69.5
B	5.1
Q3109	
E	2.2
C	4.1
B	2.8
Q3304	
E	1.5
C	160.5
B	2
Q3305	
E	1.6
C	159.8
B	2
Q3306	
E	1.6
C	156
B	2.1
Q3351	
E	11.8
C	-1
B	11.9

<LED & POWER SW PWB>
[P.2-23]

MODE PIN NO.	DC (V)
IC7701	
1	5
2	5
3	0
Q7701	
E	5
C	5
B	0.2

<USB PWB>
[P.2-24]

MODE PIN NO.	DC (V)
IC8501	
1	0.1
2	4.9
3	0

WAVEFORMS

MAIN PWB(1/2)

IC201-6



5 Vp-p

IC201-13



6 Vp-p

IC201-14



5 Vp-p

IC201-18



2.9 Vp-p

IC201-19



1.2 Vp-p

IC201-22



0.7 Vp-p

IC201-23



1 Vp-p

IC201-24



0.6 Vp-p

IC201-39



3 Vp-p

IC201-40



2.5 Vp-p

IC201-41



3.5 Vp-p

MAIN PWB(2/2)

IC421-1



0.7 Vp-p

IC421-3



32 Vp-p

IC421-5



60 Vp-p

IC421-6



35 Vp-p

Q501-B



0.8 Vp-p

Q501-C



120 Vp-p

Q511-B



2.3 Vp-p

Q511-C



1100 Vp-p

Q543-B



0.08 Vp-p

Q543-C



10 Vp-p

T502-2

90 Vp-p

T502-4



30 Vp-p

T502-6



250 Vp-p

T502-8

75 Vp-p

CRT SOCKET PWB

Q3304-C



105 Vp-p

Q3305-C



95 Vp-p

Q3306-C



120 Vp-p

JVC
Victor Company of Japan, Limited
CRT Display Category 12, 3-chome, Moriya-cho, kanagawa-ku, Yokohama-city, kanagawa-prefecture, 221-8528, Japan

(No.YA387)

Printed in Japan
VPT